

***Revised Generation Interconnection
Feasibility Study Report***

For

***PJM Generation Interconnection Request
Queue Position AD1-052***

Fremont Energy Center

February 2018

Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

General

the Interconnection Customer (IC), has proposed an uprate to an existing natural gas generating facility located in Sandusky County, Ohio. This projects requests an increase to the install capability of 38 MW with 26.3 MW of this output being recognized by PJM as capacity. The installed facilities will have a total capability of 745 MW with 703 MW of this output being recognized by PJM as capacity. The proposed in-service date for this project is October 1, 2019. **This study does not imply a ATSI commitment to this in-service date.**

Point of Interconnection

AD1-052 will interconnect with the ATSI transmission system along the West Fremont 138kV substation.

Cost Summary

The AD1-052 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$ 0
Direct Connection Network Upgrades	\$ 0
Non Direct Connection Network Upgrades	\$ 0
Total Costs	\$ 0

In addition, the AD1-052 project may be responsible for a contribution to the following costs:

Description	Total Cost
New System Upgrades	\$ 0
Previously Identified Upgrades	\$ 0
Total Costs	\$ 0

Cost allocations for these upgrades will be provided in the System Impact Study Report.

Attachment Facilities

No Attachment Facilities are required to support this interconnection request.

Direct Connection Cost Estimate

No Direct Connection Facilities are required to support this interconnection request.

Non-Direct Connection Cost Estimate

No Non-Direct Connection Facilities are required to support this interconnection request.

Transmission Owner Scope of Work

Because AD1-052 is an increase to an existing facility, no new interconnection facilities are required to accommodate the increased output. A one-line of the interconnection is shown in the Attachments.

Interconnection Customer Requirements

1. An Interconnection Customer entering the New Services Queue on or after October 1, 2012 with a proposed new Customer Facility that has a Maximum Facility Output equal to or greater than 100 MW shall install and maintain, at its expense, phasor measurement units (PMUs). See Section 8.5.3 of Appendix 2 to the Interconnection Service Agreement as well as section 4.3 of PJM Manual 14D for additional information.
2. The Interconnection Customer may be required to install and/or pay for metering as necessary to properly track real time output of the facility as well as installing metering which shall be used for billing purposes. See Section 8 of Appendix 2 to the Interconnection Service Agreement as well as Section 4 of PJM Manual 14D for additional information.
3. The Interconnection Customer seeking to interconnect a wind generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per item 5.iv. of Schedule H to the Interconnection Service Agreement.
4. The increase of 38 MW to the Interconnection Customer's facility proposed for project AD1-052 shall be designed with the ability to maintain a power factor of at least 1.0 (unity) to 0.90 lagging measured at the generator's terminals.

Revenue Metering and SCADA Requirements

PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Sections 24.1 and 24.2.

ATSI Requirements

The Interconnection Customer will be required to comply with all FE Revenue Metering Requirements for Generation Interconnection Customers. The Revenue Metering Requirements may be found within the "FirstEnergy Requirements for Transmission Connected Facilities" document located at the following links:

<http://www.firstenergycorp.com/feconnect>

<http://www.pjm.com/planning/design-engineering/to-tech-standards.aspx>

Network Impacts

The Queue Project AD1-052 was evaluated as a 38.0 MW (Capacity 26.3 MW) injection at both Fremont Energy Center CT#1 and Fremont Energy Center CT#2 in the ATSI area. Project AD1-052 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AD1-052 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Analysis - 2021

Generator Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None.

Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None.

Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None.

Short Circuit

(Summary of impacted circuit breakers)

None.

Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None.

New System Reinforcements

(Upgrades required to mitigate reliability criteria violations, i.e. Network Impacts, initially caused by the addition of this project generation)

None.

Contribution to Previously Identified System Reinforcements

(Overloads initially caused by prior Queue positions with additional contribution to overloading by this project. This project may have a % allocation cost responsibility which will be calculated and reported for the Impact Study)

None.

Affected System Analysis & Mitigation

MISO Impacts:

MISO Impacts to be determined during later study phases (as applicable).

Stability and Reactive Power Requirement

(Results of the dynamic studies should be inserted here)

To be determined

Steady-State Voltage Requirements

(Results of the steady-state voltage studies should be inserted here)

To be determined

Light Load Analysis - 2021

Light Load Studies to be conducted during later study phases (as required by PJM Manual 14B)