



**Generation Interconnection
Feasibility Study Report
for
Queue Project AE2-252
GARDNERS-MOUNTAIN 115 KV
12 MW Capacity / 20 MW Energy**

July, 2019

Table of Contents

1	Preface.....	3
2	General.....	5
2.1	Point of Interconnection	6
2.2	Cost Summary.....	6
3	Transmission Owner Scope of Work.....	8
4	Attachment Facilities	8
5	Direct Connection Cost Estimate.....	9
6	Non-Direct Connection Cost Estimate.....	10
7	Incremental Capacity Transfer Rights (ICTRs)	Error! Bookmark not defined.
8	Schedule.....	11
9	Transmission Owner Analysis.....	12
10	Interconnection Customer Requirements.....	13
11	Revenue Metering and SCADA Requirements	15
11.1	PJM Requirements	15
11.2	ME Requirements.....	15
12	Network Impacts	16
13	Generation Deliverability	18
14	Multiple Facility Contingency.....	18
15	Contribution to Previously Identified Overloads	18
16	Potential Congestion due to Local Energy Deliverability.....	18
17	System Reinforcements	19
18	Flow Gate Details	20
19	Affected Systems.....	22
19.1	LG&E.....	22
19.2	MISO	22
19.3	TVA.....	22
19.4	Duke Energy Progress.....	22
19.5	NYISO	22
20	Short Circuit.....	24

1 Introduction

This Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Metropolitan Edison (MetEd).

2 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model.

The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

3 General

The Interconnection Customer (IC), has proposed a Solar generating facility located in Cumberland County, Pennsylvania. The installed facilities will have a total capability of 20 MW with 12 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is 11/9/2021. This study does not imply a TO commitment to this in-service date.

Queue Number	AE2-252
Project Name	GARDNERS-MOUNTAIN 115 KV
Interconnection Customer	
State	Pennsylvania
County	Cumberland
Transmission Owner	ME
MFO	20
MWE	20
MWC	12
Fuel	Solar
Basecase Study Year	2022

3.1 Point of Interconnection

3.1.1 Primary POI

The interconnection of the project at the Primary POI will be accomplished by constructing a new 115 kV three (3) breaker ring bus substation and looping the Gardners - Mountain 115 kV line into the new station. The new substation will be located approximately 5.0 miles from Gardners substation. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct both the new interconnection switching station and the associated facilities. The IC will also be responsible for the rough grade of the property and an access road to the proposed three breaker ring bus site. The project will also require non-direct connection upgrades at Gardners and Mountain substations.

Attachment 1 shows a one-line diagram of the proposed primary direct connection facilities for the AE2-252 generation project to connect to the FirstEnergy (“FE”) transmission system. Attachment 2 provides the proposed location for the point of interconnection. IC will be responsible for constructing all of the facilities on its side of the POI, including the attachment facilities which connect the generator to the FE transmission system’s direct connection facilities.

3.2 Cost Summary

The AE2-252 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$ 516,580
Direct Connection Network Upgrade	\$ 4,649,220
Non Direct Connection Network Upgrades	\$ 445,100
Total Costs	\$ 5,610,900

In addition, the AE2-252 project may be responsible for a contribution to the following costs

Description	Total Cost
System Upgrades	\$ 0

Cost allocations for these upgrades will be provided in the System Impact Study Report.

The costs provided above exclude the Contribution in Aid of Construction (“CIAC”) Federal Income Tax Gross Up charge. If, at a future date, it is determined that the CIAC Federal Income Tax Gross charge is required, the Transmission Owner shall be reimbursed by the Interconnection Customer for such taxes.

The Feasibility Study is used to make a preliminary determination of the type and scope of Attachment Facilities, Local Upgrades, and Network Upgrades that will be necessary to accommodate the Interconnection Request and to provide the Interconnection Customer a preliminary estimate of the time that will be required

to construct any necessary facilities and upgrades and the Interconnection Customer's cost responsibility. The System Impact Study provides refined and comprehensive estimates of cost responsibility and construction lead times for new facilities and system upgrades. Facilities Studies will include, commensurate with the degree of engineering specificity as provided in the Facilities Study Agreement, good faith estimates of the cost, determined in accordance with Section 217 of the Tariff,

- (a) to be charged to each affected New Service Customer for the Facilities and System Upgrades that are necessary to accommodate this queue project;
- (b) the time required to complete detailed design and construction of the facilities and upgrades; and
- (c) a description of any site-specific environmental issues or requirements that could reasonably be anticipated to affect the cost or time required to complete construction of such facilities and upgrades.

The required Attachment Facilities and Direct and Non-Direct Connection work for the interconnection of the AE2-252 generation project to the FE Transmission System is detailed in the following sections. The associated one-line with the generation project Attachment Facilities and the Primary Direct and Non-Direct Connection facilities are shown in Attachment 1.

4 Transmission Owner Scope of Work

The interconnection of the project at the Primary POI will be accomplished by constructing a new 115 kV three (3) breaker ring bus substation and looping the Gardners - Mountain 115 kV line into the new station. The new substation will be located approximately 5.0 miles from Gardners substation. Attachment Facilities

The total preliminary cost estimate for the Attachment work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Install line exit take-off structure, foundations, disconnect switch and associated equipment at ring bus substation	\$ 516,580
Total Attachment Facility Costs	\$ 516,580

5 Direct Connection Cost Estimate

The total preliminary cost estimate for the Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Build new (3) breaker 115 kV ring bus ~3.5 miles from Mountain substation the Interconnection Customer	\$ 4,649,220
Total Direct Connection Facility Costs	\$ 4,649,220

6 Non-Direct Connection Cost Estimate

The total preliminary cost estimate for the Non-Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Replace Line relaying for existing Mountain 115kV line exit and rename due to AE2-252 developer interconnection at Gardners substation.	\$ 224,400
Replace Line relaying for existing Gardners 115kV line exit and rename due to AE2-252 developer interconnection at Mountain substation	\$ 220,700
Total Non-Direct Connection Facility Costs	\$ 445,100

7 Schedule

Based on the scope of work for the Attachment Facilities and the Direct and Non-Direct Connection facilities, it is expected to take a minimum of 18 months after the signing of an Interconnection Construction Service Agreement to complete the installation. This includes the requirement for the IC to make a preliminary payment that compensates FE for the first three months of the engineering design work that is related to the construction of the interconnection substation. This assumes that there will be no environmental issues with any of the new properties associated with this project, that there will be no delays in acquiring the necessary permits for implementing the defined direct connection and network upgrades, and that all transmission system outages will be allowed when requested.

The schedule for the required Network Impact Reinforcements will be more clearly identified in future study phases. The estimated time to complete each of the required reinforcements is identified in the “System Reinforcements” section of the report.

8 Transmission Owner Analysis

8.1 Power Flow Analysis

FE performed an analysis of its underlying transmission <100 kV system. The AE2-252 project did not contribute to any overloads on the FE transmission system.

9 Interconnection Customer Requirements

9.1 System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in FE's "Requirements for Transmission Connected Facilities" document located at:

<http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>.

Preliminary Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

9.2 Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. In particular, the IC is responsible for the following:

1. The purchase and installation of a fully rated 115 kV circuit breaker to protect the AE2-252 generator lead line. A single circuit breaker must be used to protect this line; if the project has several GSU transformers, the individual GSU transformer breakers cannot be used to protect this line.
2. The purchase and installation of the minimum required FE generation interconnection relaying and control facilities. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.
3. The purchase and installation of supervisory control and data acquisition ("SCADA") equipment to provide information in a compatible format to the FE Transmission System Control Center.
4. Compliance with the FE and PJM generator power factor and voltage control requirements.
5. The execution of a back-up service agreement to serve the customer load supplied from the AE2-252 generation project metering point when the units are out-of-service. This assumes the intent of the IC is to net the generation with the load.

The IC will also be required to meet all PJM, ReliabilityFirst, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the submission of the generator model and protection data required to satisfy the PJM and ReliabilityFirst audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the FE system.

9.3 Power Factor Requirements

The IC shall design its solar-powered non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the FE transmission system.

10 Revenue Metering and SCADA Requirements

10.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

10.2 FE Requirements

The IC will be required to comply with all FE revenue metering requirements for generation interconnection customers which can be found in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>

11 Network Impacts

The Queue Project AE2-252 was evaluated as a 20 MW (Capacity 12 MW) injection tapping the Gardners to Mountain 115kV in the MetEd area. Project AE2-252 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-252 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

12 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

13 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

14 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

15 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
7284035	204539	27HUNTRSTN	METED	933970	AD1-020 TAP	METED	1	ME-P1-2-ME-115-022-A	operation	160.0	99.38	99.88	DC	1.76
7283784	204543	27LINC TAP	METED	204544	27LINCOLN	METED	1	ME-P1-2-ME-115-016-A	operation	152.0	115.97	116.48	DC	1.71
7284021	933970	AD1-020 TAP	METED	204544	27LINCOLN	METED	1	ME-P1-2-ME-115-022-A	operation	160.0	99.85	100.34	DC	1.76

16 System Reinforcements

None

17 Flow Gate Details

The following appendices contain additional information about each flowgate presented in the body of the report. For each appendix, a description of the flowgate and its contingency was included for convenience. However, the intent of the appendix section is to provide more information on which projects/generators have contributions to the flowgate in question. Although this information is not used "as is" for cost allocation purposes, it can be used to gauge other generators impact. It should be noted the generator contributions presented in the appendices sections are full contributions, whereas in the body of the report, those contributions take into consideration the commercial probability of each project.

17.1 Contingency Descriptions

Contingency Name	Contingency Definition
ME-P1-2-ME-115-016-A	CONTINGENCY 'ME-P1-2-ME-115-016-A' /* HUNTERSTOWN - LINCOLN 115 KV DISCONNECT BRANCH FROM BUS 204539 TO BUS 933970 CKT 1 /* 27HUNTRSTN 115 AD1-020 TAP 115 END
ME-P1-2-ME-115-022-A	CONTINGENCY 'ME-P1-2-ME-115-022-A' /* LINCOLN JUNCTION 115 KV LINES DISCONNECT BRANCH FROM BUS 204543 TO BUS 204539 CKT 1 /* 27LINC TAP 115 27HUNTRSTN 115 DISCONNECT BRANCH FROM BUS 204543 TO BUS 204544 CKT 1 /* 27LINC TAP 115 27LINCOLN 115 DISCONNECT BRANCH FROM BUS 204543 TO BUS 939100 CKT 1 /* 27LINC TAP 115 AE1-139 TAP 115 DISCONNECT BUS 204543 /* 27LINC TAP 115 END

Affected Systems

18 Affected Systems

18.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

18.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

18.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

18.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

18.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

Short Circuit

19 Short Circuit

The following Breakers are overduty: None

Attachment 1 – One Line

Attachment 2 – Project Location