



**Generation Interconnection  
Feasibility Study Report  
for**

**Queue Project AF2-121**

**PHILIPSBURG-SHAWVILLE 34.5 KV**

**12 MW Capacity / 20 MW Energy**

July 2020

# Table of Contents

1	Introduction.....	4
2	Preface.....	4
3	General.....	5
4	Point of Interconnection.....	6
5	Cost Summary.....	6
6	Transmission Owner Scope of Work.....	7
7	Schedule.....	8
8	Transmission Owner Analysis.....	8
9	Interconnection Customer Requirements.....	8
9.1	System Protection.....	8
9.2	General Concerns.....	9
9.3	Requirements for IC’s Facility.....	9
9.4	Compliance Issues.....	9
10	Revenue Metering and SCADA Requirements.....	10
10.1	PJM Requirements.....	10
10.2	Meteorological Data Reporting Requirements.....	10
10.3	Interconnected Transmission Owner Requirements.....	10
11	Summer Peak - Load Flow Analysis.....	11
11.1	Generation Deliverability.....	12
11.2	Multiple Facility Contingency.....	12
11.3	Contribution to Previously Identified Overloads.....	12
11.4	Potential Congestion due to Local Energy Deliverability.....	14
11.5	System Reinforcements - Summer Peak Load Flow - Primary POI.....	16
11.6	Flow Gate Details.....	19
11.6.1	Index 1.....	20
11.6.2	Index 2.....	22
11.6.3	Index 3.....	24
11.6.4	Index 4.....	26
11.6.5	Index 5.....	28
11.6.6	Index 6.....	30
11.6.7	Index 7.....	32

11.6.8 Index 8 .....34

11.7 Queue Dependencies .....36

11.8 Contingency Descriptions.....38

12 Short Circuit Analysis.....40

13 Affected Systems .....41

13.1 NYISO .....41

14 Attachment 1: One Line Diagram .....42

## 1 Introduction

This Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Mid-Atlantic Interstate Transmission, LLC (MAIT) (PENELEC zone).

## 2 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

### 3 General

The Interconnection Customer (IC), has proposed a Solar generating facility located in Clearfield County, Pennsylvania. The installed facilities will have a total capability of 20 MW with 12 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is June 01, 2021. This study does not imply a TO commitment to this in-service date.

<b>Queue Number</b>	<b>AF2-121</b>
<b>Project Name</b>	PHILIPSBURG-SHAWVILLE 34.5 KV
<b>State</b>	Pennsylvania
<b>County</b>	Clearfield
<b>Transmission Owner</b>	MAIT (PENELEC zone)
<b>MFO</b>	20
<b>MWE</b>	20
<b>MWC</b>	12
<b>Fuel</b>	Solar
<b>Basecase Study Year</b>	2023

Any new service customers who can feasibly be commercially operable prior to June 1st of the basecase study year are required to request interim deliverability analysis.

## 4 Point of Interconnection

AF2-121 will interconnect with the PENELEC distribution system at POI pole SBF-22022, which is located on the 34.5kV Shawville ckt#00154-22 @ Philipsburg substation.

Attachment 1 shows a one-line diagram of the proposed primary direct connection facilities for the AF2-121 generation project to connect to the Penelec distribution system. IC will be responsible for constructing all of the facilities on its side of the POI, including the attachment facilities which connect the generator to the Penelec distribution system's direct connection facilities.

## 5 Cost Summary

The AF2-121 project will be responsible for the following costs:

Description	Total Cost
<b>Total Physical Interconnection Costs</b>	\$139,600
<b>Total Local System Upgrade Costs</b>	\$1,535,938
<b>Total System Network Upgrade Costs</b>	\$81,939,828 <sup>12</sup>
<b>Total Costs</b>	\$83,615,366

This cost excludes a Federal Income Tax Gross Up charges. This tax may or may not be charged based on whether this project meets the eligibility requirements of IRS Notice 88-129. If at a future date it is determined that the Federal Income Tax Gross charge is required, the Transmission Owner shall be reimbursed by the Interconnection Customer for such taxes.

Cost allocations for any System Upgrades will be provided in the System Impact Study Report.

---

<sup>1</sup> This project currently contributes to overloads of the Transmission System (see Summer Peak Load Flow Analysis section below) and therefore has potential to have cost allocation for the system reinforcements listed in the report. This will be re-evaluated in the System Impact phase. The results may vary with queue customers withdrawing from the queue and other generators deactivating over time. If a customer is the first to cause the need for a project (causes loading to exceed 100% of rating), then the customer is responsible. If a customer's MW contribution to a facility that is already overloaded by a prior queue is less than 5 MW, then they will not receive cost allocation.

<sup>2</sup> It should be noted that some of the contingencies taken in the analysis may not be valid due to system condition changes that were not captured in the model. This will be re-evaluated for validity in the System Impact phase.

## 6 Transmission Owner Scope of Work

AF2-121 will interconnect with the PENELEC distribution system at POI pole SBF-22022, which is located on the 34.5kV Shawville ckt#00154-22 @ Philipsburg substation.

Attachment 1 shows a one-line diagram of the proposed primary direct connection facilities for the AF2-121 generation project to connect to the Penelec distribution system. IC will be responsible for constructing all of the facilities on its side of the POI, including the attachment facilities which connect the generator to the Penelec distribution system's direct connection facilities.

The total physical interconnection costs is given in the table below:

<b>Description</b>	<b>Total Cost</b>
Tap the existing 34.5kV Shawville ckt#00154-22 @ Philipsburg at POI pole SBF-22022 and install a SCADA controlled 34.5kV recloser to interconnect queue project AF2-121. Install 34.5kV metering in customer's facilities. The customer is responsible to build their own line from their site to Penelec's existing facilities	\$ 100,000
Nameplates & Customer Drawing Review @ AF2-121	\$25,200
Philipsburg 34.5kV SS. Adjust Remote Relay and Metering Settings.	\$14,400
<b>Total Physical Interconnection Costs</b>	<b>\$139,600</b>

## 7 Schedule

Based on the scope of work for the interconnection facilities, it is expected to take a minimum of **15 months** after the signing of an Interconnection Construction Service Agreement and construction kickoff call to complete the installation. This assumes that there will be no environmental issues with any of the new properties associated with this project, that there will be no delays in acquiring the necessary permits for implementing the defined direct connection and network upgrades, and that all transmission system outages will be allowed when requested.

If the customer is ultimately responsible for network upgrades, then the schedule for those upgrades will be refined in future study phases. The customer would need to wait for those upgrades to be completed prior to commercial operation unless determined deliverable by an interim deliverability study. The elapsed time to complete any network upgrades is provided in the System Reinforcements table of this report<sup>1</sup>.

## 8 Transmission Owner Analysis

Penelec performed an analysis of its distribution system. The AF2-121 project did contribute overloads on the distribution system requiring the reconductoring of approximately 6.2 miles of three-phase mainline conductor.

Description	Total Cost
Re-conductor multiple spans of undersized three-phase main-line conductor for a total distance of 32,439 feet.	\$1,535,938
<b>Total Local System Upgrades</b>	<b>\$1,535,938</b>

## 9 Interconnection Customer Requirements

### 9.1 System Protection

An analysis was conducted to assess the impact of the Philipsburg-Shawville 34.5kV (AF2-121) Project on the system protection requirements in the area. The results of this review show that the following relay additions will be required:

Proposed single line diagrams show IC constructing a generation facility that will connect to Penelec's 34.5kV Philipsburg substation ckt#00154-22 via a customer owned tap to pole SBF-22022.

The 34.5kV interconnection proposal will require Developer to meet applicable "Technical Requirements" as outlined in First Energy's document titled "Technical Requirements for the Interconnection of Customer-Owned Generation to the FirstEnergy Distribution System".

Protection requirements are included in the "Technical Requirements" document.

## 9.2 General Concerns

It is to be understood, for abnormal operation of the Penelec system, which could cause Developer's generation facility to be electrically isolated from the Penelec system synchronous source via the tripping of an interconnecting primary voltage line or device, Developer will, via Penelec's direction, be required to disconnect the generation from Penelec's system and remain disconnected (units are required to be OFF LINE), until the Penelec system normal circuitry is restored. These abnormal conditions will be reviewed by Penelec system operators as to the need for the generation facility to be disconnected.

## 9.3 Requirements for IC's Facility

The proposed interconnection Owner's/Developer's facilities must be designed in accordance with the document titled FirstEnergy Distribution Engineering Practices Interconnection of Customer-Owned Generation to the FirstEnergy Distribution System dated 11/17/14 located at the following link:

<http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>

The document is referred to as engineering practice EP (# 02-280) with section 4 part C specifically referencing the "interconnection technical requirements". Certain protection requirements are shown.

Additionally, Owner/Developer is responsible to provide adequate protection (for their equipment) under any distribution system operating condition' - which includes 'Separation from supply' (i.e. tripping of F.E. circuit breakers) and 'Re-synchronizing the generation after electric restoration of the supply' (i.e. reclosing of F.E. circuit breakers).

Owner's/Developer's protection must be designed to coordinate with the reclosing practices of FirstEnergy line protective devices. The generator must cease to energize the FirstEnergy circuit to which it is connected prior to reclosing of any (FE) automatic reclosing devices.

Owners/Developer's electrical protection and control schematics shall be provided to FE for consideration. FE may request modifications, if required, to meet the technical requirements.

## 9.4 Compliance Issues

IC will be responsible for meeting a power factor between 0.95 lagging (producing MVARs) to 0.95 leading (absorbing MVARs) and assure that voltage deviation will be less than 1.0 volt as measured at the POI under all Solar Gen operating conditions due to the inherent dynamic reactive power capability of this solar/storage facility.

Generators with no inherent VAR (reactive power) control capability, or those that have a restricted VAR capability less than the defined requirements, must provide dynamic supplementary reactive support located at the generation facility with electrical characteristics equivalent to that provided by a similar sized synchronous generator. A Dynamic Reactive Compensation (either Static VAR Compensator (SVC) or STATCOM) or other method be applied in order to maintain the required specifications at the POI. IC is

responsible for the installation of equipment on its side of the POI in order to adhere to the criteria stated above by FirstEnergy.

## **10 Revenue Metering and SCADA Requirements**

### **10.1 PJM Requirements**

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

### **10.2 Meteorological Data Reporting Requirements**

The solar generation facility shall provide the Transmission Provider with site-specific meteorological data including:

- Back Panel temperature (Fahrenheit)
- Irradiance (Watts/meter<sup>2</sup>)
- Ambient air temperature (Fahrenheit) – (Accepted, not required)
- Wind speed (meters/second) – (Accepted, not required)

### **10.3 Interconnected Transmission Owner Requirements**

IC will be required to comply with all FE Revenue Metering Requirements for Generation Interconnection Customers. These FE requirements are the following:

The FE operating company (Penelec) shall provide, own, operate, test, and maintain the revenue metering equipment at the Interconnection Customer's (IC) expense. The revenue metering equipment includes, but is not limited to, current transformers, voltage transformers, secondary wires, meter socket, bidirectional revenue meter, and associated devices. The IC shall mount the instrument transformers unless otherwise agreed to by Penelec. The instrument transformers and meter socket shall be installed in a location that is readily accessible to authorized Penelec representatives. Penelec will provide the IC access to bidirectional kWh and kVARh pulses from the Penelec meter at the IC's expense if requested. The IC shall, at its expense, install, own, operate, test, and maintain any metering and telemetry equipment that may be required to provide real-time meter data to FE or PJM.

## 11 Summer Peak - Load Flow Analysis<sup>2</sup>

The Queue Project AF2-121 was evaluated as a 20.0 MW (Capacity 12.0 MW) injection at the Philipsburg 34.5 kV substation in the PENELEC area. Project AF2-121 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AF2-121 was studied with a commercial probability of 53.0 %. Potential network impacts were as follows:

### 11.1 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

### 11.2 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

### 11.3 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

ID	FROM BUS#	FROM BUS	KV	FROM BUS AREA	TO BUS#	TO BUS	KV	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101036583	200712	26DUBOIS	115.0	PENELEC	200720	26HARVY.RU	115.0	PENELEC	1	AP-P2-2-WP-230-001T	bus	179.0	113.77	115.33	DC	2.79
101036884	200712	26DUBOIS	115.0	PENELEC	200720	26HARVY.RU	115.0	PENELEC	1	AP-P2-3-WP-230-446T	breaker	179.0	113.88	115.44	DC	2.79
101036885	200712	26DUBOIS	115.0	PENELEC	200720	26HARVY.RU	115.0	PENELEC	1	AP-P2-2-WP-230-001T	breaker	179.0	113.77	115.33	DC	2.79
101036886	200712	26DUBOIS	115.0	PENELEC	200720	26HARVY.RU	115.0	PENELEC	1	AP-P2-3-WP-230-443T*	breaker	179.0	113.72	115.28	DC	2.79
101036533	200713	26ROCKTON	115.0	PENELEC	200712	26DUBOIS	115.0	PENELEC	1	AP-P2-2-WP-230-001T	bus	190.0	130.26	131.73	DC	2.79
101036794	200713	26ROCKTON	115.0	PENELEC	200712	26DUBOIS	115.0	PENELEC	1	AP-P2-3-WP-230-446T	breaker	190.0	130.37	131.84	DC	2.79
101036795	200713	26ROCKTON	115.0	PENELEC	200712	26DUBOIS	115.0	PENELEC	1	AP-P2-2-WP-230-001T	breaker	190.0	130.26	131.73	DC	2.79
101036796	200713	26ROCKTON	115.0	PENELEC	200712	26DUBOIS	115.0	PENELEC	1	AP-P2-3-WP-230-443T*	breaker	190.0	130.21	131.68	DC	2.79

ID	FROM BUS#	FROM BUS	kV	FROM BUS AREA	TO BUS#	TO BUS	kV	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
101036532	200714	26SHAWVL1	115.0	PENELEC	200713	26ROCKTON	115.0	PENELEC	1	AP-P2-2-WP-230-001T	bus	190.0	131.9	133.36	DC	2.79
101036789	200714	26SHAWVL1	115.0	PENELEC	200713	26ROCKTON	115.0	PENELEC	1	AP-P2-3-WP-230-446T	breaker	190.0	132.0	133.47	DC	2.79
101036790	200714	26SHAWVL1	115.0	PENELEC	200713	26ROCKTON	115.0	PENELEC	1	AP-P2-2-WP-230-001T	breaker	190.0	131.9	133.36	DC	2.79
101036791	200714	26SHAWVL1	115.0	PENELEC	200713	26ROCKTON	115.0	PENELEC	1	AP-P2-3-WP-230-443T*	breaker	190.0	131.85	133.31	DC	2.79
101037133	200716	26PHILIPSB	115.0	PENELEC	200904	26EAGL VAL	115.0	PENELEC	1	AP-P1-2-WP-230-323T	single	174.0	107.6	110.06	DC	4.28
101037134	200716	26PHILIPSB	115.0	PENELEC	200904	26EAGL VAL	115.0	PENELEC	1	AP-P1-3-WP-230-326T	single	174.0	107.38	109.84	DC	4.28
101036593	200720	26HARVY.RU	115.0	PENELEC	200711	26WHETSTON	115.0	PENELEC	1	AP-P2-2-WP-230-001T	bus	172.0	110.41	112.01	DC	2.76
101036918	200720	26HARVY.RU	115.0	PENELEC	200711	26WHETSTON	115.0	PENELEC	1	AP-P2-3-WP-230-446T	breaker	172.0	110.53	112.13	DC	2.76
101036919	200720	26HARVY.RU	115.0	PENELEC	200711	26WHETSTON	115.0	PENELEC	1	AP-P2-2-WP-230-001T	breaker	172.0	110.41	112.01	DC	2.76
101036920	200720	26HARVY.RU	115.0	PENELEC	200711	26WHETSTON	115.0	PENELEC	1	AP-P2-3-WP-230-443T*	breaker	172.0	110.29	111.9	DC	2.76
101037074	200904	26EAGL VAL	115.0	PENELEC	200527	26TYRONE N	115.0	PENELEC	1	AP-P1-2-WP-230-323T	single	191.0	107.58	109.81	DC	4.28
101037075	200904	26EAGL VAL	115.0	PENELEC	200527	26TYRONE N	115.0	PENELEC	1	AP-P1-3-WP-230-326T	single	191.0	107.32	109.56	DC	4.28
101036560	945550	AF1-220 TAP	115.0	PENELEC	200582	26RIDGWAY	115.0	PENELEC	1	AP-P2-2-WP-230-001T	bus	239.0	120.9	122.07	DC	2.79

ID	FROM BUS#	FROM BUS	kV	FROM BUS AREA	TO BUS#	TO BUS	kV	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPACT
101036834	945550	AF1-220 TAP	115.0	PENELEC	200582	26RIDGWAY	115.0	PENELEC	1	AP-P2-3-WP-230-446T	breaker	239.0	120.98	122.15	DC	2.79
101036835	945550	AF1-220 TAP	115.0	PENELEC	200582	26RIDGWAY	115.0	PENELEC	1	AP-P2-2-WP-230-001T	breaker	239.0	120.9	122.07	DC	2.79
101036836	945550	AF1-220 TAP	115.0	PENELEC	200582	26RIDGWAY	115.0	PENELEC	1	AP-P2-3-WP-230-443T*	breaker	239.0	120.86	122.03	DC	2.79
101036784	957580	AF2-052 TAP	115.0	PENELEC	200668	26FARM VLY	115.0	PENELEC	1	PN-P2-3-PN-230-7AT	breaker	160.0	133.45	133.91	DC	1.62

#### 11.4 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

ID	FROM BUS#	FROM BUS	kV	FROM BUS AREA	TO BUS#	TO BUS	kV	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPACT
101037222	200527	26TYRONE N	115.0	PENELEC	200528	26WESTFAL L	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	237.0	117.38	120.39	DC	7.13
101037120	200714	26SHAWVL 1	115.0	PENELEC	200872	26BIOEN TP	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	185.0	140.65	142.08	DC	2.64
101037128	200716	26PHILIPSB	115.0	PENELEC	200904	26EAGL VAL	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	174.0	137.58	141.68	DC	7.13
101037314	200717	26MADERA	115.0	PENELEC	944180	AF1-086 TAP	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	237.0	100.34	101.45	DC	2.64

ID	FROM BUS#	FROM BUS	kV	FROM BUS AREA	TO BUS#	TO BUS	kV	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101037158	200755	26WESTOVER	115.0	PENELEC	200801	26GARMAN	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	246.0	126.66	127.74	DC	2.64
101037160	200755	26WESTOVER	115.0	PENELEC	200801	26GARMAN	115.0	PENELEC	1	Base Case	operation	193.0	105.26	106.42	DC	2.24
101037262	200801	26GARMAN	115.0	PENELEC	200507	26GLORY	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	233.0	106.24	107.35	DC	2.59
101037321	200872	26BIOENTP	115.0	PENELEC	200717	26MADERA	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	242.0	104.05	105.14	DC	2.64
101037068	200904	26EAGL VAL	115.0	PENELEC	200527	26TYRONE	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	191.0	167.8	171.53	DC	7.13
101037073	200904	26EAGL VAL	115.0	PENELEC	200527	26TYRONE	115.0	PENELEC	1	Base Case	operation	147.0	127.21	131.77	DC	6.71
101037141	944180	AF1-086 TAP	115.0	PENELEC	200755	26WESTOVER	115.0	PENELEC	1	AP-P1-2-WP-230-323T	operation	237.0	132.23	133.35	DC	2.64
101037143	944180	AF1-086 TAP	115.0	PENELEC	200755	26WESTOVER	115.0	PENELEC	1	Base Case	operation	175.0	117.12	118.39	DC	2.24

## 11.5 System Reinforcements - Summer Peak Load Flow - Primary POI<sup>2</sup>

ID	Idx	Facility	Upgrade Description	Cost
101036835,101036834,101036560,101036836	7	AF1-220 TAP 115.0 kV - 26RIDGWAY 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>PN-AF2-F-0062A (1840) : Reconductor 0.31 miles of transmission line.</b>  <b>Replace line drops at Ridgway.</b>  <b>Project Type : FAC</b>  <b>Cost : \$947,670</b>  <b>Time Estimate : 12.0 Months</b></p> <p><b>PN-AF2-F-0062B (1841) : Reconductor 6.42 miles of transmission line</b>  <b>Project Type : FAC</b>  <b>Cost : \$19,625,940</b>  <b>Time Estimate : 42.0 Months</b></p> <p><b>s1886_s1886.1_s1886.2 (1889) : Ridgway 115 kV Substation: Replace line relaying and circuit breaker (s1886.1)</b>  <b>Whetstone 115 kV Substation: Replace line relaying (s1886.2)</b>  <b>Project Type : FAC</b>  <b>Cost : \$0</b></p> <p><b>s1888_s1888.1_s1888.2 (1904) : Grandview 115 kV Substation: Replace line relaying and line trap (s1888.1)</b>  <b>Titusville 115 kV Substation: Replace line relaying, breaker, and line trap (s1888.2)</b>  <b>Project Type : FAC</b>  <b>Cost : \$0</b></p>	\$20,573,610
101036884,101036885,101036583,101036886	1	26DUBOIS 115.0 kV - 26HARVY.RU 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>PN-AF2-F-0058A (1825) : Replace relays at Dubois</b>  <b>Project Type : FAC</b>  <b>Cost : \$427,980</b>  <b>Time Estimate : 12.0 Months</b></p> <p><b>PN-AF2-F-0058B (1826) : Replace line trap at Dubois.</b>  <b>Project Type : FAC</b>  <b>Cost : \$122,280</b>  <b>Time Estimate : 12.0 Months</b></p>	\$550,260
101037074,101037075	6	26EAGL VAL 115.0 kV - 26TYRONE N 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>s1776.1_s1776.2_s1776.3 (1891) : Construct a four breaker 115 kV ring bus (s1776.1)</b>  <b>Replace the #2 115/46 kV 45/60/75 MVA transformer (s1776.2)</b>  <b>Install a 46 kV 1200 A bypass switch between the Tipton and Warrior Ridge 46 kV lines (s1776.3)</b>  <b>Project Type : FAC</b>  <b>Cost : \$0</b></p>	\$0

ID	Idx	Facility	Upgrade Description	Cost
101036532,101036790,101036789,101036791	3	26SHAWVL 1 115.0 kV - 26ROCKTON 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>PN-AF2-F-0050A (1810) : Replace line trap at Shawville.</b>  Project Type : FAC  Cost : <b>\$122,280</b>  Time Estimate : <b>12.0 Months</b></p> <p><b>PN-AF2-F-0050B (1811) : Reconductor 8.63 miles of transmission line.</b>  <b>Replace line drops at Shawville.</b>  Project Type : FAC  Cost : <b>\$26,381,910</b>  Time Estimate : <b>48.0 Months</b></p>	\$26,504,190
101036794,101036795,101036796,101036533	2	26ROCKTON 115.0 kV - 26DUBOIS 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>PN-AF2-F-0054A (1817) : Replace line trap at Dubois.</b>  Project Type : FAC  Cost : <b>\$122,280</b>  Time Estimate : <b>12.0 Months</b></p> <p><b>PN-AF2-F-0054B (1818) : Reconductor 11.67 miles of transmission line</b>  Project Type : FAC  Cost : <b>\$28,540,152</b>  Time Estimate : <b>48.0 Months</b></p> <p><b>PN-AF2-F-0054C (1819) : Adjust CT ratios at Dubois.</b>  Project Type : FAC  Cost : <b>\$733,680</b>  Time Estimate : <b>12.0 Months</b></p>	\$29,396,112
101036593,101036920,101036918,101036919	5	26HARVY.RU 115.0 kV - 26WHETSTON 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>PN-AF2-F-0060A (1833) : Replace disconnect switches at Whetstone.</b>  Project Type : FAC  Cost : <b>\$183,420</b>  Time Estimate : <b>12.0 Months</b></p>	\$183,420
101037134,101037133	4	26PHILIPSB 115.0 kV - 26EAGL VAL 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>s1919_s1919.1_s1919.2_s1919.3_s1919.4 (1894) : Construct Philipsburg 115 kV Ring Bus (s1919)</b>  <b>Construct a four breaker 115 kV ring bus (s1919.1)</b>  <b>Replace limiting CTs, substation conductor / drop, line trap, and circuit breakers on Shawvilleexit (s1919.2)</b>  <b>Replace limiting CTs, substation conductor / drop, and circuit breakers on Eagle Valley exit (s1919.3)</b>  <b>Replace line trap on Philipsburg line exit at Shawville (s1919.4)</b>  <b>Adjust Line Relays as necessary</b>  Project Type : FAC  Cost : <b>\$0</b></p>	\$0

ID	Idx	Facility	Upgrade Description	Cost
101036784	8	AF2-052 TAP 115.0 kV - 26FARM VLY 115.0 kV Ckt 1	<p><b>PENELEC</b>  <b>PN-AF2-F-0056A (1821) : Reconductor 1.71 miles of transmission line</b>  <b>Project Type : FAC</b>  <b>Cost : \$4,181,976</b>  <b>Time Estimate : 24.0 Months</b></p> <p><b>PN-AF2-F-0056B (1822) : Replace substation conductor at Farmers Valley</b>  <b>Project Type : FAC</b>  <b>Cost : \$122,280</b>  <b>Time Estimate : 12.0 Months</b></p> <p><b>PN-AF2-F-0056C (1823) : Adjust line relaying at Farmers Valley</b>  <b>Project Type : FAC</b>  <b>Cost : \$427,980</b>  <b>Time Estimate : 12.0 Months</b></p> <p><b>Note: It should be noted that some of the contingencies taken in the analysis may not be valid due to system condition changes that were not captured in the model. This will be re-evaluated for validity in the System Impact phase.</b></p>	\$4,732,236
N/A	N/A	26RIDGWAY 115.0 kV - AE2- 113 TAP 115.0 kV Ckt 1	<p><b>Note: It should be noted that some of the contingencies taken in the analysis may not be valid due to system condition changes that were not captured in the model. This will be re-evaluated for validity in the System Impact phase.</b></p>	\$0
N/A	N/A	26GARMAN 115.0 kV - 200507 26GLORY 115.0 kV Ckt 1	<p><b>Note: It should be noted that some of the contingencies taken in the analysis may not be valid due to system condition changes that were not captured in the model. This will be re-evaluated for validity in the System Impact phase.</b></p>	\$0
			<b>TOTAL COST</b>	<b>\$81,939,828<sup>1</sup></b>

## 11.6 Flow Gate Details

The following indices contain additional information about each facility presented in the body of the report. For each index, a description of the flowgate and its contingency was included for convenience. The intent of the indices is to provide more details on which projects/generators have contributions to the flowgate in question. All New Service Queue Requests, through the end of the Queue under study, that are contributors to a flowgate will be listed in the indices. Please note that there may be contributors that are subsequently queued after the queue under study that are not listed in the indices. Although this information is not used "as is" for cost allocation purposes, it can be used to gage the impact of other projects/generators. It should be noted the project/generator MW contributions presented in the body of the report are Full MW Impact contributions which are also noted in the indices column named "Full MW Impact", whereas the loading percentages reported in the body of the report, take into consideration the PJM Generator Deliverability Test rules such as commercial probability of each project as well as the ramping impact of "Adder" contributions. The MW Impact found and used in the analysis is shown in the indices column named "Gendeliv MW Impact".

---

### 11.6.1 Index 1

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101036886	200712	26DUBOIS	PENELEC	200720	26HARVY.RU	PENELEC	1	AP-P2-3-WP-230-443T *	breaker	179.0	113.72	115.28	DC	2.79

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200665	26SHAWVL 3	3.3814	50/50	3.3814
200666	26SHAWVL 4	3.3661	50/50	3.3661
200715	26SHAWVL 1	3.0636	50/50	3.0636
200722	26SHAWVL 2	3.1420	50/50	3.1420
200905	26Q36	0.1849	50/50	0.1849
200913	26SHAW-D	0.1864	50/50	0.1864
235003	AC1-025 E	0.0987	Adder	0.12
236828	O1GRAYMONT	0.2707	Adder	0.32
290086	Q-036 E	4.2876	50/50	4.2876
919491	AA2-000	28.6741	Adder	33.73
930511	AB1-092	1.0528	Adder	1.24
936421	AD2-055	2.1676	Adder	2.55
936991	AD2-133 C	1.9294	50/50	1.9294
936992	AD2-133 E	8.8250	50/50	8.8250
939171	AE1-147 C	0.8156	Adder	0.96
939172	AE1-147 E	0.5437	Adder	0.64
940201	AE2-001 C	0.8137	Adder	0.96
940202	AE2-001 E	0.5424	Adder	0.64
940681	AE2-055 C (Suspended)	0.7834	Adder	0.92
940682	AE2-055 E (Suspended)	0.5222	Adder	0.61
941261	AE2-120 C	0.8125	Adder	0.96
941262	AE2-120 E	0.5417	Adder	0.64
941271	AE2-121 C	0.4355	Adder	0.51
941272	AE2-121 E	0.2908	Adder	0.34
941321	AE2-126 C	5.8504	50/50	5.8504
941322	AE2-126 E	3.9002	50/50	3.9002
941331	AE2-129 C	1.6744	50/50	1.6744
941332	AE2-129 E	1.1162	50/50	1.1162
941351	AE2-131 C	1.6744	50/50	1.6744
941352	AE2-131 E	1.1162	50/50	1.1162
942351	AE2-248 C	0.6368	Adder	0.75
942352	AE2-248 E	0.4245	Adder	0.5
942491	AE2-262 C	3.8169	Adder	4.49
942492	AE2-262 E	2.5650	Adder	3.02
942501	AE2-263 C	3.5879	Adder	4.22
942502	AE2-263 E	2.3955	Adder	2.82
943751	AF1-043	6.5028	Adder	7.65
944001	AF1-068 C O1	0.8449	Adder	0.99
944002	AF1-068 E O1	0.4753	Adder	0.56
944181	AF1-086 C O1	1.1729	Adder	1.38
944182	AF1-086 E O1	5.1027	Adder	6.0

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
944311	AF1-099 C	5.7941	Adder	6.82
944312	AF1-099 E	3.8627	Adder	4.54
944321	AF1-100 C	16.4745	50/50	16.4745
944322	AF1-100 E	10.9830	50/50	10.9830
944382	AF1-103 BAT	1.3786	Merchant Transmission	1.3786
944471	AF1-112 C	0.8526	Adder	1.0
944472	AF1-112 E	0.4796	Adder	0.56
944671	AF1-132 C O1	0.7900	Adder	0.93
944672	AF1-132 E O1	0.5267	Adder	0.62
944691	AF1-134 C O1	1.3878	50/50	1.3878
944692	AF1-134 E O1	0.9252	50/50	0.9252
944771	AF1-142 C	9.2705	Adder	10.91
944772	AF1-142 E	6.1804	Adder	7.27
944841	AF1-149 C	0.8124	Adder	0.96
944842	AF1-149 E	0.5416	Adder	0.64
945161	AF1-181	0.0912	50/50	0.0912
945171	AF1-182	0.4565	50/50	0.4565
945181	AF1-183	0.1456	50/50	0.1456
945491	AF1-214 C	0.8126	Adder	0.96
945492	AF1-214 E	0.5418	Adder	0.64
946423	AF1-306 BAT	32.4419	50/50	32.4419
957451	AF2-039 C	1.4574	50/50	1.4574
957452	AF2-039 E	0.9716	50/50	0.9716
957941	AF2-088 C	0.7017	50/50	0.7017
957942	AF2-088 E	0.4678	50/50	0.4678
958271	AF2-121 C	1.6744	50/50	1.6744
958272	AF2-121 E	1.1162	50/50	1.1162
959802	AF2-271 E	0.1218	Adder	0.27
960022	AF2-293 E	0.0420	Adder	0.09
960051	AF2-296 C	1.3878	50/50	1.3878
960052	AF2-296 E	0.9252	50/50	0.9252
<b>NEWTON</b>	<b>NEWTON</b>	0.3138	Confirmed LTF	0.3138
<b>FARMERCITY</b>	<b>FARMERCITY</b>	0.0161	Confirmed LTF	0.0161
<b>G-007A</b>	<b>G-007A</b>	1.2563	Confirmed LTF	1.2563
<b>VFT</b>	<b>VFT</b>	3.4185	Confirmed LTF	3.4185
<b>CALDERWOOD</b>	<b>CALDERWOOD</b>	0.1118	Confirmed LTF	0.1118
<b>NY</b>	<b>NY</b>	0.0216	Confirmed LTF	0.0216
<b>PRAIRIE</b>	<b>PRAIRIE</b>	0.7284	Confirmed LTF	0.7284
<b>CHEOAH</b>	<b>CHEOAH</b>	0.1116	Confirmed LTF	0.1116
<b>EDWARDS</b>	<b>EDWARDS</b>	0.1064	Confirmed LTF	0.1064
<b>TILTON</b>	<b>TILTON</b>	0.1903	Confirmed LTF	0.1903
<b>MADISON</b>	<b>MADISON</b>	0.0202	Confirmed LTF	0.0202
<b>GIBSON</b>	<b>GIBSON</b>	0.1600	Confirmed LTF	0.1600
<b>BLUEG</b>	<b>BLUEG</b>	0.5052	Confirmed LTF	0.5052
<b>TRIMBLE</b>	<b>TRIMBLE</b>	0.1619	Confirmed LTF	0.1619
<b>CATAWBA</b>	<b>CATAWBA</b>	0.0606	Confirmed LTF	0.0606

## 11.6.2 Index 2

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101036796	200713	26ROCKTON	PENELEC	200712	26DUBOIS	PENELEC	1	AP-P2-3-WP-230-443T *	breaker	190.0	130.21	131.68	DC	2.79

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200665	26SHAWVL 3	3.3814	50/50	3.3814
200666	26SHAWVL 4	3.3661	50/50	3.3661
200715	26SHAWVL 1	3.0636	50/50	3.0636
200722	26SHAWVL 2	3.1420	50/50	3.1420
200905	26Q36	0.1849	50/50	0.1849
200913	26SHAW-D	0.1864	50/50	0.1864
235003	AC1-025 E	0.0987	Adder	0.12
236828	01GRAYMONT	0.2707	Adder	0.32
290086	Q-036 E	4.2876	50/50	4.2876
919491	AA2-000	28.6741	Adder	33.73
930511	AB1-092	1.0528	Adder	1.24
936421	AD2-055	2.1676	Adder	2.55
936991	AD2-133 C	1.9294	50/50	1.9294
936992	AD2-133 E	8.8250	50/50	8.8250
939171	AE1-147 C	0.8156	Adder	0.96
939172	AE1-147 E	0.5437	Adder	0.64
940201	AE2-001 C	0.8137	Adder	0.96
940202	AE2-001 E	0.5424	Adder	0.64
940681	AE2-055 C (Suspended)	0.7834	Adder	0.92
940682	AE2-055 E (Suspended)	0.5222	Adder	0.61
941261	AE2-120 C	0.8125	Adder	0.96
941262	AE2-120 E	0.5417	Adder	0.64
941271	AE2-121 C	0.4355	Adder	0.51
941272	AE2-121 E	0.2908	Adder	0.34
941331	AE2-129 C	1.6744	50/50	1.6744
941332	AE2-129 E	1.1162	50/50	1.1162
941351	AE2-131 C	1.6744	50/50	1.6744
941352	AE2-131 E	1.1162	50/50	1.1162
942351	AE2-248 C	0.6368	Adder	0.75
942352	AE2-248 E	0.4245	Adder	0.5
942491	AE2-262 C	3.8169	Adder	4.49
942492	AE2-262 E	2.5650	Adder	3.02
942501	AE2-263 C	3.5879	Adder	4.22
942502	AE2-263 E	2.3955	Adder	2.82
943751	AF1-043	6.5028	Adder	7.65
944001	AF1-068 C O1	0.8449	Adder	0.99
944002	AF1-068 E O1	0.4753	Adder	0.56
944181	AF1-086 C O1	1.1729	Adder	1.38
944182	AF1-086 E O1	5.1027	Adder	6.0
944311	AF1-099 C	5.7941	Adder	6.82
944312	AF1-099 E	3.8627	Adder	4.54

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
944321	AF1-100 C	16.4745	50/50	16.4745
944322	AF1-100 E	10.9830	50/50	10.9830
944382	AF1-103 BAT	1.3786	Merchant Transmission	1.3786
944471	AF1-112 C	0.8526	Adder	1.0
944472	AF1-112 E	0.4796	Adder	0.56
944671	AF1-132 C O1	0.7900	Adder	0.93
944672	AF1-132 E O1	0.5267	Adder	0.62
944691	AF1-134 C O1	1.3878	50/50	1.3878
944692	AF1-134 E O1	0.9252	50/50	0.9252
944771	AF1-142 C	9.2705	Adder	10.91
944772	AF1-142 E	6.1804	Adder	7.27
944841	AF1-149 C	0.8124	Adder	0.96
944842	AF1-149 E	0.5416	Adder	0.64
945161	AF1-181	0.0912	50/50	0.0912
945171	AF1-182	0.4565	50/50	0.4565
945181	AF1-183	0.1456	50/50	0.1456
945491	AF1-214 C	0.8126	Adder	0.96
945492	AF1-214 E	0.5418	Adder	0.64
946423	AF1-306 BAT	32.4419	50/50	32.4419
957451	AF2-039 C	1.4574	50/50	1.4574
957452	AF2-039 E	0.9716	50/50	0.9716
957941	AF2-088 C	0.7017	50/50	0.7017
957942	AF2-088 E	0.4678	50/50	0.4678
958271	AF2-121 C	1.6744	50/50	1.6744
958272	AF2-121 E	1.1162	50/50	1.1162
959802	AF2-271 E	0.1218	Adder	0.27
960022	AF2-293 E	0.0420	Adder	0.09
960051	AF2-296 C	1.3878	50/50	1.3878
960052	AF2-296 E	0.9252	50/50	0.9252
<b>NEWTON</b>	<b>NEWTON</b>	0.3138	Confirmed LTF	0.3138
<b>FARMERCITY</b>	<b>FARMERCITY</b>	0.0161	Confirmed LTF	0.0161
<b>G-007A</b>	<b>G-007A</b>	1.2563	Confirmed LTF	1.2563
<b>VFT</b>	<b>VFT</b>	3.4185	Confirmed LTF	3.4185
<b>CALDERWOOD</b>	<b>CALDERWOOD</b>	0.1118	Confirmed LTF	0.1118
<b>NY</b>	<b>NY</b>	0.0216	Confirmed LTF	0.0216
<b>PRAIRIE</b>	<b>PRAIRIE</b>	0.7284	Confirmed LTF	0.7284
<b>CHEOAH</b>	<b>CHEOAH</b>	0.1116	Confirmed LTF	0.1116
<b>EDWARDS</b>	<b>EDWARDS</b>	0.1064	Confirmed LTF	0.1064
<b>TILTON</b>	<b>TILTON</b>	0.1903	Confirmed LTF	0.1903
<b>MADISON</b>	<b>MADISON</b>	0.0202	Confirmed LTF	0.0202
<b>GIBSON</b>	<b>GIBSON</b>	0.1600	Confirmed LTF	0.1600
<b>BLUEG</b>	<b>BLUEG</b>	0.5052	Confirmed LTF	0.5052
<b>TRIMBLE</b>	<b>TRIMBLE</b>	0.1619	Confirmed LTF	0.1619
<b>CATAWBA</b>	<b>CATAWBA</b>	0.0606	Confirmed LTF	0.0606

### 11.6.3 Index 3

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101036791	200714	26SHAWVL 1	PENELEC	200713	26ROCKTON	PENELEC	1	AP-P2-3-WP-230-443T *	breaker	190.0	131.85	133.31	DC	2.79

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200665	26SHAWVL 3	3.3814	50/50	3.3814
200666	26SHAWVL 4	3.3661	50/50	3.3661
200715	26SHAWVL 1	3.0636	50/50	3.0636
200722	26SHAWVL 2	3.1420	50/50	3.1420
200905	26Q36	0.1849	50/50	0.1849
200913	26SHAW-D	0.1864	50/50	0.1864
235003	AC1-025 E	0.0987	Adder	0.12
236828	O1GRAYMONT	0.2707	Adder	0.32
290086	Q-036 E	4.2876	50/50	4.2876
919491	AA2-000	28.6741	Adder	33.73
930511	AB1-092	1.0528	Adder	1.24
936421	AD2-055	2.1676	Adder	2.55
936991	AD2-133 C	1.9294	50/50	1.9294
936992	AD2-133 E	8.8250	50/50	8.8250
939171	AE1-147 C	0.8156	Adder	0.96
939172	AE1-147 E	0.5437	Adder	0.64
940201	AE2-001 C	0.8137	Adder	0.96
940202	AE2-001 E	0.5424	Adder	0.64
940681	AE2-055 C (Suspended)	0.7834	Adder	0.92
940682	AE2-055 E (Suspended)	0.5222	Adder	0.61
941261	AE2-120 C	0.8125	Adder	0.96
941262	AE2-120 E	0.5417	Adder	0.64
941271	AE2-121 C	0.4355	Adder	0.51
941272	AE2-121 E	0.2908	Adder	0.34
941331	AE2-129 C	1.6744	50/50	1.6744
941332	AE2-129 E	1.1162	50/50	1.1162
941351	AE2-131 C	1.6744	50/50	1.6744
941352	AE2-131 E	1.1162	50/50	1.1162
942351	AE2-248 C	0.6368	Adder	0.75
942352	AE2-248 E	0.4245	Adder	0.5
942491	AE2-262 C	3.8169	Adder	4.49
942492	AE2-262 E	2.5650	Adder	3.02
942501	AE2-263 C	3.5879	Adder	4.22
942502	AE2-263 E	2.3955	Adder	2.82
943751	AF1-043	6.5028	Adder	7.65
944001	AF1-068 C O1	0.8449	Adder	0.99
944002	AF1-068 E O1	0.4753	Adder	0.56
944181	AF1-086 C O1	1.1729	Adder	1.38
944182	AF1-086 E O1	5.1027	Adder	6.0
944311	AF1-099 C	5.7941	Adder	6.82
944312	AF1-099 E	3.8627	Adder	4.54

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
944321	AF1-100 C	16.4745	50/50	16.4745
944322	AF1-100 E	10.9830	50/50	10.9830
944382	AF1-103 BAT	1.3786	Merchant Transmission	1.3786
944471	AF1-112 C	0.8526	Adder	1.0
944472	AF1-112 E	0.4796	Adder	0.56
944671	AF1-132 C O1	0.7900	Adder	0.93
944672	AF1-132 E O1	0.5267	Adder	0.62
944691	AF1-134 C O1	1.3878	50/50	1.3878
944692	AF1-134 E O1	0.9252	50/50	0.9252
944771	AF1-142 C	9.2705	Adder	10.91
944772	AF1-142 E	6.1804	Adder	7.27
944841	AF1-149 C	0.8124	Adder	0.96
944842	AF1-149 E	0.5416	Adder	0.64
945161	AF1-181	0.0912	50/50	0.0912
945171	AF1-182	0.4565	50/50	0.4565
945181	AF1-183	0.1456	50/50	0.1456
945491	AF1-214 C	0.8126	Adder	0.96
945492	AF1-214 E	0.5418	Adder	0.64
946423	AF1-306 BAT	32.4419	50/50	32.4419
957451	AF2-039 C	1.4574	50/50	1.4574
957452	AF2-039 E	0.9716	50/50	0.9716
957941	AF2-088 C	0.7017	50/50	0.7017
957942	AF2-088 E	0.4678	50/50	0.4678
958271	AF2-121 C	1.6744	50/50	1.6744
958272	AF2-121 E	1.1162	50/50	1.1162
959802	AF2-271 E	0.1218	Adder	0.27
960022	AF2-293 E	0.0420	Adder	0.09
960051	AF2-296 C	1.3878	50/50	1.3878
960052	AF2-296 E	0.9252	50/50	0.9252
<b>NEWTON</b>	<b>NEWTON</b>	0.3138	Confirmed LTF	0.3138
<b>FARMERCITY</b>	<b>FARMERCITY</b>	0.0161	Confirmed LTF	0.0161
<b>G-007A</b>	<b>G-007A</b>	1.2563	Confirmed LTF	1.2563
<b>VFT</b>	<b>VFT</b>	3.4185	Confirmed LTF	3.4185
<b>CALDERWOOD</b>	<b>CALDERWOOD</b>	0.1118	Confirmed LTF	0.1118
<b>NY</b>	<b>NY</b>	0.0216	Confirmed LTF	0.0216
<b>PRAIRIE</b>	<b>PRAIRIE</b>	0.7284	Confirmed LTF	0.7284
<b>CHEOAH</b>	<b>CHEOAH</b>	0.1116	Confirmed LTF	0.1116
<b>EDWARDS</b>	<b>EDWARDS</b>	0.1064	Confirmed LTF	0.1064
<b>TILTON</b>	<b>TILTON</b>	0.1903	Confirmed LTF	0.1903
<b>MADISON</b>	<b>MADISON</b>	0.0202	Confirmed LTF	0.0202
<b>GIBSON</b>	<b>GIBSON</b>	0.1600	Confirmed LTF	0.1600
<b>BLUEG</b>	<b>BLUEG</b>	0.5052	Confirmed LTF	0.5052
<b>TRIMBLE</b>	<b>TRIMBLE</b>	0.1619	Confirmed LTF	0.1619
<b>CATAWBA</b>	<b>CATAWBA</b>	0.0606	Confirmed LTF	0.0606

#### 11.6.4 Index 4

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101037133	200716	26PHILIPSB	PENELEC	200904	26EAGL VAL	PENELEC	1	AP-P1-2-WP-230-323T	single	174.0	107.6	110.06	DC	4.28

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200649	26PENNTech	0.5827	80/20	0.5827
200665	26SHAWVL 3	3.0989	80/20	3.0989
200666	26SHAWVL 4	3.0818	80/20	3.0818
200715	26SHAWVL 1	2.7831	80/20	2.7831
200722	26SHAWVL 2	2.8606	80/20	2.8606
200913	26SHAW-D	0.1683	80/20	0.1683
919491	AA2-000	33.7018	80/20	33.7018
930511	AB1-092	1.2374	80/20	1.2374
936421	AD2-055	2.5476	80/20	2.5476
939171	AE1-147 C	1.1525	80/20	1.1525
940201	AE2-001 C	1.1530	80/20	1.1530
940681	AE2-055 C (Suspended)	1.1618	80/20	1.1618
941191	AE2-113 C	3.4480	80/20	3.4480
941261	AE2-120 C	1.1533	80/20	1.1533
941271	AE2-121 C	0.6122	80/20	0.6122
941321	AE2-126 C	1.4333	80/20	1.4333
941331	AE2-129 C	4.2773	80/20	4.2773
941351	AE2-131 C	4.2773	80/20	4.2773
942351	AE2-248 C	0.9265	80/20	0.9265
942491	AE2-262 C	4.6805	80/20	4.6805
942501	AE2-263 C	4.3997	80/20	4.3997
943751	AF1-043	7.6429	80/20	7.6429
944001	AF1-068 C O1	1.2365	80/20	1.2365
944181	AF1-086 C O1	1.0332	80/20	1.0332
944311	AF1-099 C	7.1050	80/20	7.1050
944321	AF1-100 C	15.1905	80/20	15.1905
944471	AF1-112 C	1.2343	80/20	1.2343
944671	AF1-132 C O1	1.1598	80/20	1.1598
944691	AF1-134 C O1	1.1822	80/20	1.1822
944771	AF1-142 C	11.3680	80/20	11.3680
944841	AF1-149 C	1.1533	80/20	1.1533
944881	AF1-153 C O1	0.8496	80/20	0.8496
944901	AF1-155 C	0.8431	80/20	0.8431
945161	AF1-181	0.0836	80/20	0.0836
945171	AF1-182	0.4179	80/20	0.4179
945181	AF1-183	0.1322	80/20	0.1322
945491	AF1-214 C	1.1533	80/20	1.1533
945551	AF1-220 C	8.1609	80/20	8.1609
946421	AF1-306 C	3.7976	80/20	3.7976
957451	AF2-039 C	1.3197	80/20	1.3197
957941	AF2-088 C	0.6354	80/20	0.6354

<b>Bus #</b>	<b>Bus</b>	<b>Gendeliv MW Impact</b>	<b>Type</b>	<b>Full MW Impact</b>
<b>958271</b>	AF2-121 C	4.2773	80/20	4.2773
<b>960041</b>	AF2-295 C	0.8431	80/20	0.8431
<b>960051</b>	AF2-296 C	1.1822	80/20	1.1822
<b>NEWTON</b>	NEWTON	0.0064	Confirmed LTF	0.0064
<b>FARMERCITY</b>	FARMERCITY	0.0004	Confirmed LTF	0.0004
<b>CALDERWOOD</b>	CALDERWOOD	0.0159	Confirmed LTF	0.0159
<b>CBM-W1</b>	CBM-W1	0.1501	Confirmed LTF	0.1501
<b>PRAIRIE</b>	PRAIRIE	0.0258	Confirmed LTF	0.0258
<b>CHEOAH</b>	CHEOAH	0.0165	Confirmed LTF	0.0165
<b>EDWARDS</b>	EDWARDS	0.0003	Confirmed LTF	0.0003
<b>TILTON</b>	TILTON	0.0013	Confirmed LTF	0.0013
<b>GIBSON</b>	GIBSON	0.0033	Confirmed LTF	0.0033
<b>BLUEG</b>	BLUEG	0.0139	Confirmed LTF	0.0139
<b>TRIMBLE</b>	TRIMBLE	0.0039	Confirmed LTF	0.0039
<b>CATAWBA</b>	CATAWBA	0.0178	Confirmed LTF	0.0178

## 11.6.5 Index 5

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101036919	200720	26HARVY.RU	PENELEC	200711	26WHETSTON	PENELEC	1	AP-P2-2-WP-230-001T	breaker	172.0	110.41	112.01	DC	2.76

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200665	26SHAWVL 3	3.3398	50/50	3.3398
200666	26SHAWVL 4	3.3248	50/50	3.3248
200715	26SHAWVL 1	3.0259	50/50	3.0259
200722	26SHAWVL 2	3.1034	50/50	3.1034
200905	26Q36	0.1826	50/50	0.1826
200913	26SHAW-D	0.1841	50/50	0.1841
235003	AC1-025 E	0.0975	Adder	0.11
236828	01GRAYMONT	0.2674	Adder	0.31
290086	Q-036 E	4.2348	50/50	4.2348
919491	AA2-000	28.3238	Adder	33.32
930511	AB1-092	1.0400	Adder	1.22
936421	AD2-055	2.1411	Adder	2.52
936991	AD2-133 C	1.9057	50/50	1.9057
936992	AD2-133 E	8.7163	50/50	8.7163
939171	AE1-147 C	0.8056	Adder	0.95
939172	AE1-147 E	0.5371	Adder	0.63
940201	AE2-001 C	0.8037	Adder	0.95
940202	AE2-001 E	0.5358	Adder	0.63
940681	AE2-055 C (Suspended)	0.7738	Adder	0.91
940682	AE2-055 E (Suspended)	0.5158	Adder	0.61
941261	AE2-120 C	0.8025	Adder	0.94
941262	AE2-120 E	0.5350	Adder	0.63
941271	AE2-121 C	0.4302	Adder	0.51
941272	AE2-121 E	0.2872	Adder	0.34
941321	AE2-126 C	5.7785	50/50	5.7785
941322	AE2-126 E	3.8523	50/50	3.8523
941331	AE2-129 C	1.6537	50/50	1.6537
941332	AE2-129 E	1.1025	50/50	1.1025
941351	AE2-131 C	1.6537	50/50	1.6537
941352	AE2-131 E	1.1025	50/50	1.1025
942351	AE2-248 C	0.6290	Adder	0.74
942352	AE2-248 E	0.4193	Adder	0.49
942491	AE2-262 C	3.7702	Adder	4.44
942492	AE2-262 E	2.5336	Adder	2.98
942501	AE2-263 C	3.5440	Adder	4.17
942502	AE2-263 E	2.3662	Adder	2.78
943751	AF1-043	6.4233	Adder	7.56
944001	AF1-068 C O1	0.8346	Adder	0.98
944002	AF1-068 E O1	0.4695	Adder	0.55
944181	AF1-086 C O1	1.1584	Adder	1.36
944182	AF1-086 E O1	5.0397	Adder	5.93

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
944311	AF1-099 C	5.7231	Adder	6.73
944312	AF1-099 E	3.8154	Adder	4.49
944321	AF1-100 C	16.2720	50/50	16.2720
944322	AF1-100 E	10.8480	50/50	10.8480
944382	AF1-103 BAT	1.3616	Merchant Transmission	1.3616
944471	AF1-112 C	0.8421	Adder	0.99
944472	AF1-112 E	0.4737	Adder	0.56
944671	AF1-132 C O1	0.7803	Adder	0.92
944672	AF1-132 E O1	0.5202	Adder	0.61
944691	AF1-134 C O1	1.3708	50/50	1.3708
944692	AF1-134 E O1	0.9138	50/50	0.9138
944771	AF1-142 C	9.1570	Adder	10.77
944772	AF1-142 E	6.1047	Adder	7.18
944841	AF1-149 C	0.8024	Adder	0.94
944842	AF1-149 E	0.5350	Adder	0.63
945161	AF1-181	0.0901	50/50	0.0901
945171	AF1-182	0.4509	50/50	0.4509
945181	AF1-183	0.1438	50/50	0.1438
945491	AF1-214 C	0.8026	Adder	0.94
945492	AF1-214 E	0.5351	Adder	0.63
946423	AF1-306 BAT	32.0401	50/50	32.0401
957451	AF2-039 C	1.4395	50/50	1.4395
957452	AF2-039 E	0.9596	50/50	0.9596
957941	AF2-088 C	0.6931	50/50	0.6931
957942	AF2-088 E	0.4620	50/50	0.4620
958271	AF2-121 C	1.6537	50/50	1.6537
958272	AF2-121 E	1.1025	50/50	1.1025
959802	AF2-271 E	0.1203	Adder	0.27
960022	AF2-293 E	0.0415	Adder	0.09
960051	AF2-296 C	1.3708	50/50	1.3708
960052	AF2-296 E	0.9138	50/50	0.9138
NEWTON	NEWTON	0.3095	Confirmed LTF	0.3095
FARMERCITY	FARMERCITY	0.0158	Confirmed LTF	0.0158
G-007A	G-007A	1.2419	Confirmed LTF	1.2419
VFT	VFT	3.3798	Confirmed LTF	3.3798
CALDERWOOD	CALDERWOOD	0.1103	Confirmed LTF	0.1103
NY	NY	0.0210	Confirmed LTF	0.0210
PRAIRIE	PRAIRIE	0.7181	Confirmed LTF	0.7181
CHEOAH	CHEOAH	0.1101	Confirmed LTF	0.1101
EDWARDS	EDWARDS	0.1054	Confirmed LTF	0.1054
TILTON	TILTON	0.1877	Confirmed LTF	0.1877
MADISON	MADISON	0.0202	Confirmed LTF	0.0202
GIBSON	GIBSON	0.1583	Confirmed LTF	0.1583
BLUEG	BLUEG	0.4982	Confirmed LTF	0.4982
TRIMBLE	TRIMBLE	0.1603	Confirmed LTF	0.1603
CATAWBA	CATAWBA	0.0598	Confirmed LTF	0.0598

11.6.6 Index 6

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101037075	200904	26EAGL VAL	PENELEC	200527	26TYRONE N	PENELEC	1	AP-P1-3-WP-230-326T	single	191.0	107.32	109.56	DC	4.28

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200649	26PENNTech	0.5827	80/20	0.5827
200665	26SHAWVL 3	3.1108	80/20	3.1108
200666	26SHAWVL 4	3.0951	80/20	3.0951
200715	26SHAWVL 1	2.7905	80/20	2.7905
200722	26SHAWVL 2	2.8686	80/20	2.8686
200905	26Q36	0.8862	80/20	0.8862
200913	26SHAW-D	0.1686	80/20	0.1686
919491	AA2-000	33.5258	80/20	33.5258
930511	AB1-092	1.2310	80/20	1.2310
936421	AD2-055	2.5344	80/20	2.5344
936991	AD2-133 C	9.2479	80/20	9.2479
939171	AE1-147 C	1.1226	80/20	1.1226
940201	AE2-001 C	1.1252	80/20	1.1252
940681	AE2-055 C (Suspended)	1.1653	80/20	1.1653
941191	AE2-113 C	3.4461	80/20	3.4461
941261	AE2-120 C	1.1261	80/20	1.1261
941271	AE2-121 C	0.5958	80/20	0.5958
941321	AE2-126 C	1.4348	80/20	1.4348
941331	AE2-129 C	4.2798	80/20	4.2798
941351	AE2-131 C	4.2798	80/20	4.2798
942351	AE2-248 C	0.9163	80/20	0.9163
942491	AE2-262 C	4.5890	80/20	4.5890
942501	AE2-263 C	4.3137	80/20	4.3137
943751	AF1-043	7.6030	80/20	7.6030
944001	AF1-068 C O1	1.2296	80/20	1.2296
944181	AF1-086 C O1	1.0348	80/20	1.0348
944311	AF1-099 C	6.9661	80/20	6.9661
944321	AF1-100 C	15.2175	80/20	15.2175
944471	AF1-112 C	1.2187	80/20	1.2187
944671	AF1-132 C O1	1.1557	80/20	1.1557
944691	AF1-134 C O1	1.1843	80/20	1.1843
944771	AF1-142 C	11.1458	80/20	11.1458
944841	AF1-149 C	1.1262	80/20	1.1262
944881	AF1-153 C O1	0.8489	80/20	0.8489
944901	AF1-155 C	0.8424	80/20	0.8424
945161	AF1-181	0.0839	80/20	0.0839
945171	AF1-182	0.4197	80/20	0.4197
945181	AF1-183	0.1326	80/20	0.1326
945491	AF1-214 C	1.1261	80/20	1.1261
945551	AF1-220 C	8.1636	80/20	8.1636
946421	AF1-306 C	3.7946	80/20	3.7946

<b>Bus #</b>	<b>Bus</b>	<b>Gendeliv MW Impact</b>	<b>Type</b>	<b>Full MW Impact</b>
957451	AF2-039 C	1.3220	80/20	1.3220
957941	AF2-088 C	0.6365	80/20	0.6365
958271	AF2-121 C	4.2798	80/20	4.2798
960041	AF2-295 C	0.8424	80/20	0.8424
960051	AF2-296 C	1.1843	80/20	1.1843
<b>NEWTON</b>	NEWTON	0.0118	Confirmed LTF	0.0118
<b>FARMERCITY</b>	FARMERCITY	0.0007	Confirmed LTF	0.0007
<b>CALDERWOOD</b>	CALDERWOOD	0.0184	Confirmed LTF	0.0184
<b>CBM-W1</b>	CBM-W1	0.0876	Confirmed LTF	0.0876
<b>PRAIRIE</b>	PRAIRIE	0.0387	Confirmed LTF	0.0387
<b>CHEOAH</b>	CHEOAH	0.0190	Confirmed LTF	0.0190
<b>EDWARDS</b>	EDWARDS	0.0021	Confirmed LTF	0.0021
<b>TILTON</b>	TILTON	0.0044	Confirmed LTF	0.0044
<b>GIBSON</b>	GIBSON	0.0060	Confirmed LTF	0.0060
<b>BLUEG</b>	BLUEG	0.0226	Confirmed LTF	0.0226
<b>TRIMBLE</b>	TRIMBLE	0.0067	Confirmed LTF	0.0067
<b>CATAWBA</b>	CATAWBA	0.0196	Confirmed LTF	0.0196

## 11.6.7 Index 7

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101036836	945550	AF1-220 TAP	PENELEC	200582	26RIDGWAY	PENELEC	1	AP-P2-3-WP-230-443T *	breaker	239.0	120.86	122.03	DC	2.79

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200665	26SHAWVL 3	3.3814	50/50	3.3814
200666	26SHAWVL 4	3.3661	50/50	3.3661
200715	26SHAWVL 1	3.0636	50/50	3.0636
200722	26SHAWVL 2	3.1420	50/50	3.1420
200905	26Q36	0.1849	50/50	0.1849
200913	26SHAW-D	0.1864	50/50	0.1864
235003	AC1-025 E	0.0987	Adder	0.12
236828	O1GRAYMONT	0.2707	Adder	0.32
290086	Q-036 E	4.2876	50/50	4.2876
919491	AA2-000	28.6741	Adder	33.73
930511	AB1-092	1.0528	Adder	1.24
936421	AD2-055	2.1676	Adder	2.55
936991	AD2-133 C	1.9294	50/50	1.9294
936992	AD2-133 E	8.8250	50/50	8.8250
939171	AE1-147 C	0.8156	Adder	0.96
939172	AE1-147 E	0.5437	Adder	0.64
940201	AE2-001 C	0.8137	Adder	0.96
940202	AE2-001 E	0.5424	Adder	0.64
940681	AE2-055 C (Suspended)	0.7834	Adder	0.92
940682	AE2-055 E (Suspended)	0.5222	Adder	0.61
941261	AE2-120 C	0.8125	Adder	0.96
941262	AE2-120 E	0.5417	Adder	0.64
941271	AE2-121 C	0.4355	Adder	0.51
941272	AE2-121 E	0.2908	Adder	0.34
941321	AE2-126 C	5.8504	50/50	5.8504
941322	AE2-126 E	3.9002	50/50	3.9002
941331	AE2-129 C	1.6744	50/50	1.6744
941332	AE2-129 E	1.1162	50/50	1.1162
941351	AE2-131 C	1.6744	50/50	1.6744
941352	AE2-131 E	1.1162	50/50	1.1162
942351	AE2-248 C	0.6368	Adder	0.75
942352	AE2-248 E	0.4245	Adder	0.5
942491	AE2-262 C	3.8169	Adder	4.49
942492	AE2-262 E	2.5650	Adder	3.02
942501	AE2-263 C	3.5879	Adder	4.22
942502	AE2-263 E	2.3955	Adder	2.82
943751	AF1-043	6.5028	Adder	7.65
944001	AF1-068 C O1	0.8449	Adder	0.99
944002	AF1-068 E O1	0.4753	Adder	0.56
944181	AF1-086 C O1	1.1729	Adder	1.38
944182	AF1-086 E O1	5.1027	Adder	6.0

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
944311	AF1-099 C	5.7941	Adder	6.82
944312	AF1-099 E	3.8627	Adder	4.54
944321	AF1-100 C	16.4745	50/50	16.4745
944322	AF1-100 E	10.9830	50/50	10.9830
944382	AF1-103 BAT	1.3786	Merchant Transmission	1.3786
944471	AF1-112 C	0.8526	Adder	1.0
944472	AF1-112 E	0.4796	Adder	0.56
944671	AF1-132 C O1	0.7900	Adder	0.93
944672	AF1-132 E O1	0.5267	Adder	0.62
944691	AF1-134 C O1	1.3878	50/50	1.3878
944692	AF1-134 E O1	0.9252	50/50	0.9252
944771	AF1-142 C	9.2705	Adder	10.91
944772	AF1-142 E	6.1804	Adder	7.27
944841	AF1-149 C	0.8124	Adder	0.96
944842	AF1-149 E	0.5416	Adder	0.64
945161	AF1-181	0.0912	50/50	0.0912
945171	AF1-182	0.4565	50/50	0.4565
945181	AF1-183	0.1456	50/50	0.1456
945491	AF1-214 C	0.8126	Adder	0.96
945492	AF1-214 E	0.5418	Adder	0.64
945551	AF1-220 C	63.6436	50/50	63.6436
945552	AF1-220 E	42.4524	50/50	42.4524
946423	AF1-306 BAT	32.4419	50/50	32.4419
957451	AF2-039 C	1.4574	50/50	1.4574
957452	AF2-039 E	0.9716	50/50	0.9716
957941	AF2-088 C	0.7017	50/50	0.7017
957942	AF2-088 E	0.4678	50/50	0.4678
958271	AF2-121 C	1.6744	50/50	1.6744
958272	AF2-121 E	1.1162	50/50	1.1162
959802	AF2-271 E	0.1218	Adder	0.27
960022	AF2-293 E	0.0420	Adder	0.09
960051	AF2-296 C	1.3878	50/50	1.3878
960052	AF2-296 E	0.9252	50/50	0.9252
NEWTON	NEWTON	0.3138	Confirmed LTF	0.3138
FARMERCITY	FARMERCITY	0.0161	Confirmed LTF	0.0161
G-007A	G-007A	1.2563	Confirmed LTF	1.2563
VFT	VFT	3.4185	Confirmed LTF	3.4185
CALDERWOOD	CALDERWOOD	0.1118	Confirmed LTF	0.1118
NY	NY	0.0216	Confirmed LTF	0.0216
PRAIRIE	PRAIRIE	0.7284	Confirmed LTF	0.7284
CHEOAH	CHEOAH	0.1116	Confirmed LTF	0.1116
EDWARDS	EDWARDS	0.1064	Confirmed LTF	0.1064
TILTON	TILTON	0.1903	Confirmed LTF	0.1903
MADISON	MADISON	0.0202	Confirmed LTF	0.0202
GIBSON	GIBSON	0.1600	Confirmed LTF	0.1600
BLUEG	BLUEG	0.5052	Confirmed LTF	0.5052
TRIMBLE	TRIMBLE	0.1619	Confirmed LTF	0.1619
CATAWBA	CATAWBA	0.0606	Confirmed LTF	0.0606

### 11.6.8 Index 8

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
101036784	957580	AF2-052 TAP	PENELEC	200668	26FARM VLY	PENELEC	1	PN-P2-3-PN-230-7AT	breaker	160.0	133.45	133.91	DC	1.62

Bus #	Bus	Gendeliv MW Impact	Type	Full MW Impact
200649	26PENNTech	3.7369	50/50	3.7369
200913	26SHAW-D	0.1084	50/50	0.1084
290086	Q-036 E	2.1019	Adder	2.47
936991	AD2-133 C	0.9458	Adder	1.11
936992	AD2-133 E	4.3262	Adder	5.09
941191	AE2-113 C	44.1305	50/50	44.1305
941192	AE2-113 E	47.5143	50/50	47.5143
941321	AE2-126 C	3.7429	50/50	3.7429
941322	AE2-126 E	2.4953	50/50	2.4953
941331	AE2-129 C	0.8245	Adder	0.97
941332	AE2-129 E	0.5496	Adder	0.65
941351	AE2-131 C	0.8245	Adder	0.97
941352	AE2-131 E	0.5496	Adder	0.65
944321	AF1-100 C	6.8123	Adder	8.01
944322	AF1-100 E	4.5415	Adder	5.34
944691	AF1-134 C O1	0.6981	Adder	0.82
944692	AF1-134 E O1	0.4654	Adder	0.55
945161	AF1-181	0.0380	Adder	0.04
945171	AF1-182	0.1900	Adder	0.22
945181	AF1-183	0.0674	Adder	0.08
945551	AF1-220 C	41.3722	50/50	41.3722
945552	AF1-220 E	27.5966	50/50	27.5966
957451	AF2-039 C	0.8477	50/50	0.8477
957452	AF2-039 E	0.5652	50/50	0.5652
957581	AF2-052 C	30.5509	50/50	30.5509
957582	AF2-052 E	14.8626	50/50	14.8626
957941	AF2-088 C	0.4082	50/50	0.4082
957942	AF2-088 E	0.2721	50/50	0.2721
958271	AF2-121 C	0.4370	Adder	0.97
958272	AF2-121 E	0.2913	Adder	0.65
959802	AF2-271 E	0.0700	Adder	0.16
960051	AF2-296 C	0.3700	Adder	0.82
960052	AF2-296 E	0.2467	Adder	0.55
NEWTON	NEWTON	0.1128	Confirmed LTF	0.1128
FARMERCITY	FARMERCITY	0.0058	Confirmed LTF	0.0058
G-007A	G-007A	0.3596	Confirmed LTF	0.3596
VFT	VFT	0.9546	Confirmed LTF	0.9546
CALDERWOOD	CALDERWOOD	0.0383	Confirmed LTF	0.0383
NY	NY	0.3241	Confirmed LTF	0.3241
PRAIRIE	PRAIRIE	0.2609	Confirmed LTF	0.2609
CHEOAH	CHEOAH	0.0385	Confirmed LTF	0.0385

<b>Bus #</b>	<b>Bus</b>	<b>Gendeliv MW Impact</b>	<b>Type</b>	<b>Full MW Impact</b>
<b>EDWARDS</b>	EDWARDS	0.0385	Confirmed LTF	0.0385
<b>TILTON</b>	TILTON	0.0687	Confirmed LTF	0.0687
<b>MADISON</b>	MADISON	0.0060	Confirmed LTF	0.0060
<b>GIBSON</b>	GIBSON	0.0573	Confirmed LTF	0.0573
<b>BLUEG</b>	BLUEG	0.1805	Confirmed LTF	0.1805
<b>TRIMBLE</b>	TRIMBLE	0.0579	Confirmed LTF	0.0579
<b>CATAWBA</b>	CATAWBA	0.0199	Confirmed LTF	0.0199

## 11.7 Queue Dependencies

The Queue Projects below are listed in one or more indices for the overloads identified in your report. These projects contribute to the loading of the overloaded facilities identified in your report. The percent overload of a facility and cost allocation you may have towards a particular reinforcement could vary depending on the action of these earlier projects. The status of each project at the time of the analysis is presented in the table. This list may change as earlier projects withdraw or modify their requests.

Queue Number	Project Name	Status
AA2-000	N/A	N/A
AB1-092	Moshannon-East Towanda 230kV	Active
AC1-025	Dale Summit	In Service
AD2-055	Moshannon-East Towanda 230 kV	Active
AD2-133	Eagle Valley 115kV	Active
AE1-147	Bellefonte 46 kV	Engineering and Procurement
AE2-001	Nittany-Zion 46 kV	Active
AE2-055	Shingletown-Boalsburg 46 kV	Suspended
AE2-113	Farmers Valley-Ridgeway 115 kV	Active
AE2-120	Graymont-Zion 46 kV	Active
AE2-121	Milesburg-Tanney Junction 46 kV	Active
AE2-126	Dubois-Curwensville 34.5 kV	Active
AE2-129	Philipsburg-Clarence 34.5 kV	Active
AE2-131	Philipsburg-Karthus 34.5	Active
AE2-248	Fillmore-Thompson Farm 46 kV	Active
AE2-262	Moshannon-Milesburg 230 kV	Active
AE2-263	Moshannon-Milesburg 230 kV	Active
AF1-043	Moshannon-East Towanda 230 kV	Active
AF1-068	Boalsburg-Centre Hall 46 kV	Active
AF1-086	Madera-Westover South 115 kV	Active
AF1-099	Moshannon-Milesburg 230 kV	Active
AF1-100	Shawville-Moshannon 230 kV	Active
AF1-103	Warren 34.5 kV	Active
AF1-112	Centre Hall-Boalsburg 46 kV	Active
AF1-132	Shingletown-Boalsburg 46 kV	Active
AF1-134	Philipsburg-Madera 34.5 kV	Active
AF1-142	Moshannon-Milesburg 230 kV	Active
AF1-149	Graymont-Zion 46 kV	Active
AF1-153	Motion-Ridgeway 46 kV	Active
AF1-155	Paper City-Wilcox 46 kV	Engineering and Procurement
AF1-181	Shawville 3 230 kV	Partially in Service - Under Construction
AF1-182	Shawville 4 230 kV	Partially in Service - Under Construction
AF1-183	Shawville 1 230 kV	Partially in Service - Under Construction
AF1-214	Nittany-Zion 46 kV	Active
AF1-220	Ridgeway-Whetstone 115 kV	Active
AF1-306	Squab Hollow 230 kV	Active
AF2-039	Shawville-Clearfield 34.5 kV	Active
AF2-052	Farmers Valley-Ridgeway 115 kV	Active
AF2-088	Shawville-Clearfield 34.5 kV II	Active

<b>Queue Number</b>	<b>Project Name</b>	<b>Status</b>
AF2-121	Philipsburg-Shawville 34.5 kV	Active
AF2-271	Pemberton-Sinking Valley 12.47 kV	Active
AF2-293	Beech Creek 46 kV	Active
AF2-295	Wilcox-Paper City 46 kV	Active
AF2-296	Madera 34.5 kV	Active

## 11.8 Contingency Descriptions

Contingency Name	Contingency Definition
<b>PN-P2-3-PN-230-7AT</b>	CONTINGENCY 'PN-P2-3-PN-230-7AT' /* FOREST STUCK 230KV BREAKER DISCONNECT BRANCH FROM BUS 200581 TO BUS 200593 CKT 1 /* 26FOREST 230 26GLADE 230 DISCONNECT BRANCH FROM BUS 200581 TO BUS 235971 CKT 1 /* 26FOREST 230 01SQUABHLLW 230 DISCONNECT BRANCH FROM BUS 200647 TO BUS 200581 CKT 1 /* 26FOREST 115 26FOREST 230 END
<b>AP-P2-2-WP-230-001T</b>	CONTINGENCY 'AP-P2-2-WP-230-001T' /* ELKO #2 230KV BUS DISCONNECT BRANCH FROM BUS 235175 TO BUS 235158 CKT 1 /* 01ELKO 230 01CARB 230 DISCONNECT BRANCH FROM BUS 235175 TO BUS 235236 CKT 1 /* 01ELKO 230 01QUEHAN 230 DISCONNECT BRANCH FROM BUS 235175 TO BUS 200726 CKT 1 /* 01ELKO 230 26SHAWVL 2 230 REDUCE BUS 237007 SHUNT BY 100 PERCENT /* 01ELKO CAP 138 DISCONNECT BUS 237007 /* 01ELKO CAP 138 END
<b>AP-P1-2-WP-230-323T</b>	CONTINGENCY 'AP-P1-2-WP-230-323T' /* SHINGLETOWN-LEWISTOWN 230KV APS-PN TIE DISCONNECT BRANCH FROM BUS 235248 TO BUS 200513 CKT 1 /* 01SHINGL 230 26LEWISTWN 230 END
<b>Base Case</b>	
<b>AP-P2-3-WP-230-446T</b>	CONTINGENCY 'AP-P2-3-WP-230-446T' /* ELKO-MOSHANNON STK BKR AT ELKO DISCONNECT BRANCH FROM BUS 200726 TO BUS 235175 CKT 1 /* 26SHAWVL 2 230 01ELKO 230 DISCONNECT BRANCH FROM BUS 235158 TO BUS 235175 CKT 1 /* 01CARB 230 01ELKO 230 DISCONNECT BRANCH FROM BUS 235175 TO BUS 235236 CKT 1 /* 01ELKO 230 01QUEHAN 230 DISCONNECT BRANCH FROM BUS 235220 TO BUS 235236 CKT 1 /* 01MOSHAN 230 01QUEHAN 230 DISCONNECT BRANCH FROM BUS 235236 TO BUS 236732 CKT 81 /* 01QUEHAN 230 01QUEHANNA 46 END

Contingency Name	Contingency Definition
<b>AP-P1-3-WP-230-326T</b>	CONTINGENCY 'AP-P1-3-WP-230-326T' /* SHINGLETOWN #82 230/46KV XFMR DISCONNECT BRANCH FROM BUS 235248 TO BUS 236711 CKT 82 /* 01SHINGL 230 01SHINGLTN 46 DISCONNECT BRANCH FROM BUS 235248 TO BUS 200513 CKT 1 /* 01SHINGL 230 26LEWISTWN 230 DISCONNECT BRANCH FROM BUS 235248 TO BUS 235970 CKT 1 /* 01SHINGL 230 01DALE 230 DISCONNECT BUS 237058 /*SHINGLETOWN 230 KV CAPACITOR END
<b>AP-P2-3-WP-230-443T *</b>	CONTINGENCY 'AP-P2-3-WP-230-443T *' / UPDATED CON AJK 3-31-16 DISCONNECT BRANCH FROM BUS 200726 TO BUS 235175 CKT 1 DISCONNECT BRANCH FROM BUS 235175 TO BUS 235236 CKT 1 DISCONNECT BUS 235158 END

## 12 Short Circuit Analysis

Short circuit analysis to be completed in the System Impact phase.

## 13 Affected Systems

### 13.1 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

## 14 Attachment 1: One Line Diagram