

Generation Interconnection Feasibility Study Report Queue Position X2-084

The Interconnection Customer (IC) has proposed an 19.6 MWE (7.45 MWC; 19.6 MW MFO) solar powered generating facility consisting of ground mounted fixed panel solar arrays to be located in East New Market, Dorchester County, Maryland. PJM studied X2-084 as a 19.6 MW injection into the Delmarva Power and Light (DPL) system and evaluated the project for compliance with reliability criteria for summer peak conditions in 2015. The planned in-service date, as stated in the Attachment N, is October 1, 2012.

Point(s) of Interconnection

The Interconnection Customer requested a Primary and Secondary Point of Interconnection (POI) be evaluated for the X2-084 project. The Primary POI selected was a distribution (12kV) level interconnection at the East New Market 69/12kV substation. The Secondary POI selected was a transmission (69kV) level interconnection at the East New Market 69kV substation. The results are provided in the Transmission Network Impacts section below.

Direct Connection Requirements

Primary Option

X2-084 will interconnect with the Delmarva Power and Light system at the East New Market 69/12kV substation as follows:

10 MWs will connect to a replacement of the T1 transformer; 9.6 MWs will connect to a new transformer.

Transmission Owner Scope of Direct Connection Work

The scope of work and estimated costs for the direct connection facilities is as follows:

1. Establish two new 12 kV feeders with 954 aluminum conductor from the East New Market Substation to the PV site – approximately .25 miles each
2. A utility operated recloser will be required on the customer tap that will have proper relaying and communication.
3. Utility grade primary metering will be required.
4. Generation telemetry and remote trip capabilities will be provided to the control center.
5. Perform a detailed time based study.
6. Protection, Planning, and other engineering departments will perform studies, design work, and prepare engineering estimates.
7. Transfer trip may be required.

The estimated cost to perform this work is as follows:

Estimated Costs			
East New Market Substation T1			
Replacement Transformer and Upgrades			\$3,300,000
954 AAC Express Feeder	0.25	Miles	\$100,000
Fiber Installation		Miles	\$12,500
Recloser w/ Relaying and Communications			\$50,000
Utility Grade Metering			\$20,000
SCADA Integration into EMS			\$10,000
Detailed Time Based Study			\$30,000
Various Departments Work			\$20,000
Subtotal Cost			\$3,542,500
Subtotal Cost with 18% Overheads			\$4,180,150
Approximate Total Cost with 15% Contingency			\$4,807,173

Estimated Costs			
East New Market Substation TX			
New Transformer, Feeder Terminal			\$1,700,000
954 AAC Express Feeder	0.25	Miles	\$100,000
Fiber Installation		Miles	\$12,500
Recloser w/ Relaying and Communications			\$50,000
Utility Grade Metering			\$20,000
SCADA Integration into EMS			\$10,000
Subtotal Cost			\$1,892,500
Subtotal Cost with 18% Overheads			\$2,233,150
Approximate Total Cost with 15% Contingency			\$2,568,123

Approximate Total Cost for Two Feeders: **\$7,375,296**

The estimated time to complete this work is **12 - 18 months** after receipt of a fully executed interconnection agreement.

Note: the above cost does not include the Contribution in Aid of Construction (CIAC) tax.

Special Operating Requirements

1. PHI will require the capability to remotely trip the generator from its System Operations facility. Such tripping may be facilitated by either a generator breaker, inverter (if so equipped), or a line recloser, depending upon the specific circumstances and the evaluation of PHI.
2. The Interconnection Customer will grant its permission to PJM for PJM to send PHI the following telemetry data that the Interconnection Customer sends to PJM: real time megawatts,

megavars, volts, amperes and status, and interval megawatt-hours, and megavar-hours. For generation larger than 10 MW, a direct telemetry connection to PHI System Operations will be required via a radial connection to PHI's telecommunications system or a rented data circuit, at the Interconnection Customer's cost.

3. The Interconnection Customer will be required to make provisions for a voice quality phone line within approximately 3 feet of each Company metering position to facilitate remote interrogation and data collection.
4. A mutually acceptable means of interrupting and disconnecting the generator with a visible break, able to be tagged and locked out, shall be worked out with DPL Distribution Engineering.

Interconnection Customer Scope of Direct Connection Work

The Interconnection Customer (IC) assumes full responsibility for design and construction of all facilities associated with the X2-084 generating station. Site preparation including grading and an access road, as necessary, is assumed to be by the IC.

The IC will be required to install metering and telemetry equipment to provide revenue metering and real-time telemetry data to PJM. The requirements for this equipment are listed in Appendix 2, Section 8 of Attachment O to the PJM Tariff, as well as PJM Manuals 01 and 14D. Protective relaying and metering design and installation must comply with Atlantic City Electric's Applicable Standards.

Inverter Requirements and Capabilities

The Interconnection Customer's inverter should have the following capabilities:

1. Voltage flicker reduction through dynamic VAR response
2. Ramp rate control
3. SCADA communications
4. Curtailment or other mitigation ability if high voltage were to occur
5. Low voltage and system disturbance ride through
6. Ability to receive and respond to a transfer trip or SCADA signal

The inverter shall operate in accordance with the IEEE 1547 series of standards that have been approved. While inverters should be capable of voltage stabilization thru dynamic VAR response and capable of low voltage and system disturbance ride through, neither of these capabilities shall be implemented until such time that the IEEE 1547 series of standards are revised and approved to include standards for these capabilities. At such time as these revised standards become available, the PV owner/operator shall cooperate with ACE to implement these capabilities with settings acceptable to Pepco Holdings, Inc. (ACE, DPL, and Pepco). Until such time, the inverters shall operate with a fixed power factor schedule as supplied by PHI.

Transmission Network Impacts

Potential transmission network impacts are as follows:

Generator Deliverability

*(Single or N-1 contingencies for the **Capacity** portion only of the interconnection)*

None

Multiple Facility Contingency

*(Double Circuit Tower Line, Line with Failed Breaker and, Bus Fault contingencies for the **Full** energy output.*

None

Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

Short Circuit

None

Stability Analysis

Not required due to project size.

Dynamic Analysis

A time-based dynamic study will commence during the System Impact Study phase of the project. Once complete, the results of the study will be reviewed and the proposed project will be evaluated for protection and coordination issues. Other required upgrades may be identified at that time.

Other Charges

It is anticipated that the Interconnection Customer will be charged for ongoing operation and maintenance of the attachment facilities. The methodology of calculating this charge is still under development.

New System Reinforcements

(Upgrades required to mitigate reliability criteria violations, i.e. “Network Impacts,” initially caused by the addition of this project’s generation)

None

Contribution to Previously Identified System Reinforcements

(Overloads initially caused by prior Queue positions with additional contribution to overloading by this project.)

None

Potential Congestion due to Local Energy Deliverability

(PJM also studied the delivery of the energy portion of the surrounding generation. Any potential problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with Network Upgrades to eliminate the operational restriction at their discretion by submitting a Transmission Interconnection Request. Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full deliverability for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which analyzes all overload conditions associated with the identified overloaded element(s). As a result of the aggregate energy resources in the area, the following violations were identified:

These are **not** required reliability upgrades.

None

Secondary Option

X2-084 was studied as a 19.6 MW injection at the East New Market 69kV substation.

Transmission Network Impacts

Potential transmission network impacts are as follows:

Generator Deliverability

*(Single or N-1 contingencies for the **Capacity** portion only of the interconnection)*

None

Multiple Facility Contingency

*(Double Circuit Tower Line, Line with Failed Breaker and, Bus Fault contingencies for the **Full** energy output.)*

None

Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. “Network Impacts”, identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

Short Circuit

None

Potential Congestion due to Local Energy Deliverability

(PJM also studied the delivery of the energy portion of the surrounding generation. Any potential problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with Network Upgrades to eliminate the operational restriction at their discretion by submitting a Transmission Interconnection Request. Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full deliverability for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which analyzes all overload conditions associated with the identified overloaded element(s). As a result of the aggregate energy resources in the area, the following violations were identified:

These are **not** required reliability upgrades.

None