



**Generation Interconnection
Feasibility Study Report
for
Queue Project AE2-333
BEDINGTON 138 KV
60 MW Capacity / 100 MW Energy**

July 2019

Table Of Contents

1	Preface.....	4
2	General.....	6
2.1	Point of Interconnection	7
	Primary POI.....	7
	Secondary POI.....	7
2.2	Cost Summary.....	7
3	Transmission Owner Scope of Work.....	8
4	Attachment Facilities	8
5	Direct Connection Cost Estimate.....	9
6	Non-Direct Connection Cost Estimate.....	10
7	Schedule.....	11
8	Transmission Owner Analysis.....	12
9	Interconnection Customer Requirements.....	13
	System Protection	13
	Compliance Issues and Interconnection Customer Requirements.....	13
	Power Factor Requirements	14
10	Revenue Metering and SCADA Requirements	15
10.1	PJM Requirements	15
10.1.1	Meteorological Data Reporting Requirement.....	15
10.2	APS Requirements	15
11	Network Impacts – Primary Point of Interconnection.....	16
11.1	Generation Deliverability	18
11.2	Multiple Facility Contingency	18
11.3	Contribution to Previously Identified Overloads.....	18
11.4	Potential Congestion due to Local Energy Deliverability.....	18
11.5	System Reinforcements.....	18
11.6	Short Circuit	20
12	Network Impacts – Secondary Point of Interconnection	21
12.1	Generation Deliverability	23
12.2	Multiple Facility Contingency	23
12.3	Contribution to Previously Identified Overloads.....	23

12.4	Potential Congestion due to Local Energy Deliverability.....	23
12.5	Short Circuit	25
13	Affected Systems	27
13.1	LG&E.....	27
13.2	MISO	27
13.3	TVA.....	27
13.4	Duke Energy Progress.....	27
13.5	NYISO	27
	Attachment 1 – One Line	28
	Attachment 2 – Project Location.....	29

1 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

An Interconnection Customer with a proposed new Customer Facility that has a Maximum Facility Output equal to or greater than 100 MW shall install and maintain, at its expense, phasor measurement units (PMUs). See Section 8.5.3 of Appendix 2 to the Interconnection Service Agreement as well as section 4.3 of PJM Manual 14D for additional information.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model. The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

2 General

The Interconnection Customer (IC), has proposed a Solar generating facility located in Berkley County, West Virginia. The installed facilities will have a total capability of 100 MW with 60 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is 12/1/2022. This study does not imply a TO commitment to this in-service date.

Queue Number	AE2-333
Project Name	BEDINGTON 138 kV
Interconnection Customer	
State	West Virginia
County	Berkeley
Transmission Owner	APS
MFO	100
MWE	100
MWC	60
Fuel	Solar
Basecase Study Year	2022

2.1 Point of Interconnection

Primary POI

The interconnection of the project at the Primary POI will be accomplished by expanding Bedington 138 kV substation by adding an additional breaker into the breaker-and-a-half scheme. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct the associated attachment facilities.

Attachment 1 shows a one-line diagram of the proposed primary direct connection facilities for the AE2-333 generation project to connect to the FirstEnergy (“FE”) transmission system. Attachment 2 provides the proposed location for the point of interconnection. IC will be responsible for constructing all of the facilities on its side of the POI, including the attachment facilities which connect the generator to the FE transmission system’s direct connection facilities.

Secondary POI

The interconnection of the project at a Secondary POI can be accomplished by constructing a new 138 kV three (3) breaker ring bus substation and looping the Bedington – Marlowe BMA 138 kV line into the new station. The new substation would be located approximately 3.9 miles from Bedington substation. A full scope of work or estimated cost is not provided for the proposed Secondary POI.

2.2 Cost Summary

The AE2-333 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$ 594,400
Direct Connection Network Upgrade	\$ 594,400
Non Direct Connection Network Upgrades	\$ 0
Total Costs	\$ 1,188,800

In addition, the AE2-333 project may be responsible for a contribution to the following costs

Description	Total Cost
System Upgrades	\$ 0

The costs provided above exclude the Contribution in Aid of Construction (“CIAC”) Federal Income Tax Gross Up charge. If, at a future date, it is determined that the CIAC Federal Income Tax Gross charge is required, the Transmission Owner shall be reimbursed by the Interconnection Customer for such taxes.

The required Attachment Facilities and Direct and Non-Direct Connection work for the interconnection of the AE2-333 generation project to the FE Transmission System is detailed in the following sections. The associated one-line with the generation project Attachment Facilities and the Primary Direct and Non-Direct Connection facilities are shown in Attachment 1.

3 Transmission Owner Scope of Work

The interconnection of the project at the Primary POI will be accomplished by expanding Bedington 138 kV substation by adding an additional breaker into the breaker-and-a-half scheme. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct the associated attachment facilities.

4 Attachment Facilities

The total preliminary cost estimate for the Attachment work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Install line exit take-off structure, foundations, disconnect switch and associated equipment at Bedington substation	\$ 594,400
Total Attachment Facility Costs	\$ 594,400

5 Direct Connection Cost Estimate

The total preliminary cost estimate for the Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Add one new terminal to existing Bedington 138 kV substation due to AE2-333 developer interconnection.	\$ 594,400
Total Direct Connection Facility Costs	\$ 594,400

6 Non-Direct Connection Cost Estimate

There is no non-Direct Connection scope of work required for this project.

7 Schedule

Based on the scope of work for the Attachment Facilities and the Direct and Non-Direct Connection facilities, it is expected to take a minimum of 10 months after the signing of an Interconnection Construction Service Agreement to complete the installation. This includes the requirement for the IC to make a preliminary payment that compensates FE for the first three months of the engineering design work that is related to the construction of the interconnection substation. This assumes that there will be no environmental issues with any of the new properties associated with this project, that there will be no delays in acquiring the necessary permits for implementing the defined direct connection and network upgrades, and that all transmission system outages will be allowed when requested.

The schedule for the required Network Impact Reinforcements will be more clearly identified in future study phases. The estimate elapsed time to complete each of the required reinforcements is identified in the “System Reinforcements” section of the report.

8 Transmission Owner Analysis

FE performed an analysis of its underlying transmission <100 kV system. The AE2-333 project did not contribute to any overloads on the FE transmission system.

At the proposed Secondary POI, the AE2-333 project did not contribute to any overloads on the FE transmission system

9 Interconnection Customer Requirements

System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. Preliminary Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

The IC has requested a non-standard GSU transformer winding configuration. This transformer is in violation of section 14.2.6 of FE's "Requirements for Transmission Connected Facilities" document and will not be accepted. The GSU transformer must have a grounded wye connection on the high (utility) side and a delta connection on the low (generator) side. Notification to the developer of the transformer winding configuration requirement has been previously communicated, however an updated project single line has not been received.

Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. In particular, the IC is responsible for the following:

1. The purchase and installation of a fully rated 138 kV circuit breaker to protect the AE2-333 generator lead line. A single circuit breaker must be used to protect this line; if the project has several GSU transformers, the individual GSU transformer breakers cannot be used to protect this line.
2. The purchase and installation of the minimum required FE generation interconnection relaying and control facilities. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.
3. The purchase and installation of supervisory control and data acquisition ("SCADA") equipment to provide information in a compatible format to the FE Transmission System Control Center.
4. Compliance with the FE and PJM generator power factor and voltage control requirements.
5. The execution of a back-up service agreement to serve the customer load supplied from the AE2-333 generation project metering point when the units are out-of-service. This assumes the intent of the IC is to net the generation with the load.

The IC will also be required to meet all PJM, ReliabilityFirst, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the

submission of the generator model and protection data required to satisfy the PJM and ReliabilityFirst audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the FE system.

Power Factor Requirements

The IC shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the FE transmission system.

10 Revenue Metering and SCADA Requirements

10.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

10.1.1 Meteorological Data Reporting Requirement

The solar generation facility shall provide the Transmission Provider with site-specific meteorological data including:

- Temperature (degrees Fahrenheit)
- Atmospheric pressure (hectopascals)
- Irradiance
- Forced outage data

10.2 APS Requirements

The IC will be required to comply with all FE revenue metering requirements for generation interconnection customers which can be found in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>

11 Network Impacts – Primary Point of Interconnection

The Queue Project AE2-333 was evaluated as a 100 MW (Capacity 60 MW) injection at Bedington 138 kV substation in the APS area. Project AE2-333 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-333 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

11.1 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

11.2 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

11.3 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

11.4 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

11.5 System Reinforcements

None

Short Circuit

11.6 Short Circuit

The following Breakers are overduty: None

12 Network Impacts – Secondary Point of Interconnection

The Queue Project AE2-333 was evaluated as a 100.0 MW (Capacity 60.0 MW) injection tapping the Bedington to Marlow 138kV line in the APS area. Project AE2-333 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-333 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

12.1 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

12.2 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

12.3 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

12.4 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

Short Circuit

12.5 Short Circuit

The following Breakers are overduty : None

Affected Systems

13 Affected Systems

13.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

13.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

13.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

13.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

13.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

Attachment 1 – One Line

Attachment 2 – Project Location