



Generation Interconnection

Feasibility Study Report

for

Queue Project AE2-275

JK SMITH-FAWKES 138 KV

65.4 MW Capacity / 90 MW Energy

July, 2019

Table of Contents

- 1 Preface..... 4
- 2 General..... 5
 - 2.1 Point of Interconnection 6
 - 2.2 Cost Summary..... 6
- 3 Transmission Owner Scope of Work..... 7
- 4 Attachment Facilities 7
- 5 Direct Connection Cost Estimate..... 8
- 6 Non-Direct Connection Cost Estimate..... 9
- 7 Incremental Capacity Transfer Rights (ICTRs) 10
- 8 Interconnection Customer Requirements..... 11
- 9 Revenue Metering and SCADA Requirements 11
 - 9.1 PJM Requirements 11
 - 9.2 EKPC Requirements 11
- 10 Network Impacts Option-1 12
- 11 Generation Deliverability 14
- 12 Multiple Facility Contingency 14
- 13 Contribution to Previously Identified Overloads 14
- 14 Potential Congestion due to Local Energy Deliverability..... 14
- 15 System Reinforcements..... 16
- 16 Flow Gate Details 17
 - 16.1 Index 1 18
 - 16.2 Index 2 19
 - 16.3 Index 3 21
 - 16.4 Index 4 22
- 17 Affected Systems 25
 - 17.1 LG&E..... 25
 - 17.2 MISO 25
 - 17.3 TVA..... 25
 - 17.4 Duke Energy Progress..... 25
 - 17.5 NYISO 25
- 18 Short Circuit..... 28

19	Point of Interconnection Option-2.....	29
20	Network Impacts Option-2	29
21	Generation Deliverability	31
22	Multiple Facility Contingency	31
23	Contribution to Previously Identified Overloads	31
24	Potential Congestion due to Local Energy Deliverability.....	31
25	Flow Gate Details	33
25.1	Index 1	34
25.2	Index 2	37
25.3	Index 3	39
25.4	Index 4.....	40
26	Affected Systems	43
26.1	LG&E.....	43
26.2	MISO	43
26.3	TVA.....	43
26.4	Duke Energy Progress.....	43
26.5	NYISO	43
27	Short Circuit.....	46

1 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model. The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

2 General

The Interconnection Customer (IC), has proposed a Solar generating facility located in Madison County, Kentucky. The installed facilities will have a total capability of 90 MW with 65.4 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is 6/1/2022. This study does not imply a TO commitment to this in-service date.

Queue Number	AE2-275
Project Name	JK SMITH-FAWKES 138 KV
State	Kentucky
County	Madison
Transmission Owner	EKPC
MFO	90
MWE	90
MWC	65.4
Fuel	Solar
Basecase Study Year	2022

2.1 Point of Interconnection

AE2-275 will interconnect with the EKPC transmission system tapping the JK Smith to Fawkes 138kV line.

2.2 Cost Summary

The AE2-275 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$250,000
Direct Connection Network Upgrade	\$5,650,000
Non Direct Connection Network Upgrades	\$100,000
Total Costs	\$6,000,000

In addition, the AE2-275 project may be responsible for a contribution to the following costs

Description	Total Cost
System Upgrades	\$10,300,000

Cost allocations for these upgrades will be provided in the System Impact Study Report.

3 Transmission Owner Scope of Work

4 Attachment Facilities

The total preliminary cost estimate for the Attachment work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Install a 138 kV switch structure at the point of demarcation.	\$250,000
Total Attachment Facility Costs	\$250,000

5 Direct Connection Cost Estimate

The total preliminary cost estimate for the Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Build 138kV switching station along the JK Smith - Fawke 138kV line, includes line work. Estimated Time to Construct: 24 months	\$5,650,000
Total Direct Connection Facility Costs	\$5,650,000

6 Non-Direct Connection Cost Estimate

The total preliminary cost estimate for the Non-Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Relaying upgrades at the remote end substations	\$100,000
Total Non-Direct Connection Facility Costs	\$100,000

7 Incremental Capacity Transfer Rights (ICTRs)

Will be determined at a later study phase

8 Interconnection Customer Requirements

1. An Interconnection Customer entering the New Services Queue on or after October 1, 2012 with a proposed new Customer Facility that has a Maximum Facility Output equal to or greater than 100 MW shall install and maintain, at its expense, phasor measurement units (PMUs). See Section 8.5.3 of Appendix 2 to the Interconnection Service Agreement as well as section 4.3 of PJM Manual 14D for additional information.
2. The Interconnection Customer may be required to install and/or pay for metering as necessary to properly track real time output of the facility as well as installing metering which shall be used for billing purposes. See Section 8 of Appendix 2 to the Interconnection Service Agreement as well as Section 4 of PJM Manual 14D for additional information.

9 Revenue Metering and SCADA Requirements

9.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Sections 24.1 and 24.2.

9.2 EKPC Requirements

The Interconnection Customer will be required to comply with all EKPC Revenue Metering Requirements for Generation Interconnection Customers. The Revenue Metering Requirements may be found within the "EKPC Facility Connection Requirements" document located at the following link:

<http://www.pjm.com/planning/design-engineering/to-tech-standards/ekpc.aspx>

10 Network Impacts Option-1

The Queue Project AE2-275 was evaluated as a 90.0 MW (Capacity 65.4 MW) injection tapping the JK Smith to Fawkes 138kV line in the EKPC area. Project AE2-275 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-275 was studied with a commercial probability of 0.53. Potential network impacts were as follows:

Summer Peak Load Flow

11 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8926448	342574	4DALE	EKPC	342565	4BOONESBOR T	EKPC	1	EKPC_P1-2_JKS-NCLA345	single	296.0	88.21	92.42	DC	12.47

12 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

13 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8926740	342559	4BOONE CO	EKPC	250054	08LONG BR	DEO&K	1	DEO&K-DAY-EKPC.C5 4541MELDAHLSRCLCKSTUARTSPURLOC KDPLEK	tower	284.0	102.58	103.59	DC	6.38
8926428	342607	4JK SMITH	EKPC	342574	4DALE	EKPC	1	EKPC_P1-2_JKS-NCLA345	single	284.0	102.07	103.89	DC	5.17
8925718	342838	7SPURLO CK	EKPC	253077	09STUAR T	DAY	1	.138.DEO&K.C2 816_SILVERGROVE	breaker	1421.0	120.78	121.47	DC	21.58
8925719	342838	7SPURLO CK	EKPC	253077	09STUAR T	DAY	1	.345.DEO&K.C2 1493_RED BANK	breaker	1421.0	120.66	121.35	DC	21.56
8926278	342838	7SPURLO CK	EKPC	253077	09STUAR T	DAY	1	.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545	single	1421.0	115.68	116.18	DC	15.67
8926281	342838	7SPURLO CK	EKPC	253077	09STUAR T	DAY	1	Base Case	single	1240.0	111.71	112.9	DC	14.71

14 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8926085	324114	7TRIMBLE CO	LGEE	248000	06CLIFTY	OVEC	1	Base Case	operation	1134.0	155.96	156.95	DC	11.57
8926447	342574	4DALE	EKPC	342565	4BOONESBOR T	EKPC	1	EKPC_P1-2_JKS-NCLA345	operation	296.0	84.01	89.81	DC	17.15
8926429	342607	4JK SMITH	EKPC	342574	4DALE	EKPC	1	EKPC_P1-2_JKS-NCLA345	operation	284.0	99.52	100.65	DC	7.12
8926277	342838	7SPURLOCK	EKPC	253077	09STUART	DAY	1	.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545	operation	1421.0	120.6	121.29	DC	21.56
8926279	342838	7SPURLOCK	EKPC	253077	09STUART	DAY	1	Base Case	operation	1240.0	115.44	116.17	DC	20.25

15 System Reinforcements

ID	Index	Facility	Upgrade Description	Cost
8926448	1	4DALE 138.0 kV - 4BOONESBOR T 138.0 kV Ckt 1	8926448 No violation. Post queue loading less than 100%.	\$0
8926281,8925719,8925718,8926278	4	7SPURLOCK 345.0 kV - 09STUART 345.0 kV Ckt 1	r190002 (353) : Replace substation riser conductor with 2500AAC (parallel) Project Type : FAC Cost : \$100,000 Time Estimate : 12.0 Months r190004 (355) : Reconductor line with 795 ACCR high temperature conductor in a twin bundle Project Type : FAC Cost : \$10,000,000 Time Estimate : 18.0 Months r0005 (640) : No Violation. EKPC emergency rating 1792 MVA. Project Type : FAC Cost : \$0 Time Estimate : N/A Months	\$10,100,000
8926428	3	4JK SMITH 138.0 kV - 4DALE 138.0 kV Ckt 1	r0011 (648) : No violation. Rating Correction: [Rate A: 229, Rate B: 296, Rate C: 358] Project Type : FAC Cost : \$0 Time Estimate : N/A Months	\$0
8926740	2	4BOONE CO 138.0 kV - 08LONGBR 138.0 kV Ckt 1	8926740 Facility is 100% Owned by EKPC. No DL reinforcements needed. EKPC r0009 (646) : Increase MOT of Boone-Longbranch 138kV line section 954 MCM conductor to 275F (~2.25 miles) Project Type : FAC Cost : \$200,000 Time Estimate : 6 mo Months	\$200,000
			TOTAL COST	\$10,300,000

16 Flow Gate Details

The following appendices contain additional information about each flowgate presented in the body of the report. For each appendix, a description of the flowgate and its contingency was included for convenience. However, the intent of the appendix section is to provide more information on which projects/generators have contributions to the flowgate in question. Although this information is not used "as is" for cost allocation purposes, it can be used to gage other generators impact. It should be noted the generator contributions presented in the appendices sections are full contributions, whereas in the body of the report, those contributions take into consideration the commercial probability of each project.

16.1 Index 1

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8926448	342574	4DALE	EKPC	342565	4BOONESBOR T	EKPC	1	EKPC_P1- 2_JKS- NCLA345	single	296.0	88.21	92.42	DC	12.47

Bus #	Bus	MW Impact
342900	1COOPER1 G	0.77
342903	1COOPER2 G	1.49
342918	1JKCT 1G	2.5
342921	1JKCT 2G	2.5
342924	1JKCT 3G	2.5
342927	1JKCT 4G	1.66
342930	1JKCT 5G	1.65
342933	1JKCT 6G	1.66
342936	1JKCT 7G	1.66
342939	1JKCT 9G	1.34
342942	1JKCT 10G	1.34
342945	1LAUREL 1G	0.58
935011	AD1-134	12.57
936571	AD2-072 C O1	4.55
936821	AD2-105 C O1	2.24
942411	AE2-254 C O1	2.81
942591	AE2-275 C O1	12.47
942891	AE2-308 C O1	38.38
CARR	CARR	0.03
CBM-S1	CBM-S1	4.43
CBM-S2	CBM-S2	1.26
CBM-W1	CBM-W1	0.54
CBM-W2	CBM-W2	19.29
CIN	CIN	0.92
CPL	CPL	0.39
IPL	IPL	0.35
LGEE	LGEE	0.86
MEC	MEC	1.91
RENSELAER	RENSELAER	0.02
WEC	WEC	0.09

16.2 Index 2

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPAC T
8926740	342559	4BOON E CO	EKPC	250054	08LONGB R	DEO&K	1	DEO&K-DAY-EKPC.C5 4541MELDAHLSPRLCKSTUARTSPURLOCK DPLEK	tower	284.0	102.58	103.59	DC	6.38

Bus #	Bus	MW Impact
342957	1SPURLK1G	4.49
342960	1SPURLK2G	7.03
342963	1SPURLK3G	3.69
342966	1SPURLK4G	3.69
925981	AC1-074 C O1	9.17
925982	AC1-074 E O1	3.93
932551	AC2-075 C	2.18
932552	AC2-075 E	1.1
935011	AD1-134	5.06
936281	AD2-036 C	6.55
936282	AD2-036 E	3.27
936381	AD2-048 C	5.97
936382	AD2-048 E	2.98
936571	AD2-072 C O1	3.35
936572	AD2-072 E O1	1.64
939141	AE1-144 C O1	8.69
939142	AE1-144 E O1	4.31
940531	AE2-038 C O1	5.79
940532	AE2-038 E O1	2.87
941411	AE2-138 C	16.37
941412	AE2-138 E	6.05
941981	AE2-210 C O1	5.66
941982	AE2-210 E O1	2.13
942231	AE2-235 C O1	4.52
942232	AE2-235 E O1	1.95
942411	AE2-254 C O1	1.61
942412	AE2-254 E O1	1.07
942591	AE2-275 C O1	4.63
942592	AE2-275 E O1	1.74
942891	AE2-308 C O1	8.29
942892	AE2-308 E O1	3.01
943111	AE2-339 C	3.03
943112	AE2-339 E	1.49
CARR	CARR	0.05
CBM-S1	CBM-S1	4.34
CBM-S2	CBM-S2	0.84
CBM-W1	CBM-W1	0.14
CBM-W2	CBM-W2	15.68
CIN	CIN	1.16
CPL	CPL	0.25

Bus #	Bus	MW Impact
G-007	G-007	0.12
IPL	IPL	0.49
LGEE	LGEE	1.78
MEC	MEC	1.39
O-066	O-066	0.78
RENSELAER	RENSELAER	0.04
WEC	WEC	0.04

16.3 Index 3

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8926428	342607	4JK SMITH	EKPC	342574	4DALE	EKPC	1	EKPC_P1-2_JKS-NCLA345	single	284.0	102.07	103.89	DC	5.17

Bus #	Bus	MW Impact
342918	1JKCT 1G	2.72
342921	1JKCT 2G	2.72
342924	1JKCT 3G	2.72
342927	1JKCT 4G	1.81
342930	1JKCT 5G	1.8
342933	1JKCT 6G	1.81
342936	1JKCT 7G	1.81
342939	1JKCT 9G	1.41
342942	1JKCT 10G	1.41
935011	AD1-134	11.75
942591	AE2-275 C O1	5.17
942893	AE2-308 BAT	13.91
CARR	CARR	0.03
CBM-S1	CBM-S1	2.16
CBM-S2	CBM-S2	0.65
CBM-W1	CBM-W1	0.07
CBM-W2	CBM-W2	9.69
CIN	CIN	0.44
CPLE	CPLE	0.2
IPL	IPL	0.15
LGEE	LGEE	0.31
MEC	MEC	0.86
RENSELAER	RENSELAER	0.02
WEC	WEC	0.02

16.4 Index 4

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8925719	342838	7SPURLOCK	EKPC	253077	09STUART	DAY	1	.345.DEO&K.C2 1493_RED BANK	breaker	1421.0	120.66	121.35	DC	21.56

Bus #	Bus	MW Impact
251968	08ZIMRHP	33.39
251969	08ZIMRLP	18.29
251970	08MELDL1	1.69
251971	08MELDL2	1.69
251972	08MELDL3	1.7
342957	1SPURLK1G	17.48
342960	1SPURLK2G	33.1
342963	1SPURLK3G	17.39
342966	1SPURLK4G	17.39
925981	AC1-074 C O1	15.31
925982	AC1-074 E O1	6.56
926951	AC1-182	0.8
932551	AC2-075 C	3.64
932552	AC2-075 E	1.83
935011	AD1-134	17.48
936281	AD2-036 C	10.93
936282	AD2-036 E	5.47
936381	AD2-048 C	11.97
936382	AD2-048 E	5.97
936571	AD2-072 C O1	9.64
936572	AD2-072 E O1	4.73
936821	AD2-105 C O1	4.08
936822	AD2-105 E O1	5.98
936831	AD2-106 C O1	2.82
936832	AD2-106 E O1	3.9
936841	AD2-107 C O1	2.23
936842	AD2-107 E O1	3.08
939131	AE1-143 C	7.15
939132	AE1-143 E	3.54
939141	AE1-144 C O1	32.16
939142	AE1-144 E O1	15.96
940531	AE2-038 C O1	21.45
940532	AE2-038 E O1	10.63
941411	AE2-138 C	62.82
941412	AE2-138 E	23.23
941961	AE2-208	2.43
941981	AE2-210 C O1	21.29
941982	AE2-210 E O1	8.01
942231	AE2-235 C O1	14.72
942232	AE2-235 E O1	6.36
942411	AE2-254 C O1	4.87

Bus #	Bus	MW Impact
942412	AE2-254 E O1	3.25
942591	AE2-275 C O1	15.67
942592	AE2-275 E O1	5.89
942891	AE2-308 C O1	26.79
942892	AE2-308 E O1	9.74
943111	AE2-339 C	9.06
943112	AE2-339 E	4.46
CARR	CARR	0.51
CBM-S1	CBM-S1	13.72
CBM-S2	CBM-S2	1.86
CBM-W1	CBM-W1	3.85
CBM-W2	CBM-W2	65.29
CIN	CIN	7.07
CPLE	CPLE	0.39
G-007	G-007	1.38
IPL	IPL	4.27
LGEE	LGEE	5.18
MEC	MEC	7.85
O-066	O-066	8.9
RENSSELAER	RENSSELAER	0.4
WEC	WEC	0.68

Affected Systems

17 Affected Systems

17.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

17.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

17.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

17.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

17.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

Contingency Name	Contingency Definition
DEO&K-DAY-EKPC.C5 4541MELDAHLSPLRCKSTUARTSPURLOC KDPLEK	CONTINGENCY 'DEO&K-DAY-EKPC.C5 4541MELDAHLSPLRCKSTUARTSPURLOCKDPLEK' OPEN BRANCH FROM BUS 342838 TO BUS 249581 CKT 1 OPEN BRANCH FROM BUS 253077 TO BUS 342838 CKT 1 END
EKPC_P1-2_JKS-NCLA345	CONTINGENCY 'EKPC_P1-2_JKS-NCLA345' /* JK SMITH - N CLARK OPEN BRANCH FROM BUS 342832 TO BUS 342835 CKT 1 /* 342832 7JK SMITH 345.00 342835 7N CLARK 345.00 END
.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545	CONTINGENCY '.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545' OPEN BRANCH FROM BUS 249573 TO BUS 249577 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249571 TO BUS 249573 CKT 1 END
.138.DEO&K.C2 816_SILVERGROVE	CONTINGENCY '.138.DEO&K.C2 816_SILVERGROVE' OPEN BRANCH FROM BUS 249573 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249988 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 250042 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 250052 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 250053 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249571 TO BUS 249573 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 249577 CKT 1 END
.345.DEO&K.C2 1493_RED BANK	CONTINGENCY '.345.DEO&K.C2 1493_RED BANK' OPEN BRANCH FROM BUS 249571 TO BUS 249573 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 249577 CKT 1 OPEN BRANCH FROM BUS 249571 TO BUS 250092 CKT 1 END
Base Case	

Short Circuit

18 Short Circuit

The following Breakers are overduty

None.

19 Point of Interconnection Option-2

AE2-275 will interconnect with the EKPC transmission system tapping the JK Smith to Union City 138kV line.

20 Network Impacts Option-2

The Queue Project AE2-275 was evaluated as a 90.0 MW (Capacity 65.4 MW) injection tapping the JK Smith to Union City 138kV line in the EKPC area. Project AE2-275 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-275 was studied with a commercial probability of 0.53. Potential network impacts were as follows:

Summer Peak Load Flow

21 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

22 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
7333072	253038	09KILLEN	DAY	242938	05MARQUI	AEP	1	AEP_P4_#2085_05BEATTY 345_304C	breaker	1372.0	99.99	100.28	DC	8.89

23 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8926740	34259	4BOONE CO	EKPC	250054	08LONGBR	DEO&K	1	DEO&K-DAY-EKPC.C5 4541MELDAHLSRCLKSTUARTSPURLOC KDPLEK	tower	284.0	102.7	103.71	DC	6.3
8926428	342607	4JK SMITH	EKPC	342574	4DALE	EKPC	1	EKPC_P1-2_JKS-NCLA345	single	284.0	102.07	104.47	DC	6.83
8925718	342838	7SPURLO CK	EKPC	253077	09STUART	DAY	1	.138.DEO&K.C2 816_SILVERGROVE	breaker	1421.0	120.85	121.53	DC	21.43
8925719	342838	7SPURLO CK	EKPC	253077	09STUART	DAY	1	.345.DEO&K.C2 1493_RED BANK	breaker	1421.0	120.74	121.42	DC	21.4
8926278	342838	7SPURLO CK	EKPC	253077	09STUART	DAY	1	.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545	single	1421.0	115.83	116.32	DC	15.55
8926281	342838	7SPURLO CK	EKPC	253077	09STUART	DAY	1	Base Case	single	1240.0	111.94	113.12	DC	14.6

24 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

ID	FROM BUS#	FROM BUS AREA	TO BUS#	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT		
8926085	324114	7TRIMBLE CO	LGEE	248000	06CLIFTY	OVEC	1	Base Case	operation	1134.0	155.85	156.83	DC	11.43
8926429	342607	4JK SMITH	EKPC	342574	4DALE	EKPC	1	EKPC_P1-2_JKS-NCLA345	operation	284.0	99.52	101.02	DC	9.39
8926277	342838	7SPURLOCK	EKPC	253077	09STUART	DAY	1	.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545	operation	1421.0	120.67	121.35	DC	21.4
8926279	342838	7SPURLOCK	EKPC	253077	09STUART	DAY	1	Base Case	operation	1240.0	115.75	116.48	DC	20.1

25 Flow Gate Details

The following appendices contain additional information about each flowgate presented in the body of the report. For each appendix, a description of the flowgate and its contingency was included for convenience. However, the intent of the appendix section is to provide more information on which projects/generators have contributions to the flowgate in question. Although this information is not used "as is" for cost allocation purposes, it can be used to gage other generators impact. It should be noted the generator contributions presented in the appendices sections are full contributions, whereas in the body of the report, those contributions take into consideration the commercial probability of each project.

25.1 Index 1

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
7333072	253038	09KILLEN	DAY	242938	05MARQUI	AEP	1	AEP_P4_#2085_05BEATTY 345_304C	breaker	1372.0	99.99	100.28	DC	8.89

Bus #	Bus	MW Impact
253038	09KILLEN	293.42
253077	09STUART	459.74
902531	W2-040 C	0.56
902532	W2-040 E	0.92
904722	V4-073 E	0.12
913222	Y1-054 E	1.57
914372	Y2-111 E	0.9
915582	Y3-080 E	0.6
915662	Y3-099 E	0.14
915672	Y3-100 E	0.14
916182	Z1-065 E	0.48
916272	Z1-080 E	0.41
918802	AA1-099 E	0.27
925242	AB2-178 E	1.37
925921	AC1-068 C	7.45
925922	AC1-068 E	3.48
925931	AC1-069 C	7.45
925932	AC1-069 E	3.48
925981	AC1-074 C O1	6.6
925982	AC1-074 E O1	2.83
926061	AC1-085 C O1	32.34
926062	AC1-085 E O1	52.76
926101	AC1-089 C O1	3.85
926102	AC1-089 E O1	6.28
926791	AC1-165 C	7.36
926792	AC1-165 E	3.57
926801	AC1-166 C	7.36
926802	AC1-166 E	3.57
930062	AB1-014 E	12.71
931181	AB1-169	289.54
932462	AC2-066 E	0.41
932481	AC2-068 C	1.9
932482	AC2-068 E	3.12
932551	AC2-075 C	1.57
932552	AC2-075 E	0.79
932661	AC2-088 C O1	7.14
932662	AC2-088 E O1	5.88
935011	AD1-134	7.2
935031	AD1-136 C	1.0
935032	AD1-136 E	0.86
935041	AD1-140 C O1	6.21
935042	AD1-140 E O1	5.13

Bus #	Bus	MW Impact
936251	AD2-031 C O1	1.99
936252	AD2-031 E O1	3.25
936281	AD2-036 C	4.71
936282	AD2-036 E	2.36
936381	AD2-048 C	5.23
936382	AD2-048 E	2.61
936571	AD2-072 C O1	4.58
936572	AD2-072 E O1	2.25
937151	AD2-151 C O1	7.04
937152	AD2-151 E O1	9.72
938051	AE1-007 C	0.55
938052	AE1-007 E	0.89
938271	AE1-040 C O1	2.16
938272	AE1-040 E O1	1.09
938921	AE1-120	7.22
939141	AE1-144 C O1	12.59
939142	AE1-144 E O1	6.25
940531	AE2-038 C O2	7.88
940532	AE2-038 E O2	3.93
941411	AE2-138 C O2	24.75
941412	AE2-138 E O2	9.15
941981	AE2-210 C O2	8.64
941982	AE2-210 E O2	3.25
942091	AE2-221 C	29.2
942092	AE2-221 E	19.47
942231	AE2-235 C O2	7.47
942232	AE2-235 E O2	3.23
942411	AE2-254 C O2	2.19
942412	AE2-254 E O2	1.46
942521	AE2-267 C O2	2.55
942522	AE2-267 E O2	1.58
942591	AE2-275 C O2	6.46
942592	AE2-275 E O2	2.43
942781	AE2-296 O2	7.77
942891	AE2-308 C O1	10.77
942892	AE2-308 E O1	3.92
942951	AE2-315	1.86
942981	AE2-320 C O2	16.5
942982	AE2-320 E O2	8.16
943111	AE2-339 C	3.77
943112	AE2-339 E	1.86
943191	AE2-318 C	9.39
943192	AE2-318 E	4.58
943201	AE2-319 C O2	16.5
943202	AE2-319 E O2	8.16
CARR	CARR	0.41
CATAWBA	CATAWBA	0.1
CBM-S1	CBM-S1	7.51
CBM-W1	CBM-W1	9.16
CBM-W2	CBM-W2	50.15
CIN	CIN	8.01
G-007	G-007	1.21

Bus #	Bus	MW Impact
HAMLET	HAMLET	0.25
IPL	IPL	5.46
LGEE	LGEE	3.55
MEC	MEC	8.84
MECS	MECS	3.74
O-066	O-066	7.77
RENSSELAER	RENSSELAER	0.33
WEC	WEC	1.22

25.2 Index 2

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPAC T
8926740	342559	4BOON E CO	EKPC	250054	08LONGB R	DEO& K	1	DEO&K-DAY-EKPC.C5 4541MELDAHLSRRLCKSTUARTSPURLOCK DPLEK	tower	284.0	102.7	103.71	DC	6.3

Bus #	Bus	MW Impact
342957	1SPURLK1G	4.49
342960	1SPURLK2G	7.03
342963	1SPURLK3G	3.69
342966	1SPURLK4G	3.69
925981	AC1-074 C O1	9.16
925982	AC1-074 E O1	3.93
932551	AC2-075 C	2.18
932552	AC2-075 E	1.1
935011	AD1-134	5.06
936281	AD2-036 C	6.55
936282	AD2-036 E	3.27
936381	AD2-048 C	5.97
936382	AD2-048 E	2.98
936571	AD2-072 C O1	3.35
936572	AD2-072 E O1	1.64
939141	AE1-144 C O1	8.69
939142	AE1-144 E O1	4.31
940531	AE2-038 C O2	5.46
940532	AE2-038 E O2	2.72
941411	AE2-138 C O2	16.44
941412	AE2-138 E O2	6.08
941981	AE2-210 C O2	5.64
941982	AE2-210 E O2	2.12
942231	AE2-235 C O2	5.02
942232	AE2-235 E O2	2.17
942411	AE2-254 C O2	1.62
942412	AE2-254 E O2	1.08
942591	AE2-275 C O2	4.58
942592	AE2-275 E O2	1.72
942891	AE2-308 C O1	7.72
942892	AE2-308 E O1	2.81
943111	AE2-339 C	3.03
943112	AE2-339 E	1.49
CARR	CARR	0.05
CBM-S1	CBM-S1	4.34
CBM-S2	CBM-S2	0.84
CBM-W1	CBM-W1	0.14
CBM-W2	CBM-W2	15.68
CIN	CIN	1.16
CPLE	CPLE	0.25

Bus #	Bus	MW Impact
G-007	G-007	0.12
IPL	IPL	0.49
LGEE	LGEE	1.78
MEC	MEC	1.39
O-066	O-066	0.78
RENSELAER	RENSELAER	0.04
WEC	WEC	0.04

25.3 Index 3

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8926428	342607	4JK SMITH	EKPC	342574	4DALE	EKPC	1	EKPC_P1-2_JKS-NCLA345	single	284.0	102.07	104.47	DC	6.83

Bus #	Bus	MW Impact
342918	1JKCT 1G	2.72
342921	1JKCT 2G	2.72
342924	1JKCT 3G	2.72
342927	1JKCT 4G	1.81
342930	1JKCT 5G	1.8
342933	1JKCT 6G	1.81
342936	1JKCT 7G	1.81
342939	1JKCT 9G	1.41
342942	1JKCT 10G	1.41
935011	AD1-134	11.75
942591	AE2-275 C O2	6.83
CARR	CARR	0.03
CBM-S1	CBM-S1	2.16
CBM-S2	CBM-S2	0.65
CBM-W1	CBM-W1	0.07
CBM-W2	CBM-W2	9.69
CIN	CIN	0.44
CPLE	CPLE	0.2
IPL	IPL	0.15
LGEE	LGEE	0.31
MEC	MEC	0.86
RENSELAER	RENSELAER	0.02
WEC	WEC	0.02

25.4 Index 4

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
8925719	342838	7SPURLOCK	EKPC	253077	09STUART	DAY	1	.345.DEO&K.C2 1493_RED BANK	breaker	1421.0	120.74	121.42	DC	21.4

Bus #	Bus	MW Impact
251968	08ZIMRHP	33.39
251969	08ZIMRLP	18.29
251970	08MELDL1	1.69
251971	08MELDL2	1.69
251972	08MELDL3	1.7
342957	1SPURLK1G	17.48
342960	1SPURLK2G	33.1
342963	1SPURLK3G	17.39
342966	1SPURLK4G	17.39
925981	AC1-074 C O1	15.31
925982	AC1-074 E O1	6.56
926951	AC1-182	0.8
932551	AC2-075 C	3.64
932552	AC2-075 E	1.83
935011	AD1-134	17.48
936281	AD2-036 C	10.93
936282	AD2-036 E	5.47
936381	AD2-048 C	11.97
936382	AD2-048 E	5.97
936571	AD2-072 C O1	9.64
936572	AD2-072 E O1	4.73
936821	AD2-105 C O1	4.08
936822	AD2-105 E O1	5.98
936841	AD2-107 C O1	2.23
936842	AD2-107 E O1	3.08
939131	AE1-143 C	7.15
939132	AE1-143 E	3.54
939141	AE1-144 C O1	32.16
939142	AE1-144 E O1	15.96
940531	AE2-038 C O2	20.11
940532	AE2-038 E O2	10.02
941411	AE2-138 C O2	61.77
941412	AE2-138 E O2	22.85
941961	AE2-208	2.43
941981	AE2-210 C O2	21.64
941982	AE2-210 E O2	8.14
942231	AE2-235 C O2	19.29
942232	AE2-235 E O2	8.33
942411	AE2-254 C O2	4.88
942412	AE2-254 E O2	3.25
942591	AE2-275 C O2	15.55

Bus #	Bus	MW Impact
942592	AE2-275 E O2	5.85
942891	AE2-308 C O1	25.76
942892	AE2-308 E O1	9.37
943111	AE2-339 C	9.06
943112	AE2-339 E	4.46
CARR	CARR	0.51
CBM-S1	CBM-S1	13.73
CBM-S2	CBM-S2	1.86
CBM-W1	CBM-W1	3.87
CBM-W2	CBM-W2	65.34
CIN	CIN	7.07
CPLE	CPLE	0.39
G-007	G-007	1.38
IPL	IPL	4.27
LGEE	LGEE	5.19
MEC	MEC	7.86
O-066	O-066	8.9
RENSSELAER	RENSSELAER	0.4
WEC	WEC	0.68

Affected Systems

26 Affected Systems

26.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

26.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

26.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

26.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

26.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

Contingency Name	Contingency Definition
DEO&K-DAY-EKPC.C5 4541MELDAHLSPLRCKSTUARTSPURLOC KDPLEK	CONTINGENCY 'DEO&K-DAY-EKPC.C5 4541MELDAHLSPLRCKSTUARTSPURLOCKDPLEK' OPEN BRANCH FROM BUS 342838 TO BUS 249581 CKT 1 OPEN BRANCH FROM BUS 253077 TO BUS 342838 CKT 1 END
EKPC_P1-2_JKS-NCLA345	CONTINGENCY 'EKPC_P1-2_JKS-NCLA345' /* JK SMITH - N CLARK OPEN BRANCH FROM BUS 342832 TO BUS 342835 CKT 1 /* 342832 7JK SMITH 345.00 342835 7N CLARK 345.00 END
.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545	CONTINGENCY '.345.DEO&K.B2 RED BANK-SG-ZIMMER 4545' OPEN BRANCH FROM BUS 249573 TO BUS 249577 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249571 TO BUS 249573 CKT 1 END
.138.DEO&K.C2 816_SILVERGROVE	CONTINGENCY '.138.DEO&K.C2 816_SILVERGROVE' OPEN BRANCH FROM BUS 249573 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249988 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 250042 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 250052 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 250053 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249571 TO BUS 249573 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 249577 CKT 1 END
.345.DEO&K.C2 1493_RED BANK	CONTINGENCY '.345.DEO&K.C2 1493_RED BANK' OPEN BRANCH FROM BUS 249571 TO BUS 249573 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 250097 CKT 1 OPEN BRANCH FROM BUS 249573 TO BUS 249577 CKT 1 OPEN BRANCH FROM BUS 249571 TO BUS 250092 CKT 1 END
Base Case	
AEP_P4_#2085_05BEATTY 345_304C	CONTINGENCY 'AEP_P4_#2085_05BEATTY 345_304C' OPEN BRANCH FROM BUS 243453 TO BUS 243454 CKT 1 / 243453 05BEATTY 345 243454 05BIXBY 345 1 OPEN BRANCH FROM BUS 243453 TO BUS 253110 CKT 1 / 243453 05BEATTY 345 253110 09ADKINS 345 1 END

Short Circuit

27 Short Circuit

The following Breakers are overduty

None