



**Generation Interconnection
Feasibility Study Report
for
Queue Project AF1-066
NEW ROAD 230 KV
130 MW Capacity / 130 MW Energy**

January, 2020

Table of Contents

- 1 Introduction 4
- 2 Preface 4
- 3 General 6
 - 3.1 Point of Interconnection 7
 - 3.2 Cost Summary 7
- 4 Transmission Owner Scope of Work 8
- 5 Attachment Facilities 8
- 6 Direct Connection Cost Estimate 9
- 7 Non-Direct Connection Cost Estimate 10
- 8 Schedule 11
- 9 Transmission Owner Analysis 12
 - 9.1 Power Flow Analysis 12
 - 9.2 Short Circuit Analysis 12
 - 9.3 Stability Analysis 12
- 10 Interconnection Customer Requirements 13
- System Protection 13
- Compliance Issues and Interconnection Customer Requirements 13
- Power Factor Requirements 14
- 11 Revenue Metering and SCADA Requirements 15
 - 11.1 PJM Requirements 15
 - 11.2 Dominion Requirements 15
- 12 Network Impacts 16
 - 12.1 Generation Deliverability 18
 - 12.2 Multiple Facility Contingency 18
 - 12.3 Contribution to Previously Identified Overloads 18
 - 12.4 Potential Congestion due to Local Energy Deliverability 18
 - 12.5 System Reinforcements 18
- 13 Short Circuit 20

14 Affected Systems 22
 14.1 Duke Energy Progress..... 22
15 Attachment 1 23

1 Introduction

This Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between, the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Virginia Electric and Power Company (VEPCO).

2 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances, a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

An Interconnection Customer with a proposed new Customer Facility that has a Maximum Facility Output equal to or greater than 100 MW shall install and maintain, at its expense, phasor measurement units (PMUs). See Section 8.5.3 of Appendix 2 to the Interconnection Service Agreement as well as section 4.3 of PJM Manual 14D for additional information.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See

Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model. The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

3 General

The Interconnection Customer (IC), has proposed a Storage generating facility located in Loudoun County, Virginia. This project is an increase to the Interconnection Customer's AE2-019 project, which will share the same property and point of interconnection. The AF1-066 queue position is a 130 MW uprate to the previous project with 130 MW of this output being recognized by PJM as capacity. The total installed facilities will have a capability of 300 MW with 300 MW of this output being recognized by PJM as capacity. The proposed in-service date for this project is 11/30/2021. This study does not imply an ITO commitment to this in-service date.

Queue Number	AF1-066
Project Name	NEW ROAD 230 KV
State	Virginia
County	Loudoun
Transmission Owner	Dominion
MFO	300
MWE	130
MWC	130
Fuel	Storage
Basecase Study Year	2023

3.1 Point of Interconnection

AF1-066 “New Road 230 kV” will interconnect with the Dominion’s transmission system via an existing substation: New Road 230 kV substation. The project is an uprate to previous queue AE2-019 which will share the same property and point of interconnection. The IC is responsible for securing right-of-way, permits and constructing the proposed attachment line from the battery energy storage facility site to the existing switching station. Attachment 1 shows a one-line diagram of the proposed interconnection facilities. The IC may not install any facilities on Dominion’s right-of-way without first obtaining the necessary approval from Dominion Energy.

3.2 Cost Summary

The AF1-066 project will be responsible for the following costs:

None.

4 Transmission Owner Scope of Work

Dominion assessed the impact of the proposed Queue Project AF1-066. The project was evaluated as a 130 MW Capacity (130.0 MW Energy) injection at the New Road 230 kV substation in the Dominion Transmission System, for compliance with NERC Reliability Criteria on Dominion Transmission System. The system was assessed using the summer 2023 AF1 case provided to Dominion by PJM. When performing a generation analysis, Dominion's main analysis will be load flow study results under single contingency (both normal and stressed system conditions). Dominion Criteria considers a transmission facility overloaded if it exceeds 94% of its emergency rating under normal and stressed system conditions. A full listing of Dominion's Planning Criteria and interconnection requirements can be found in the Company's Facility Connection Requirements which are publicly available at: <http://www.dominionenergy.com>.

The results of these studies evaluate the system under a limited set of operating conditions and do not guarantee the full delivery of the capacity and associated energy of this proposed generation facility under all operating conditions. NERC Planning and Operating Reliability Criteria allow for the re-dispatch of generating units to resolve projected and actual deficiencies in real time and planning studies. Specifically, in Planning Studies, NERC Planning Event 3 and 6 Contingency Conditions (Loss of generator, transmission circuit, transformer, shunt device, or Single Pole of a DC line followed by the loss of a generator, transmission circuit, transformer, shunt device or single pole of a DC line) allow for re-dispatch of generating units to resolve potential reliability deficiencies. For Dominion Planning Criteria the re-dispatch of generating units for these contingency conditions is allowed as long as the projected loading does not exceed 100% of a facility Load Dump Rating.

The required Attachment Facilities, Direct Connection and Non-Direct Connection work for the interconnection of the AF1-066 generation project to the Dominion Transmission System is detailed in the following sections. The associated one-line with the generation project attachment facilities and primary direct and non-direct connection are shown in Attachment 1.

Note that the ITO findings were made from a conceptual review of this project. A more detailed review of the connection facilities and their cost will be identified in a future study phases. Further note that the cost estimate data contained in this document should be considered high level estimates since it was produced without a detailed engineering review. The applicant will be responsible for the actual cost of construction. ITO herein reserves the right to return to any issues in this document and, upon appropriate justification, request additional monies to complete any reinforcements to the transmission systems.

5 Attachment Facilities

None.

6 Direct Connection Cost Estimate

None.

7 Non-Direct Connection Cost Estimate

None.

Remote Terminal Work: During the Facilities Study, ITO's System Protection Engineering Department will review transmission line protection as well as anti-islanding required to accommodate the new generation and interconnection substation. System Protection Engineering will determine the minimal acceptable protection requirements to reliably interconnect the proposed generating facility with the transmission system. The review is based on maintaining system reliability by reviewing ITO's protection requirements with the known transmission system configuration which includes generating facilities in the area. This review may determine that transmission line protection and communication upgrades are required at remote substations.

8 Schedule

The schedule for the required Network Impact Reinforcements will be more clearly identified in future study phases. The estimate elapsed time to complete each of the required reinforcements is identified in the “System Reinforcements” section of the report.

9 Transmission Owner Analysis

9.1 Power Flow Analysis

PJM performed a power flow analysis of the transmission system using a 2023 summer peak load flow model and the results were verified by Dominion. Additionally, Dominion performed an analysis of its transmission system and no further deficiencies were identified.

9.2 Short Circuit Analysis

PJM performed a short circuit analysis and the results were verified by Dominion. The connection of AF1-075 project to the system does not result in any newly overdutied circuit breakers on the Dominion transmission system and does not have a significant fault current contribution to existing overdutied circuit breakers.

9.3 Stability Analysis

PJM will complete a dynamic stability analysis, if necessary, as part of the System Impact Study. The results of this analysis will be reviewed by Dominion. Should stability concerns be identified in PJM's study, Dominion will develop appropriate system reinforcement(s) and included the estimated cost of any reinforcement(s) in Dominion's System Impact Study report.

10 Interconnection Customer Requirements

System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in Dominion’s “Dominion Energy Electric Transmission Generator Interconnection Requirements” documented in Dominion’s Facility Interconnection Requirements “Exhibit C” located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>. Preliminary Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with Dominion’s “Dominion’s Facility Interconnection Requirements” document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>. In particular, the IC is responsible for the following:

The purchase and installation of a fully rated protection device (circuit breaker, circuit switcher, fuse) to protect the IC’s GSU transformer(s).

The purchase and installation of the minimum required Dominion generation interconnection relaying and control facilities as described in the System Protection noted above. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.

The purchase and installation of supervisory control and data acquisition (“SCADA”) equipment to provide information in a compatible format to the Dominion Transmission System Control Center.

Compliance with the Dominion and PJM generator power factor and voltage control requirements.

The GSU(s) associated with the IC queue request shall meet the grounding requirements as noted in Dominion’s “Dominion’s Facility Interconnection Requirements” document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>.

The IC will also be required to meet all PJM, SERC, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the submission of the generator model and protection data required to satisfy the PJM and SERC audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the Dominion system.

Power Factor Requirements

The IC shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the Dominion transmission system.

11 Revenue Metering and SCADA Requirements

11.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

11.2 Dominion Requirements

See Section 3.4.6 "Metering and telecommunications" of Dominion's "Dominion's Facility Interconnection Requirements" document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>.

12 Network Impacts

The Queue Project AF1-066 was evaluated as a 130.0 MW (Capacity 130.0 MW) injection at existing New Road 230 kV substation in the Dominion area. The project is an uprate to the existing AE2-019 project. Project AF1-066 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AF1-066 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

12.1 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

12.2 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

12.3 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

12.4 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

12.5 System Reinforcements

None

Short Circuit

13 Short Circuit

The following Breakers are overduty:

None

Affected Systems

14 Affected Systems

14.1 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).