



Generation Interconnection

Combined Feasibility / System Impact Study Report

for

Queue Project AF1-263

BENNETT-FARMINGDALE 2 34.5 KV

0.7 MW Capacity / 0 MW Energy

January 2020

Table of Contents

1	Introduction.....	3
2	Preface.....	3
3	General.....	4
3.1	Point of Interconnection	5
3.2	Cost Summary.....	5
4	Transmission Owner Scope of Work.....	5
5	Schedule.....	5
6	Transmission Owner Analysis.....	5
7	Interconnection Customer Requirements.....	6
7.1	System Protection.....	6
7.2	Compliance Issues and Interconnection Customer Requirements	6
7.3	Power Factor Requirements.....	7
8	Revenue Metering and SCADA Requirements	8
8.1	PJM Requirements	8
8.1.1	Meteorological Data Reporting Requirement.....	8
8.2	JCPL Requirements.....	8
9	Network Impacts	9
10	Generation Deliverability	11
11	Multiple Facility Contingency	11
12	Contribution to Previously Identified Overloads	11
13	Potential Congestion due to Local Energy Deliverability.....	11
14	System Reinforcements.....	12
15	Affected Systems	14
16	Short Circuit.....	16
17	Stability	18
18	Attachment One: One Line Diagram.....	19

1 Introduction

This Combined Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Jersey Central Power and Light (JCPL).

2 Preface

The intent of the combined feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

3 General

The Interconnection Customer (IC) has proposed an update to a solar generating facility located in Salem County, New Jersey. This project is a Capacity-only increase to the Interconnection Customer's X4-031 project. The AF1-263 queue position is a 0.7 MW Capacity-only update to the previous project. The total installed facilities will have a capability of 2 MW with 0.7 MW of this output being recognized by PJM as Capacity (see table below for clarity). The proposed in-service date for this update project was October 1, 2019. This study does not imply a TO commitment to this in-service date.

Queue	Maximum Facility Output (MFO) (MW)	Energy (MW)	Capacity (MW)
X4-031	2	2	0
AF1-263	2	0	0.7
Total	2	2	0.7

Queue Number	AF1-263
Project Name	BENNETT-FARMINGDALE 2 34.5 KV
State	New Jersey
County	Salem
Transmission Owner	JCPL
MFO	2
MWE	0
MWC	0.7
Fuel	Solar
Basecase Study Year	2023

3.1 Point of Interconnection

The interconnection of the project at the Primary POI will be accomplished by utilizing the Brickyard Solar (X4-031) interconnection which is tapped from the Bennett – Farmingdale 34.5 kV line in the JCPL area.

Attachment 1 shows a one-line diagram of the X4-031/AF1-263 generation project to connection to the FirstEnergy (“FE”) transmission system.

3.2 Cost Summary

The AF1-263 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$0
Direct Connection Network Upgrade	\$0
Non Direct Connection Network Upgrades	\$0
Total Costs	\$0

No network upgrades are required to accommodate AF1-263:

Description	Total Cost
System Upgrades	\$0

4 Transmission Owner Scope of Work

No physical interconnection work is required for this Capacity-only uprate.

5 Schedule

No physical interconnection work is required for this Capacity-only uprate.

6 Transmission Owner Analysis

FE performed an analysis of its underlying transmission <100 kV system. The AF1-263 project did not contribute to any overloads on the FE transmission <100 kV system.

7 Interconnection Customer Requirements

7.1 System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. Preliminary Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

7.2 Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. In particular, the IC is responsible for the following:

1. The purchase and installation of a fully rated 34.5 kV circuit breaker to protect the X4-031/AF1-263 generator lead line. A single circuit breaker must be used to protect this line; if the project has several GSU transformers, the individual GSU transformer breakers cannot be used to protect this line.
2. The purchase and installation of the minimum required FE generation interconnection relaying and control facilities. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.
3. The purchase and installation of supervisory control and data acquisition ("SCADA") equipment to provide information in a compatible format to the FE Transmission System Control Center.
4. Compliance with the FE and PJM generator power factor and voltage control requirements.
5. The execution of a back-up service agreement to serve the customer load supplied from the X4-031/AF1-263 generation project metering point when the units are out-of-service. This assumes the intent of the IC is to net the generation with the load.

The IC will also be required to meet all PJM, ReliabilityFirst, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the submission of the generator model and protection data required to satisfy the PJM and ReliabilityFirst audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the FE system.

7.3 Power Factor Requirements

The IC shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the FE transmission system.

8 Revenue Metering and SCADA Requirements

8.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

8.1.1 Meteorological Data Reporting Requirement

The solar generation facility shall provide the Transmission Provider with site-specific meteorological data including:

- Temperature (degrees Fahrenheit)
- Atmospheric pressure (hectopascals)
- Irradiance

Forced outage data

8.2 JCPL Requirements

The IC will be required to comply with all FE revenue metering requirements for generation interconnection customers which can be found in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>.

9 Network Impacts

The Queue Project AF1-263 was evaluated as a 0.7 MW (Capacity 0.7 MW) injection as an uprate to X4-031 tapping the Bennett to Farmingdale 34.5 kV line in the JCPL area. Project AF1-263 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AF1-263 was studied with a commercial probability of 100%. Potential network impacts were as follows:

Summer Peak Load Flow

10 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

11 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

12 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

13 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

14 System Reinforcements

None

Affected Systems

15 Affected Systems

None

Short Circuit

16 Short Circuit

The following Breakers are overduty:

None

Stability

17 Stability

Not required for a Capacity-only update.

18 Attachment One: One Line Diagram

