



**Generation Interconnection**  
**Combined Feasibility / System Impact Study Report**  
**for**  
**Queue Project AF1-327**  
**POHATCONG-NEWBURGH 34.5 KV**  
**0 MW Capacity / 20 MW Energy**

January 2020

# Table of Contents

- 1 Introduction..... 3
- 2 Preface..... 3
- 3 General..... 3
  - 3.1 Point of Interconnection ..... 4
  - 3.2 Cost Summary..... 4
- 4 Transmission Owner Scope of Work..... 5
- 5 Attachment Facilities ..... 5
- 6 Direct Connection Cost Estimate..... 5
- 7 Non-Direct Connection Cost Estimate..... 5
- 8 Schedule..... 7
- 9 Transmission Owner Analysis..... 8
  - 9.1 Power Flow Analysis ..... 8
- 10 Interconnection Customer Requirements..... 9
  - 10.1 System Protection..... 9
  - 10.2 Compliance Issues and Interconnection Customer Requirements ..... 9
  - 10.3 Power Factor Requirements.....10
- 11 Revenue Metering and SCADA Requirements .....11
  - 11.1 PJM Requirements .....11
  - 11.2 JCPL Requirements.....11
- 12 Network Impacts.....12
- 13 Generation Deliverability .....14
- 14 Multiple Facility Contingency .....14
- 15 Contribution to Previously Identified Overloads .....14
- 16 Potential Congestion due to Local Energy Deliverability.....14
- 17 System Reinforcements.....15
- 18 Affected Systems .....17
- 19 Short Circuit.....19
- 20 Stability .....21
- 21 Attachment One: One Line Diagram.....22

## 1 Introduction

This Combined Feasibility/System Impact Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Jersey Central Power and Light (JCPL).

## 2 Preface

The intent of the Combined Feasibility/System Impact study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

## 3 General

The Interconnection Customer (IC), has proposed a Storage generating facility located in Warren Count, New Jersey. The installed facilities will have a total capability of 20 MW with 0 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is August 31, 2021. This study does not imply a TO commitment to this in-service date.

<b>Queue Number</b>	<b>AF1-327</b>
<b>Project Name</b>	<b>POHATCONG-NEWBURGH 34.5 KV</b>
<b>State</b>	New Jersey
<b>County</b>	Warren
<b>Transmission Owner</b>	JCPL
<b>MFO</b>	20
<b>MWE</b>	20
<b>MWC</b>	0
<b>Fuel</b>	Storage
<b>Basecase Study Year</b>	2023

### 3.1 Point of Interconnection

The interconnection of the project to the JCPL system will be accomplished by tapping the Pohatcong - Newburgh 34.5 kV (E733-2) line with a three-switch tap and constructing a one span 34.5 kV line extension. The transmission line tap will be located approximately 1.25 miles from Pohatcong substation and 1.55 miles from Newburgh substation. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct both the new interconnection line tap and the associated Attachment facilities. The project will also require non-direct connection upgrades at Pohatcong and Chester substations.

Attachment 1 shows a one-line diagram of the proposed interconnection facilities for the AF1-327 generation project to connect to the FirstEnergy (“FE”) transmission system. IC will be responsible for constructing all the facilities on its side of the POI, including the Attachment facilities which connect the generator to the FE transmission system.

### 3.2 Cost Summary

The AF1-327 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$561,800
Direct Connection Network Upgrade	\$0
Non Direct Connection Network Upgrades	\$1,705,900
<b>Total Costs</b>	<b>\$2,267,700</b>

The AF1-327 project does not require any network upgrades:

Description	Total Cost
System Upgrades	\$0

The costs provided above exclude the Contribution in Aid of Construction (“CIAC”) Federal Income Tax Gross Up charge. If, at a future date, it is determined that the CIAC Federal Income Tax Gross charge is required, the Transmission Owner shall be reimbursed by the Interconnection Customer for such taxes.

The required Attachment Facilities and Direct and/or Non-Direct Connection work for the interconnection of the AF1-327 generation project to the FE Transmission System is detailed in the following sections. The associated one-line with the generation project Attachment Facilities and the Primary Direct and Non-Direct Connection facilities are shown in Attachment 1.

#### 4 Transmission Owner Scope of Work

The interconnection of the project to the JCPL system will be accomplished by tapping the Pohatcong - Newburgh 34.5 kV (E733-2) line with a three-switch tap and constructing a one span 34.5 kV line extension. The transmission line tap will be located approximately 1.25 miles from Pohatcong substation and 1.55 miles from Newburgh substation. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct both the new interconnection line tap and the associated Attachment facilities. The project will also require non-direct connection upgrades at Pohatcong and Chester substations.

#### 5 Attachment Facilities

The total preliminary cost estimate for the Attachment work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Tap the existing E733 (Chester-Pohatcong Mountain) 34.5 kV line with a 3 switch tap (1 switch and associated facilities) to interconnect queue project AF1-327. @ Pohatcong-Newburgh 34.5 kV Battery: Provide Interconnection facilities for AF1-327	\$281,600
Install 34.5 kV metering in customer facilities @ AF1-327	\$280,200
<b>Total Attachment Facility Costs</b>	<b>\$561,800</b>

#### 6 Direct Connection Cost Estimate

No Direct Connection work is required.

#### 7 Non-Direct Connection Cost Estimate

The total preliminary cost estimate for the Non-Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Tap the existing E733 (Chester-Pohatcong Mountain) 34.5 kV line with a 3 switch tap (2 switches) to interconnect queue project AF1-327. @ Pohatcong-Newburgh 34.5 kV Battery: Provide Interconnection facilities for AF1-327	\$1,367,800

Description	Total Cost
Install inline strain structures on the Q719 (Pohatcong Mountain-Washington) 34.5 kV line. @ Pohatcong-Newburgh 34.5 kV Battery: Provide Interconnection facilities for AF1-327	\$302,300
Update relay settings @ Pohatcong	\$17,900
Update relay settings @ Chester	\$17,900
<b>Total Non-Direct Connection Facility Costs</b>	<b>\$1,705,900</b>

## 8 Schedule

Based on the scope of work for the Attachment Facilities and the Direct and/or Non-Direct Connection facilities, it is expected to take a minimum of **11 months** after the signing of an Interconnection Construction Service Agreement to complete the installation. This includes the requirement for the IC to make a preliminary payment that compensates FE for the first three months of the engineering design work that is related to the Attachment Facilities. Full initial deposit is required for the Non-Direct Connection work. This assumes that there will be no environmental issues with any of the new properties associated with this project, that there will be no delays in acquiring the necessary permits for implementing the defined interconnection work, and that all transmission system outages will be allowed when requested.

## 9 Transmission Owner Analysis

### 9.1 Power Flow Analysis

FE performed an analysis of its underlying transmission <100 kV system. The AF1-327 project did not contribute to any overloads on the FE transmission <100 kV system.

## 10 Interconnection Customer Requirements

### 10.1 System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. Preliminary Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

All new generator only and new generator plus load facilities must be isolated from the FE transmission System by a Power Transformer. Section 14.2.6 of FE's "Requirements for Transmission Connected Facilities" document specifies the winding configurations of the transformer connecting to a non-effectively grounded portion of the FE Transmission system shall be determined by FE on a case-by-case basis. The IC has requested a GSU transformer winding configuration that will not be accepted. The GSU transformer must have a delta or ungrounded wye connection on the high (utility) side.

### 10.2 Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. In particular, the IC is responsible for the following:

1. The purchase and installation of a fully rated 34.5 kV circuit breaker to protect the AF1-327 generator lead line. A single circuit breaker must be used to protect this line; if the project has several GSU transformers, the individual GSU transformer breakers cannot be used to protect this line.
2. The purchase and installation of the minimum required FE generation interconnection relaying and control facilities. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.
3. The purchase and installation of supervisory control and data acquisition ("SCADA") equipment to provide information in a compatible format to the FE Transmission System Control Center.
4. Compliance with the FE and PJM generator power factor and voltage control requirements.
5. The execution of a back-up service agreement to serve the customer load supplied from the AF1-327 generation project metering point when the units are out-of-service. This assumes the intent of the IC is to net the generation with the load.

The IC will also be required to meet all PJM, Reliability First, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the

submission of the generator model and protection data required to satisfy the PJM and Reliability First audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the FE system.

### **10.3 Power Factor Requirements**

The IC shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the FE transmission system.

## 11 Revenue Metering and SCADA Requirements

### 11.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

### 11.2 JCPL Requirements

The IC will be required to comply with all FE revenue metering requirements for generation interconnection customers which can be found in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>.

## 12 Network Impacts

The Queue Project AF1-327 was evaluated as a 20 MW (Capacity 0.0 MW) injection tapping the Pohatcong to Newburgh 34.5 kV (E733-2) line in the JCPL area. Project AF1-327 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AF1-327 was studied with a commercial probability of 100%. Potential network impacts were as follows:

# Summer Peak Load Flow

### **13 Generation Deliverability**

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

### **14 Multiple Facility Contingency**

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

### **15 Contribution to Previously Identified Overloads**

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

### **16 Potential Congestion due to Local Energy Deliverability**

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

# 17 System Reinforcements

None

—

# Affected Systems

## 18 Affected Systems

None

# Short Circuit

## 19 Short Circuit

The following Breakers are overduty:

None

# Stability

## 20 Stability

Not required for this project.

## 21 Attachment One: One Line Diagram

