



**Generation Interconnection
Feasibility Study Report
for
Queue Project AF2-088
SHAWVILLE-CLEARFIELD 34.5 KV II
3.9 MW Capacity / 6.5 MW Energy**

July 2020

Table of Contents

- 1 Introduction..... 4
- 2 Preface..... 4
- 3 General..... 5
- 4 Point of Interconnection (POI)..... 6
 - 4.1 Primary POI..... 6
 - 4.2 Secondary POI..... 6
- 5 Cost Summary..... 6
- 6 Transmission Owner Scope of Work..... 8
- 7 Schedule..... 9
- 8 Transmission Owner Analysis..... 9
- 9 Interconnection Customer Requirements..... 9
 - 9.1 System Protection..... 9
 - 9.2 General Concerns..... 9
 - 9.3 Requirements for Owner’s/Developer’s generation IPP Facility..... 9
 - 9.4 Compliance Issues..... 10
- 10 Revenue Metering and SCADA Requirements..... 10
 - 10.1 PJM Requirements..... 10
 - 10.2 Meteorological Data Reporting Requirements..... 10
 - 10.3 Interconnected Transmission Owner Requirements..... 11
- 11 Summer Peak Analysis..... 12
 - 11.1 Generation Deliverability..... 12
 - 11.2 Multiple Facility Contingency..... 12
 - 11.3 Contribution to Previously Identified Overloads..... 12
 - 11.4 Steady-State Voltage Requirements..... 12
 - 11.5 Potential Congestion due to Local Energy Deliverability..... 12
 - 11.6 System Reinforcements..... 13
 - 11.7 Flow Gate Details..... 14
 - 11.8 Queue Dependencies..... 15
 - 11.9 Contingency Descriptions..... 16
- 12 Short Circuit Analysis..... 17
- 13 Affected Systems..... 18

13.1 NYISO18

14 Attachment 1: One Line Diagram19

1 Introduction

This Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Mid-Atlantic Interstate Transmission (MAIT) (PENELEC zone).

2 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

3 General

The Interconnection Customer (IC) has proposed an uprate to a planned/existing Solar generating facility located in Clearfield, Pennsylvania. This project is an increase to the Interconnection Customer's AF2-039 project, which will share the same point of interconnection. The AF2-088 queue position is a 6.5 MW uprate (3.9 MW Capacity uprate) to the previous project. The total installed facilities will have a capability of 20 MW with 12 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this uprate project is May 31, 2021. This study does not imply a TO commitment to this in-service date.

Queue Number	AF2-088
Project Name	SHAWVILLE-CLEARFIELD 34.5 KV II
State	Pennsylvania
County	Clearfield
Transmission Owner	MAIT (PENELEC zone)
MFO	20
MWE	6.5
MWC	3.9
Fuel	Solar
Basecase Study Year	2023

Any new service customers who can feasibly be commercially operable prior to June 1st of the basecase study year are required to request interim deliverability analysis.

4 Point of Interconnection (POI)

4.1 Primary POI

AF2-088 will interconnect with the PENELEC distribution system at the same POI as AF2-039. The AF2-039 project is being studied for a primary and a secondary point of interconnection (POI). The primary POI is a 34.5kV interconnection via a tap on the #2 Clearfield circuit at the Penelec-owned Shawville substation. The IC's proposed generating unit site is approximately 1.0 mile northwest of Woodland, PA., near 211 Independent Road.

Attachment 1 shows a one-line diagram of the proposed primary direct connection facilities for the AF2-088 generation project to connect to the Penelec distribution system. IC will be responsible for constructing all of the facilities on its side of the POI, including the attachment facilities which connect the generator to the Penelec distribution system's direct connection facilities.

4.2 Secondary POI

The secondary POI is a 34.5kV interconnection via a tap on the Philipsburg circuit at the Penelec-owned Shawville substation. No physical interconnection costs are provided for the secondary POI, only analysis results are provided. If the customer chooses the secondary POI for the System Impact phase, then the costs will be provided at that time.

The analysis results for the primary and secondary POI are the same as the project was studied at the same electrical point in the model for each location.

5 Cost Summary

The AF2-088 project will be responsible for the following costs:

Description	Total Cost
Total Physical Interconnection Costs	\$0
System Network Upgrade Costs	\$0
Total Costs	\$0

This cost excludes a Federal Income Tax Gross Up charges. This tax may or may not be charged based on whether this project meets the eligibility requirements of IRS Notice 88-129. If at a future date it is determined that the Federal Income Tax Gross charge is required, the Transmission Owner shall be reimbursed by the Interconnection Customer for such taxes.

Note 1: PJM Open Access Transmission Tariff (OATT) section 217.3A outline cost allocation rules. The rules are further clarified in PJM Manual 14A Attachment B. The allocation of costs for a network upgrade will start with the first Queue project to cause the need for the upgrade. Later queue projects will receive cost

allocation contingent on their contribution to the violation and are allocated to the queues that have not closed less than 5 years following the execution of the first Interconnection Service Agreement which identifies the need for this upgrade.

Note 2: For customers with System Reinforcements listed: If your present cost allocation to a System Reinforcement indicates \$0, then please be aware that as changes to the interconnection process occur, such as prior queued projects withdrawing from the queue, reducing in size, etc, the cost responsibilities can change and a cost allocation may be assigned to your project. In addition, although your present cost allocation to a System Reinforcement is presently \$0, your project may need this system reinforcement completed to be deliverable to the PJM system. If your project comes into service prior to completion of the system reinforcement, an interim deliverability study for your project will be required.

6 Transmission Owner Scope of Work

The AF2-088 will interconnect with the Penelec distribution system at the same POI as AF2-039 via a tap on the 34.5 kV #2 Clearfield circuit at pole # SBC-2-8021. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct the new interconnection station and the associated facilities.

Attachment 1 shows a one-line diagram of the proposed primary direct connection facilities for the AF2-088 generation project to connect to the Penelec distribution system. The IC will be responsible for constructing all of the facilities on its side of the POI, including the attachment facilities which connect the generator to the FE distribution system's direct connection facilities.

There are no additional physical interconnection costs for this project. If AF2-039 withdraws from the interconnection queue, then this project will be responsible for the interconnection work identified in the AF2-039 Feasibility Study Report and the analysis results will need to be retooled for any required system reinforcements.

Description	Total Cost
Total Physical Interconnection Costs	\$0

7 Schedule

The AF2-088 project is the same POI as AF2-039 and requires no additional facilities.

8 Transmission Owner Analysis

Penelec performed an analysis of its distribution system. The AF2-088 project did not contribute to any overloads on the distribution system for either the primary POI or the secondary POI.

9 Interconnection Customer Requirements

9.1 System Protection

The same analysis that was conducted to assess the impact of the Shawville-Clearfield 34.5 kV (AF2-039) Project on the system protection requirements in the area applies to the AF2-088 project. The results of this review show that the following relay additions will be required:

Proposed single line diagrams show IC constructing a generation facility tapping Penelec's Shawville - 34.5kV #2 Clearfield circuit at pole SBC-2-8021.

The 34.5kV interconnection proposal will require Developer to meet applicable "Technical Requirements" as outlined in First Energy's document titled "Technical Requirements for the Interconnection of Customer-Owned Generation to the FirstEnergy Distribution System". Anti-islanding system shall meet IEEE 1547 and UL 1741. Therefore, no Direct Transfer Trip (DTT) will be required.

9.2 General Concerns

It is to be understood, for abnormal operation of the Penelec system, which could cause Developer's generation facility to be electrically isolated from the Penelec system synchronous source via the tripping of a interconnecting primary voltage line or device, Developer will, via Penelec's direction, be required to disconnect the generation from Penelec's system and remain disconnected (**units are required to be OFF LINE**), until the Penelec system normal circuitry is restored. These abnormal conditions will be reviewed by Penelec system operators as to the need for the generation facility to be disconnected.

9.3 Requirements for Owner's/Developer's generation IPP Facility

The proposed interconnection Owner's/Developer's facilities must be designed in accordance with the document titled *FirstEnergy Distribution Engineering Practices Interconnection of Customer-Owned Generation to the FirstEnergy Distribution System* dated 11/17/14 located at the following link:

<http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>

The document is referred to as engineering practice EP(# 02-280) with section 4 part C specifically referencing the "interconnection technical requirements". Certain protection requirements are shown.

Additionally, Owner/Developer is responsible to provide adequate protection (for their equipment) under any distribution system operating condition' - which includes 'Separation from supply' (i.e. tripping of F.E. circuit breakers) and 'Re-synchronizing the generation after electric restoration of the supply' (i.e. reclosing of F.E. circuit breakers).

Owner's/Developer's protection must be designed to coordinate with the reclosing practices of FirstEnergy line protective devices. The generator must cease to energize the FirstEnergy circuit to which it is connected prior to reclosing of any (FE) automatic reclosing devices.

Owners/Developer's electrical protection and control schematics shall be provided to FE for consideration. FE may request modifications, if required, to meet the technical requirements.

9.4 Compliance Issues

IC will be responsible for meeting a power factor between 0.95 lagging (producing MVARs) to 0.95 leading (absorbing MVARs) and assure that voltage deviation will be less than 1.0 volt as measured at the POI under all Solar Gen operating conditions due to the inherent dynamic reactive power capability of this solar facility.

Generators with no inherent VAR (reactive power) control capability, or those that have a restricted VAR capability less than the defined requirements, must provide dynamic supplementary reactive support located at the generation facility with electrical characteristics equivalent to that provided by a similar sized synchronous generator. A Dynamic Reactive Compensation (either Static VAR Compensator (SVC) or STATCOM) or other method be applied in order to maintain the required specifications at the POI. IC is responsible for the installation of equipment on its side of the POI in order to adhere to the criteria stated above by FirstEnergy.

10 Revenue Metering and SCADA Requirements

10.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

10.2 Meteorological Data Reporting Requirements

The solar generation facility shall provide the Transmission Provider with site-specific meteorological data including:

- Back Panel temperature (Fahrenheit)
- Irradiance (Watts/meter²)
- Ambient air temperature (Fahrenheit) – (Accepted, not required)
- Wind speed (meters/second) – (Accepted, not required)

Wind direction (decimal degrees from true north) – (Accepted, not required)

10.3 Interconnected Transmission Owner Requirements

The IC will be required to comply with all Interconnected Transmission Owner's revenue metering requirements for generation interconnection customers located at the following link:

<http://www.pjm.com/planning/design-engineering/to-tech-standards/>

These FE requirements are the following:

The FE operating company (Penelec) shall provide, own, operate, test, and maintain the revenue metering equipment at the Interconnection Customer's (IC) expense. The revenue metering equipment includes, but is not limited to, current transformers, voltage transformers, secondary wires, meter socket, bidirectional revenue meter, and associated devices. The IC shall mount the instrument transformers unless otherwise agreed to by Penelec. The instrument transformers and meter socket shall be installed in a location that is readily accessible to authorized Penelec representatives. Penelec will provide the IC access to bidirectional kWh and kVARh pulses from the Penelec meter at the IC's expense if requested. The IC shall, at its expense, install, own, operate, test, and maintain any metering and telemetry equipment that may be required to provide real-time meter data to FE or PJM.

11 Summer Peak Analysis¹

The Queue Project AF2-088 was evaluated as a 6.5 MW (Capacity 3.9 MW) injection as an update to AF2-039 at the Shawville 34.5 kV substation in the PENELEC area. Project AF2-088 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AF2-088 was studied with a commercial probability of 53.0 %. Potential network impacts were as follows:

11.1 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

11.2 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

11.3 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

11.4 Steady-State Voltage Requirements

To be determined in System Impact phase.

11.5 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

¹¹ Primary and Secondary POI studied at the same electrical Point so analysis results are the same for both locations.

11.6 System Reinforcements

None

11.7 Flow Gate Details

The following indices contain additional information about each facility presented in the body of the report. For each index, a description of the flowgate and its contingency was included for convenience. The intent of the indices is to provide more details on which projects/generators have contributions to the flowgate in question. All New Service Queue Requests, through the end of the Queue under study, that are contributors to a flowgate will be listed in the indices. Please note that there may be contributors that are subsequently queued after the queue under study that are not listed in the indices. Although this information is not used "as is" for cost allocation purposes, it can be used to gage the impact of other projects/generators. It should be noted the project/generator MW contributions presented in the body of the report are Full MW Impact contributions which are also noted in the indices column named "Full MW Impact", whereas the loading percentages reported in the body of the report, take into consideration the PJM Generator Deliverability Test rules such as commercial probability of each project as well as the ramping impact of "Adder" contributions. The MW Impact found and used in the analysis is shown in the indices column named "Gendeliv MW Impact".

None

—

11.8 Queue Dependencies

The Queue Projects below are listed in one or more indices for the overloads identified in your report. These projects contribute to the loading of the overloaded facilities identified in your report. The percent overload of a facility and cost allocation you may have towards a particular reinforcement could vary depending on the action of these earlier projects. The status of each project at the time of the analysis is presented in the table. This list may change as earlier projects withdraw or modify their requests.

None

11.9 Contingency Descriptions

None

12 Short Circuit Analysis

Short Circuit analysis to be performed in the System Impact phase.

13 Affected Systems

13.1 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

14 Attachment 1: One Line Diagram