



**Generation Interconnection
Feasibility Study Report
for
Queue Project AE2-079
POOLESVILLE 34.5 KV
13.2 MW Capacity / 20 MW Energy**

July, 2019

Table of Contents

1	Introduction.....	4
2	Preface.....	4
3	General	5
3.1	Point of Interconnection	5
3.2	Cost Summary.....	5
4	Transmission Owner Scope of Work	6
5	Non-Direct Connection Cost Estimate.....	6
6	Schedule.....	7
7	Transmission Owner Analysis.....	7
7.1	Power Flow Analysis	7
7.2	Short Circuit Analysis.....	7
7.3	Stability Analysis	7
8	Interconnection Customer Requirements.....	7
8.1	System Protection.....	7
8.2	Compliance Issues and Interconnection Customer Requirements	8
8.3	Power Factor Requirements.....	8
9	Revenue Metering and SCADA Requirements	8
9.1.1	PJM Requirements	8
9.1.2	Meteorological Data Reporting Requirement.....	8
9.2	Dominion Requirements.....	9
10	Network Impacts.....	9
11	Generation Deliverability	11
12	Multiple Facility Contingency	11
13	Contribution to Previously Identified Overloads	11
14	Potential Congestion due to Local Energy Deliverability.....	11
15	System Reinforcements.....	11
16	Affected Systems	13
16.1	LG&E.....	13
16.2	MISO	13
16.3	TVA.....	13
16.4	Duke Energy Progress.....	13

16.5	NYISO	13
17	Short Circuit.....	15
	Attachment 1.....	16

1 Introduction

This Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Virginia Electric and Power Company (VEPCO).

2 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model.

The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

3 General

The Interconnection Customer (IC), has proposed a Solar generating facility located in Surry County, Virginia. The installed facilities will have a total capability of 20 MW with 13.2 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is 06/18/2021. This study does not imply a TO commitment to this in-service date.

Final attachment facilities and local upgrades (if required) along with terms and conditions to interconnect AE2-079 will be specified in a separate two party Interconnection Agreement (IA) between Dominion and the Interconnection Customer as this project is considered FERC non-jurisdictional per the PJM Open Access Transmission Tariff (OATT).

From the transmission perspective, no network impacts were identified as detailed in the “Network Impacts” section below.

Queue Number	AE2-079
Project Name	POOLESVILLE 34.5 KV
Interconnection Customer	
State	Virginia
County	Surry
Transmission Owner	Dominion
MFO	20
MWE	20
MWC	13.2
Fuel	Solar
Basecase Study Year	2022

3.1 Point of Interconnection

AE2-079 will interconnect with the Dominion distribution system on the Poolesville 34.5 kV circuit 470 off of transformer #1. The one-line diagram can be found in Attachment 1.

3.2 Cost Summary

The AE2-079 project may be responsible for a contribution to the following costs

Description	Total Cost
System Upgrades	\$ 0

Cost allocations for these upgrades will be provided in the System Impact Study Report.

4 Transmission Owner Scope of Work

Dominion assessed the impact of the proposed Queue Project AE2-079 was evaluated as a 13.2 MW Capacity (20.0 MW energy) load reducer at the Poolesville 230 kV substation in the Dominion Transmission System, for compliance with NERC Reliability Criteria on Dominion Transmission System. The system was assessed using the summer 2022 AE2 case provided to Dominion by PJM. When performing a generation analysis, Dominion's main analysis will be load flow study results under single contingency (both normal and stressed system conditions). Dominion Criteria considers a transmission facility overloaded if it exceeds 94% of its emergency rating under normal and stressed system conditions. A full listing of Dominion's Planning Criteria and interconnection requirements can be found in the Company's Facility Connection Requirements which are publicly available at: <http://www.dominionenergy.com>.

The results of these studies evaluate the system under a limited set of operating conditions and do not guarantee the full delivery of the capacity and associated energy of this proposed generation facility under all operating conditions. NERC Planning and Operating Reliability Criteria allow for the re-dispatch of generating units to resolve projected and actual deficiencies in real time and planning studies. Specifically in Planning Studies NERC Category C Contingency Conditions (Bus Fault, Tower Line, N-1-1, and Stuck Breaker scenarios) allow for re-dispatch of generating units to resolve potential reliability deficiencies. For Dominion Planning Criteria the re-dispatch of generating units for these contingency conditions is allowed as long as the projected loading does not exceed 100% of a facility Load Dump Rating.

Note that the ITO findings were made from a conceptual review of this project. A more detailed review of the connection facilities and their cost will be identified in a future study phases. Further note that the cost estimate data contained in this document should be considered high level estimates since it was produced without a detailed engineering review. The applicant will be responsible for the actual cost of construction. ITO herein reserves the right to return to any issues in this document and, upon appropriate justification, request additional monies to complete any reinforcements to the transmission systems.

5 Non-Direct Connection Cost Estimate

The total preliminary cost estimate for the Non-Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
-------------	------------

Description	Total Cost
	\$ 0
Total Non-Direct Connection Facility Costs	\$ 0

6 Schedule

The schedule for the required Network Impact Reinforcements will be more clearly identified in future study phases. The estimate elapsed time to complete each of the required reinforcements is identified in the “System Reinforcements” section of the report.

7 Transmission Owner Analysis

7.1 Power Flow Analysis

PJM performed a power flow analysis of the transmission system using a 2022 summer peak load flow model and the results were verified by Dominion. Additionally, Dominion performed an analysis of its transmission system.

7.2 Short Circuit Analysis

PJM performed a short circuit analysis and the results were verified by Dominion. The connection of AE2-079 project to the system does not result in any newly overdutied circuit breakers on the Dominion transmission system and does not have a significant fault current contribution to existing overdutied circuit breakers

7.3 Stability Analysis

PJM will complete a dynamic stability analysis, if necessary, as part of the System Impact Study. The results of this analysis will be reviewed by Dominion. Should stability concerns be identified in PJM’s study, Dominion will develop appropriate system reinforcement(s) and included the estimated cost of any reinforcement(s) in Dominion’s System Impact Study report.

8 Interconnection Customer Requirements

8.1 System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in Dominion’s “Dominion Energy Electric Transmission Generator Interconnection Requirements” documented in Dominion’s Facility Interconnection Requirements “Exhibit C” located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>. Preliminary Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

8.2 Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with Dominion's "Dominion's Facility Interconnection Requirements" document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>. In particular, the IC is responsible for the following:

1. The purchase and installation of a fully rated protection device (circuit breaker, circuit switcher, fuse) to protect the IC's GSU transformer(s).
2. The purchase and installation of the minimum required Dominion generation interconnection relaying and control facilities as described in the System Protection noted above. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.
3. The purchase and installation of supervisory control and data acquisition ("SCADA") equipment to provide information in a compatible format to the Dominion Transmission System Control Center.
4. Compliance with the Dominion and PJM generator power factor and voltage control requirements.

The GSU(s) associated with the IC queue request shall meet the grounding requirements as noted in Dominion's "Dominion's Facility Interconnection Requirements" document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>.

The IC will also be required to meet all PJM, SERC, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the submission of the generator model and protection data required to satisfy the PJM and SERC audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the Dominion system.

8.3 Power Factor Requirements

The IC shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the Dominion transmission system.

9 Revenue Metering and SCADA Requirements

9.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

9.1.1 Meteorological Data Reporting Requirement

The solar generation facility shall provide the Transmission Provider with site-specific meteorological data including:

- Temperature (degrees Fahrenheit)

- Atmospheric pressure (hectopascals)
- Irradiance
- Forced outage data

9.2 Dominion Requirements

See Section 3.4.6 “Metering and Telecommunications” of Dominion’s “Dominion’s Facility Interconnection Requirements” document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>.

10 Network Impacts

The Queue Project AE2-079 was evaluated as a 20.0 MW (Capacity 13.2 MW) injection at the Poolesville 230 kV substation in the Dominion area. Project AE2-079 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-079 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

11 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

12 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

13 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

14 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

15 System Reinforcements

None

Affected Systems

16 Affected Systems

16.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

16.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

16.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

16.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

16.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

Short Circuit

17 Short Circuit

The following Breakers are overduty: None

Attachment 1

System Configuration

