



**Generation Interconnection
Feasibility Study Report
for
Queue Project AE2-082
ENGLISHTOWN-WYCKOFF 34.5 KV SOLAR
3.4 MW Capacity / 7 MW Energy**

July, 2019

Table of Contents

1	Introduction.....	4
2	Preface.....	4
3	General	6
4	Point of Interconnection.....	7
4.1	Primary POI.....	7
5	Cost Summary	7
6	Transmission Owner Scope of Work.....	8
7	Attachment Facilities	8
8	Direct Connection Cost Estimate.....	8
9	Non-Direct Connection Cost Estimate.....	8
10	Schedule.....	9
11	Transmission Owner Analysis.....	10
11.1	Power Flow Analysis	10
11.2	Short Circuit Analysis.....	10
11.3	Stability Analysis.....	10
12	Interconnection Customer Requirements.....	11
12.1	System Protection.....	11
12.2	Compliance Issues and Interconnection Customer Requirements	11
12.3	Power Factor Requirements.....	11
13	Revenue Metering and SCADA Requirements	12
13.1	PJM Requirements	12
13.2	JCPL Requirements.....	12
14	Network Impacts.....	13
15	Generation Deliverability	15
16	Multiple Facility Contingency	15
17	Contribution to Previously Identified Overloads	15
18	Potential Congestion due to Local Energy Deliverability.....	15
19	System Reinforcements:	16
20	Flow Gate Details	17
21	Affected Systems	19
21.1	LG&E.....	19

21.2	MISO	19
21.3	TVA.....	19
21.4	Duke Energy Progress.....	19
21.5	NYISO	19
22	Short Circuit.....	21
23	Attachment 1 – One Line.....	22
24	Attachment 2 – Project Location	23

1 Introduction

This Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Jersey Central Power & Light Company (JCPL).

2 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model.

The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

3 General

The Interconnection Customer (IC) has proposed a Solar generating facility located in Monmouth County, New Jersey. The installed facilities will have a total capability of **7 MW** with **3.4 MW** of this output being recognized by PJM as Capacity. The proposed in-service date for this project is **September 30, 2019**. **This study does not imply a Jersey Central Power & Light Company (JCPL) commitment to this in-service date.**

Queue Number	AE2-082
Project Name	ENGLISHTOWN-WYCKOFF 34.5 KV SOLAR
Interconnection Customer	
State	New Jersey
County	Monmouth
Transmission Owner	JCPL
MFO	7
MWE	7
MWC	3.4
Fuel	Solar
Basecase Study Year	2022

4 Point of Interconnection

4.1 Primary POI

The interconnection of the project at the Primary POI will be accomplished by tapping the Englishtown – Wyckoff Street 34.5 kV line. The transmission line tap will be located approximately 1 mile from Englishtown substation and 2 miles from Wyckoff Street substation. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct both the new interconnection line tap and the associated attachment facilities. The project will also require direct connection upgrades to tap the Englishtown – Wyckoff Street 34.5 kV line.

Attachment 1 shows a one-line diagram of the proposed primary direct connection facilities for the AE2-082 generation project to connect to the FirstEnergy (“FE”) transmission system. Attachment 2 provides the proposed location for the point of interconnection. IC will be responsible for constructing all of the facilities on its side of the POI, including the attachment facilities which connect the generator to the FE transmission system’s direct connection facilities.

5 Cost Summary

The AE2-082 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$ 209,825
Direct Connection Network Upgrade	\$ 629,475
Non Direct Connection Network Upgrades	\$ 0
Total Costs	\$ 839,300

In addition, the AE2-082 project may be responsible for a contribution to the following costs:

Description	Total Cost
System Upgrades	\$ 0

The costs provided above exclude the Contribution in Aid of Construction (“CIAC”) Federal Income Tax Gross Up charge. If, at a future date, it is determined that the CIAC Federal Income Tax Gross charge is required, the Transmission Owner shall be reimbursed by the Interconnection Customer for such taxes.

The required Attachment Facilities and Direct and Non-Direct Connection work for the interconnection of the AE2-082 generation project to the FE Transmission System is detailed in the following sections. The associated one-line with the generation project Attachment Facilities and the Primary Direct and Non-Direct Connection facilities are shown in Attachment 1.

6 Transmission Owner Scope of Work

The interconnection of the project at the Primary POI will be accomplished by tapping the Englishtown - Wyckoff Street 34.5 kV line. The transmission line tap will be located approximately 1 mile from Englishtown substation and 2 miles from Wyckoff Street substation. The IC will be responsible for acquiring all easements, properties, and permits that may be required to construct both the new interconnection line tap and the associated attachment facilities.

7 Attachment Facilities

To accommodate the proposed AE2-082 Project, JCPL will tap the Englishtown – Wyckoff Street 34.5 kV line to the new customer substation. Additionally, a new 34.5 kV tap switch and associated line extension will also be installed. The IC will be responsible for acquiring all easements, properties and permits that may be required to construct the associated facilities.

The total preliminary cost estimate for the Attachment work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Install 34.5 kV Tap Switch and associated line extension. Provide 34.5 kV Revenue Meter Package.	\$ 209,825
Total Attachment Facility Costs	\$ 209,825

8 Direct Connection Cost Estimate

The total preliminary cost estimate for the Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Install (2) switches to tap I87 Englishtown – Wyckoff Street 34.5 kV line	\$ 629,475
Total Direct Connection Facility Costs	\$ 629,475

The total Direct Connection cost estimate for the AE2-028 project is approximately \$629,475.

The installation of two switches is required to tap the Englishtown – Wyckoff Street (I87) 34.5 kV line to facilitate the interconnection of the new generation.

9 Non-Direct Connection Cost Estimate

There is no Non-Direct Connection scope of work required for this project.

10 Schedule

Based on the scope of work for the Attachment Facilities and the Direct and Non-Direct Connection facilities, it is expected to take a minimum of **thirteen (13)** months after the signing of an Interconnection Construction Service Agreement to complete the installation. This includes the requirement for the IC to make a preliminary payment that compensates FE for the first three months of the engineering design work that is related to the Attachment Facilities and Direct Connection work. This assumes that there will be no environmental issues with any of the new properties associated with this project, that there will be no delays in acquiring the necessary permits for implementing the defined direct connection and network upgrades, and that all transmission system outages will be allowed when requested.

11 Transmission Owner Analysis

11.1 Power Flow Analysis

PJM performed a power flow analysis of the transmission system using a 2022 summer peak load flow model and the results were verified by FE. Additionally, FE performed an analysis of its underlying transmission <100 kV system. The AE2-082 project did not contribute to any overloads on the FE transmission system.

11.2 Short Circuit Analysis

PJM performed a short circuit analysis and the results were verified by FE. The connection of AE2-082 project to the system does not result in any newly overdutied circuit breakers on the FE transmission system and does not have a significant fault current contribution to existing overdutied circuit breakers.

11.3 Stability Analysis

PJM will complete a dynamic stability analysis, if necessary, as part of the System Impact Study. The results of this analysis will be reviewed by FE. Should stability concerns be identified in PJM's study, FE will develop appropriate system reinforcement(s) and included the estimated cost of any reinforcement(s) in FE's System Impact Study report.

12 Interconnection Customer Requirements

12.1 System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. Preliminary Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

The IC has requested a non-standard GSU transformer winding configuration. Further evaluation and review of the non-standard GSU transformer configuration will be part of the System Impact Study.

12.2 Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>. In particular, the IC is responsible for the following:

1. The purchase and installation of a fully rated 34.5 kV circuit breaker to protect the AE2-082 generator lead line. A single circuit breaker must be used to protect this line; if the project has several GSU transformers, the individual GSU transformer breakers cannot be used to protect this line.
2. The purchase and installation of the minimum required FE generation interconnection relaying and control facilities. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.
3. The purchase and installation of supervisory control and data acquisition ("SCADA") equipment to provide information in a compatible format to the FE Transmission System Control Center.
4. Compliance with the FE and PJM generator power factor and voltage control requirements.
5. The execution of a back-up service agreement to serve the customer load supplied from the AE2-082 generation project metering point when the units are out-of-service. This assumes the intent of the IC is to net the generation with the load.

The IC will also be required to meet all PJM, ReliabilityFirst, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the submission of the generator model and protection data required to satisfy the PJM and ReliabilityFirst audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the FE system.

12.3 Power Factor Requirements

The IC shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the FE transmission system.

13 Revenue Metering and SCADA Requirements

13.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

13.2 JCPL Requirements

The IC will be required to comply with all FE revenue metering requirements for generation interconnection customers which can be found in FE's "Requirements for Transmission Connected Facilities" document located at: <http://www.pjm.com/planning/design-engineering/to-tech-standards/private-firstenergy.aspx>.

14 Network Impacts

The Queue Project AE2-082 was evaluated as a 7.0 MW (Capacity 3.4 MW) injection tapping the Englishtown to Rt. 33 34.5kV line in the JCPL area. Project AE2-082 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-082 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

15 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

16 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

17 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

18 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

None

19 System Reinforcements:

None

20 Flow Gate Details

The following appendices contain additional information about each flowgate presented in the body of the report. For each appendix, a description of the flowgate and its contingency was included for convenience. However, the intent of the appendix section is to provide more information on which projects/generators have contributions to the flowgate in question. Although this information is not used "as is" for cost allocation purposes, it can be used to gage other generators impact. It should be noted the generator contributions presented in the appendices sections are full contributions, whereas in the body of the report, those contributions take into consideration the commercial probability of each project.

—
None

Affected Systems

21 Affected Systems

21.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

21.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

21.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

21.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

21.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

Short Circuit

22 Short Circuit

The following Breakers are overduty:

None

23 Attachment 1 – One Line

24 Attachment 2 – Project Location