



**Generation Interconnection
Feasibility Study Report
for
Queue Project AE2-166
STOCKTON 138 KV
54 MW Capacity / 90 MW Energy**

November, 2019

Table Of Contents

1	Preface.....	5
2	General.....	6
2.1	Primary Point of Interconnection	7
2.2	Cost Summary.....	7
3	Transmission Owner Scope of Work.....	8
4	Attachment Facilities	8
5	Direct Connection Cost Estimate.....	8
6	Non-Direct Connection Cost Estimate.....	8
7	Incremental Capacity Transfer Rights (ICTRs)	9
8	Schedule.....	9
9	Interconnection Customer Requirements.....	9
10	Revenue Metering and SCADA Requirements	10
10.1	PJM Requirements	10
10.2	AEP Requirements.....	10
11	Network Impacts – Option 1	11
12	Generation Deliverability	13
13	Multiple Facility Contingency	13
14	Contribution to Previously Identified Overloads	13
15	Potential Congestion due to Local Energy Deliverability.....	14
16	System Reinforcements.....	15
17	Flow Gate Details	17
17.1	Index 1	18
17.2	Index 2	19
17.3	Index 3	20
17.4	Index 4	21
17.5	Index 5	22
17.6	Index 6	23
17.7	Index 7	24
17.8	Index 8	25
17.9	Index 9	26
17.10	Index 10.....	27

18	Affected Systems	29
18.1	LG&E.....	29
18.2	MISO	29
18.3	TVA.....	29
18.4	Duke Energy Progress.....	29
18.5	NYISO	29
19	Contingency Descriptions.....	30
20	Short Circuit.....	33
21	Figure 1: AE2-166 Primary Point of Interconnection (Stockton 138kV)	Error! Bookmark not defined.
22	Figure 2: Primary Point of Interconnection (Stockton 138kV)	Error! Bookmark not defined.
23	Generation Deliverability	37
24	Multiple Facility Contingency	37
25	Contribution to Previously Identified Overloads	37
26	Potential Congestion due to Local Energy Deliverability	38
27	Flow Gate Details	40
27.1	Index 1	41
27.2	Index 2	42
27.3	Index 3	43
27.4	Index 4	44
27.5	Index 5	45
27.6	Index 6	46
27.7	Index 8	47
27.8	Index 9	48
27.9	Index 10	49
27.10	Index 11.....	50
28	Affected Systems	52
28.1	LG&E.....	52
28.2	MISO	52
28.3	TVA.....	52
28.4	Duke Energy Progress.....	52
28.5	NYISO	52
29	Contingency Descriptions.....	54

30	Short Circuit.....	57
31	Figure 3: AE2-166 Secondary Point of Interconnection.....	Error! Bookmark not defined.
32	Figure 4: Point of Interconnection (Stockton – Axton 138kV).....	Error! Bookmark not defined.

1 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model. The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

2 General

The Interconnection Customer has proposed a Solar generating facility located in Henry County, Virginia. The installed facilities will have a total capability of 90 MW with 54 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is 12/31/2022. This study does not imply a TO commitment to this in-service date.

The objective of this Feasibility Study is to determine budgetary cost estimates and approximate construction timelines for identified transmission facilities required to connect the proposed generating facilities to the AEP transmission system. These reinforcements include the Attachment Facilities, Local Upgrades, and Network Upgrades required for maintaining the reliability of the AEP transmission system.

The Feasibility Study includes Short Circuit and Peak Load steady state power flow analyses. The conduct of power flow studies at other load levels, stability analysis, and coordination with non-PJM Transmission Planners, as required under the PJM planning process, is not performed during the Generation Interconnection Feasibility Study phase of the PJM study process. Additional reinforcement requirements for this Interconnection Request may be defined during the conduct of these additional analyses which shall be performed following execution of the System Impact Study agreement.

Queue Number	AE2-166
Project Name	STOCKTON 138 KV
State	Virginia
County	Henry
Transmission Owner	AEP
MFO	90
MWE	90
MWC	54
Fuel	Solar
Basecase Study Year	2022

2.1 Primary Point of Interconnection

AE2-166 will interconnect with the AEP transmission system at the Stockton 138 kV substation.

To accommodate the interconnection at Stockton 138 kV substation, Stockton substation will have to be expanded to a new four (4) circuit breaker 138 kV substation physically configured in a breaker and half bus arrangement (see Figure 1). Installation of associated protection and control equipment, 138 kV line risers, SCADA, and 138 kV revenue metering will also be required. AEP reserves the right to specify the final acceptable configuration considering design practices, future expansion, and compliance requirements.

2.2 Cost Summary

The AE2-166 project will be responsible for the following costs:

Description	Total Cost
Attachment Facilities	\$250,000
Direct Connection Network Upgrade	\$6,000,000
Non Direct Connection Network Upgrades	\$1,250,000
Total Costs	\$7,500,000

In addition, the AE2-166 project may be responsible for a contribution to the following costs

Description	Total Cost
System Upgrades	\$13,010,800

Cost allocations for these upgrades will be provided in the System Impact Study Report.

3 Transmission Owner Scope of Work

4 Attachment Facilities

The total preliminary cost estimate for the Attachment work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
138kV Revenue Metering	\$ 250,000
Total Attachment Facility Costs	\$250,000

5 Direct Connection Cost Estimate

The total preliminary cost estimate for the Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Expand Stockton 138 kV substation to a new four (4) circuit breaker 138 kV substation physically configured in a breaker and half bus arrangement (see Figure 1). Installation of associated protection and control equipment, 138 kV line risers, SCADA, and 138 kV revenue metering will also be required. (See Figure 1).	\$ 6,000,000
Total Direct Connection Facility Costs	\$ 6,000,000

6 Non-Direct Connection Cost Estimate

The total preliminary cost estimate for the Non-Direct Connection work is given in the table below. These costs do not include CIAC Tax Gross-up.

Description	Total Cost
Axton- Martinsville 138kV circuit cut into Stockton	\$500,000
Upgrade line Protection and Controls at the proposed expanded Stockton 138kV substation	\$ 250,000
Upgrade line Protection and Controls at the Axton138kV station to coordinate with the expanded Stockton 138kV substation	\$ 250,000
Upgrade line Protection and Controls at the Martinsville 138kV station to coordinate with the expanded Stockton 138kV substation	\$ 250,000
Total Non-Direct Connection Facility Costs	\$1,250,000

7 Incremental Capacity Transfer Rights (ICTRs)

Will be determined at a later study phase

8 Schedule

It is anticipated that the time between receipt of executed Agreements and Commercial Operation may range from 12 to 18 months if no line work is required. If line work is required, construction time would generally be between 24 to 36 months after Agreement execution.

9 Interconnection Customer Requirements

It is understood that the Interconnection Customer is responsible for all costs associated with this interconnection. The costs above are reimbursable to AEP. The cost of the Interconnection Customer's generating plant and the costs for the line connecting the generating plant at the Stockton 138kV station are not included in this report; these are assumed to be the Interconnection Customer's responsibility.

The Generation Interconnection Agreement does not in or by itself establish a requirement for American Electric Power to provide power for consumption at the developer's facilities. A separate agreement may be reached with the local utility that provides service in the area to ensure that infrastructure is in place to meet this demand and proper metering equipment is installed. It is the responsibility of the developer to contact the local service provider to determine if a local service agreement is required.

Requirement from the PJM Open Access Transmission Tariff:

1. An Interconnection Customer entering the New Services Queue on or after October 1, 2012 with a proposed new Customer Facility that has a Maximum Facility Output equal to or greater than 100 MW shall install and maintain, at its expense, phasor measurement units (PMUs). See Section 8.5.3 of Appendix 2 to the Interconnection Service Agreement as well as section 4.3 of PJM Manual 14D for additional information.

The Interconnection Customer may be required to install and/or pay for metering as necessary to properly track real time output of the facility as well as installing metering which shall be used for billing purposes. See Section 8 of Appendix 2 to the Interconnection Service Agreement as well as Section 4 of PJM Manual 14D for additional information.

10 Revenue Metering and SCADA Requirements

10.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

10.2 AEP Requirements

The Interconnection Customer will be required to comply with all AEP Revenue Metering Requirements for Generation Interconnection Customers. The Revenue Metering Requirements may be found within the "Requirements for Connection of New Facilities or Changes to Existing Facilities Connected to the AEP Transmission System" document located at the following link:

<http://www.pjm.com/~media/planning/plan-standards/private-aep/aep-interconnection-requirements.ashx>

11 Network Impacts – Option 1

The Queue Project AE2-166 was evaluated as a 90 MW (Capacity 54 MW) injection at Stockton 138kV substation in the AEP area. Project AE2-166 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-166 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

12 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
1566402	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	Base Case	single	202.0	95.92	103.12	DC	14.54

13 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
1566243	242744	05PATCTR	AEP	243799	05FIELDAL2	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	296.0	89.67	99.58	DC	29.34
1566244	242744	05PATCTR	AEP	243799	05FIELDAL2	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	296.0	90.43	99.47	DC	26.76
1566241	243799	05FIELDAL2	AEP	242736	05OAKLEV	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	223.0	93.44	99.6	DC	13.74
1567318	926050	AC1-083 TAP	AEP	242802	05SMITHMTN1	AEP	1	AEP_P7-1_#10781-B	tower	296.0	97.34	101.64	DC	12.71

14 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
1565826	242544	05AXTON	AEP	941430	AE2-140 TAP	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	382.0	122.47	133.92	DC	43.74
7107092	242555	05BLAINE	AEP	242773	05ROANO1	AEP	1	247499 05SMITHMTN2 - 242802 05SMITHMTN1 CKT Z1	single	223.0	113.01	115.0	DC	4.44
1566517	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	AEP_P1-2_#1370	single	402.0	110.12	116.94	DC	27.41
2582429	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	402.0	110.12	116.94	DC	27.41
1565827	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	AEP_P4_#2916_05J.FERR 765_A	breaker	296.0	125.01	133.86	DC	26.19
1565685	242711	05MARTN 1	AEP	242744	05PATCTR	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	202.0	139.22	153.75	DC	29.34
1565686	242711	05MARTN 1	AEP	242744	05PATCTR	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	202.0	140.33	153.58	DC	26.76
1566479	242711	05MARTN 1	AEP	242744	05PATCTR	AEP	1	AEP_P1-2_#5459	single	202.0	129.21	136.32	DC	14.36
1566481	242711	05MARTN 1	AEP	242744	05PATCTR	AEP	1	AEP_P1-2_#1370	single	202.0	114.98	122.98	DC	16.16
2582391	242711	05MARTN 1	AEP	242744	05PATCTR	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	202.0	114.98	122.98	DC	16.16
1565620	242816	05STOCKT	AEP	242711	05MARTN 1	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	202.0	158.6	174.74	DC	32.61
1565621	242816	05STOCKT	AEP	242711	05MARTN 1	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	202.0	158.57	172.8	DC	28.75

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
1566394	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P1-2_#5459	single	202.0	146.62	154.26	DC	15.42
1566396	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P1-2_#1370	single	202.0	132.11	141.01	DC	17.99
2582307	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	202.0	132.11	141.01	DC	17.99
1565652	941430	AE2-140 TAP	AEP	242620	05DANVL2	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	382.0	152.79	164.24	DC	43.74

15 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
7107093	242555	05BLAINE	AEP	242773	05ROANO1	AEP	1	247499 05SMITHMTN2 - 242802 05SMITHMTN1 CKT Z1	operation	223.0	106.54	108.05	DC	7.4
1566515	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	AEP_P1-2_#1370	operation	402.0	130.24	141.6	DC	45.68
1566516	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	Base Case	operation	275.0	114.79	125.03	DC	28.16
2582426	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	operation	402.0	130.24	141.6	DC	45.68
1566568	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	AEP_P1-2_#1370	operation	296.0	124.89	133.74	DC	26.2
2582480	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	242509 05AXTON 765 242514 05J.FERR 765 1	operation	296.0	124.89	133.74	DC	26.2
1566476	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	AEP_P1-2_#5459	operation	202.0	138.73	150.58	DC	23.94
1566391	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P1-2_#5459	operation	202.0	156.83	169.55	DC	25.7
1566401	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	Base Case	operation	202.0	97.43	109.42	DC	24.24
1566816	941430	AE2-140 TAP	AEP	242620	05DANVL2	AEP	1	AEP_P1-2_#1370	operation	382.0	105.91	113.71	DC	29.78
1566818	941430	AE2-140 TAP	AEP	242620	05DANVL2	AEP	1	Base Case	operation	271.0	95.48	102.22	DC	18.27
2582733	941430	AE2-140 TAP	AEP	242620	05DANVL2	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	operation	382.0	105.91	113.71	DC	29.78

16 System Reinforcements

ID	Index	Facility	Upgrade Description	Cost
1566481,1565686,1566479,2582391,1565685	9	05MARTN1 138.0 kV - 05PATCTR 138.0 kV Ckt 1	<u>AEP</u> No Violation. Current AEP End Ratings: S/N: 293, S/E: 341.	\$0
1566241	3	05FIELDAL2 138.0 kV - 05OAKLEV 138.0 kV Ckt 1	<u>AEP</u> No violation. Post queue loading less than 100%.	\$0
1566244,1566243	2	05PATCTR 138.0 kV - 05FIELDAL2 138.0 kV Ckt 1	<u>AEP</u> No violation. Post queue loading less than 100%.	\$0
1565826	5	05AXTON 138.0 kV - AE2-140 TAP 138.0 kV Ckt 1	<u>AEP</u> AEPA0004a (274) : Rebuild Axton-AE2-140 138 kV (2.5 miles) using 1590 ACSR/SSAC Falcon @ 401 deg. F Project Type : FAC Cost : \$3,750,000 Time Estimate : 24-36 months Months AEPA0004b (275) : Replace 2000 A Wavetrap @ Axton w/ 3000 A Project Type : FAC Cost : \$50,000 Time Estimate : 24-36 months Months	\$3,800,000
7107092	6	05BLAINE 138.0 kV - 05ROANO1 138.0 kV Ckt 1	<u>AEP</u> AEPA0008a (279) : Perform Sag Study on 3.2 miles of ACSR ~ 636 ~ 26/7 ~ GROSBEAK conductor section of the Blaine-Roanoke 138 kV line. Project Type : FAC Cost : \$12,800 Time Estimate : 6 - 12 months Months AEPA0008b (280) : Perform Sag Study on 14.4 miles of ACSR ~ 795 ~ 45/7 ~ TERN conductor section of the Blaine-Roanoke 138 kV line. Project Type : FAC Cost : \$57,600 Time Estimate : 6 - 12 months Months AEPA0008c (281) : Replace 795 AAC Station Cond. at Blaine Station Project Type : FAC Cost : \$100,000 Time Estimate : 12- 18 months Months	\$170,400
1565652	10	AE2-140 TAP 138.0 kV - 05DANVL2 138.0 kV Ckt 1	<u>AEP</u> Current AEP Ratings are S/N: 296 MVA S/E: 392 MVA. Current AEP ratings are sufficient to mitigate the overloads.	\$0
1566402,2582307,1566394,1565620,1565621,1566396	1	05STOCKT 138.0 kV - 05MARTN1 138.0 kV Ckt 1	<u>AEP</u> Current AEP Ratings are S/N: 283 MVA S/E: 378 MVA. Current AEP ratings are sufficient to mitigate the overloads.	\$0

ID	Index	Facility	Upgrade Description	Cost
1567318	4	AC1-083 TAP 138.0 kV - 05SMITHMTN1 138.0 kV Ckt 1	<u>AEP</u> AEP A0007a (277) : Perform Sag Study on ~10.1 miles of ACSR ~ 1033.5 ~ 45/7 ~ ORTOLAN conductor section of the Smith Mountain-Bearskin 138 kV line . Project Type : FAC Cost : \$40,400 Time Estimate : 6 - 12 months Months	\$40,400
1565827	8	05EDAN 1 138.0 kV - 05EDAN 2 138.0 kV Ckt Z1	<u>AEP</u> n6124 (75) : PJM Network Upgrade n6124. Increasing the Danville East Danville 138 kV circuit summer rating to 572/572/572 MVA will still require us to rebuild the line. The network project has an projected in-service date of 06/01/2021. Project Type : FAC Cost : \$9,000,000 Time Estimate : Months	\$9,000,000
1566517,2582429	7	05DANVL2 138.0 kV - 05EDAN 1 138.0 kV Ckt 1		
			TOTAL COST	\$13,010,800

17 Flow Gate Details

The following appendices contain additional information about each flowgate presented in the body of the report. For each appendix, a description of the flowgate and its contingency was included for convenience. However, the intent of the appendix section is to provide more information on which projects/generators have contributions to the flowgate in question. Although this information is not used "as is" for cost allocation purposes, it can be used to gauge other generators impact. It should be noted the generator contributions presented in the appendices sections are full contributions, whereas in the body of the report, those contributions take into consideration the commercial probability of each project.

17.1 Index 1

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPACT
1565620	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	202.0	158.6	174.74	DC	32.61

Bus #	Bus	MW Impact
244012	05PINNACLE	0.75
926461	AC1-117 C	2.75
926462	AC1-117 E	4.49
938741	AE1-100 C O1	8.72
938742	AE1-100 E O1	5.02
938931	AE1-121 O1	100.87
938941	AE1-122 O1	100.87
941431	AE2-140 C O1	23.01
941432	AE2-140 E O1	15.34
941671	AE2-166 C	19.57
941672	AE2-166 E	13.04
942321	AE2-245	2.5
BLUEG	BLUEG	0.89
CANNELTON	CANNELTON	0.04
CBM-N	CBM-N	0.01
CBM-S1	CBM-S1	0.12
CBM-S2	CBM-S2	1.49
CBM-W2	CBM-W2	0.05
COFFEEN	COFFEEN	0.06
CPL	CPL	1.02
DUCKCREEK	DUCKCREEK	0.15
EDWARDS	EDWARDS	0.07
ELMERSMITH	ELMERSMITH	0.06
FARMERCITY	FARMERCITY	0.02
G-007A	G-007A	0.09
GIBSON	GIBSON	0.03
NEWTON	NEWTON	0.16
NYISO	NYISO	0.04
PRAIRIE	PRAIRIE	0.16
SMITHLAND	SMITHLAND	0.0
TATANKA	TATANKA	0.06
TILTON	TILTON	0.1
TRIMBLE	TRIMBLE	0.1
VFT	VFT	0.24

17.2 Index 2

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC DC	MW IMPACT
1566244	242744	05PATCT R	AEP	243799	05FIELDAL E 2	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	296.0	90.43	99.47	DC	26.76

Bus #	Bus	MW Impact
926461	AC1-117 C	2.26
926462	AC1-117 E	3.69
938741	AE1-100 C O1	8.02
938742	AE1-100 E O1	4.61
938931	AE1-121 O1	92.69
938941	AE1-122 O1	92.69
941671	AE2-166 C	16.06
941672	AE2-166 E	10.71
942321	AE2-245	2.05
CARR	CARR	0.01
CBM-S1	CBM-S1	0.69
CBM-S2	CBM-S2	0.7
CBM-W1	CBM-W1	0.59
CBM-W2	CBM-W2	4.27
CIN	CIN	0.27
CPL	CPL	0.47
G-007	G-007	0.05
IPL	IPL	0.17
LGEE	LGEE	0.08
MEC	MEC	0.63
MECS	MECS	0.22
O-066	O-066	0.28
RENSSELAER	RENSSELAER	0.01
WEC	WEC	0.07

17.3 Index 3

ID	FROM BUS#	FROM BUS	FRO M BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Ratin g MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPAC T
156624 1	24379 9	05FIELDALE 2	AEP	24273 6	05OAKLE V	AEP	1	AEP_P4_#10171_05AXTO N 138_G	breake r	223.0	93.44	99.6	DC	13.74

Bus #	Bus	MW Impact
244012	05PINNACLE	0.63
247723	05PHILPOTT	0.32
926461	AC1-117 C	1.16
926462	AC1-117 E	1.89
938741	AE1-100 C O1	5.8
938742	AE1-100 E O1	3.33
938931	AE1-121 O1	67.04
938941	AE1-122 O1	67.04
940601	AE2-047 C O1	4.16
940602	AE2-047 E O1	2.78
941431	AE2-140 C O1	15.48
941432	AE2-140 E O1	10.32
941671	AE2-166 C	8.24
941672	AE2-166 E	5.5
942321	AE2-245	1.05
BLUEG	BLUEG	0.47
CANNELTON	CANNELTON	0.01
CARR	CARR	0.01
CBM-S1	CBM-S1	0.56
CBM-S2	CBM-S2	1.94
CBM-W2	CBM-W2	2.88
COFFEEN	COFFEEN	0.01
CPLE	CPLE	1.06
DUCKCREEK	DUCKCREEK	0.05
EDWARDS	EDWARDS	0.03
ELMERSMITH	ELMERSMITH	0.01
G-007	G-007	0.01
GIBSON	GIBSON	0.01
MEC	MEC	0.05
NEWTON	NEWTON	0.04
O-066	O-066	0.06
RENSSELAER	RENSSELAER	0.01
TILTON	TILTON	0.04
TRIMBLE	TRIMBLE	0.06

17.4 Index 4

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
1567318	926050	AC1-083 TAP	AEP	242802	05SMITHMTN1	AEP	1	AEP_P7-1_#10781-B	tower	296.0	97.34	101.64	DC	12.71

Bus #	Bus	MW Impact
244012	05PINNACLE	3.29
926051	AC1-083 C O1	25.0
926052	AC1-083 E O1	40.78
926461	AC1-117 C	1.07
926462	AC1-117 E	1.75
933941	AD1-017 C	5.0
933942	AD1-017 E	8.16
936161	AD2-022 C O1	18.75
936162	AD2-022 E O1	11.25
936171	AD2-023 C O1	10.95
936172	AD2-023 E O1	5.95
938741	AE1-100 C O1	6.6
938742	AE1-100 E O1	3.8
938931	AE1-121 O1	76.31
938941	AE1-122 O1	76.31
939943	AE1-230 E2	0.42
940081	AE1-250 C	48.34
940082	AE1-250 E	32.23
940601	AE2-047 C O1	4.83
940602	AE2-047 E O1	3.22
941431	AE2-140 C O1	21.06
941432	AE2-140 E O1	14.04
941671	AE2-166 C	7.63
941672	AE2-166 E	5.08
942321	AE2-245	0.98
CARR	CARR	0.0
CBM-S1	CBM-S1	1.19
CBM-S2	CBM-S2	0.35
CBM-W1	CBM-W1	1.89
CBM-W2	CBM-W2	8.3
CIN	CIN	0.86
G-007	G-007	0.04
IPL	IPL	0.55
LGEE	LGEE	0.26
MEC	MEC	1.59
MECS	MECS	1.03
O-066	O-066	0.25
RENSSELAER	RENSSELAER	0.0
WEC	WEC	0.22

17.5 Index 5

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
1565826	242544	05AXTON	AEP	941430	AE2-140 TAP	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	382.0	122.47	133.92	DC	43.74

Bus #	Bus	MW Impact
247723	05PHILPOTT	0.49
926461	AC1-117 C	3.69
926462	AC1-117 E	6.03
938741	AE1-100 C O1	22.65
938742	AE1-100 E O1	13.03
938931	AE1-121 O1	261.96
938941	AE1-122 O1	261.96
939441	AE1-176	0.14
940083	AE1-250 EBAT	6.02
940601	AE2-047 C O1	3.77
940602	AE2-047 E O1	2.52
941671	AE2-166 C	26.25
941672	AE2-166 E	17.5
942321	AE2-245	3.36
CALDERWOOD	CALDERWOOD	0.22
CARR	CARR	0.01
CATAWBA	CATAWBA	0.56
CBM-W1	CBM-W1	1.75
CHEOAH	CHEOAH	0.23
CHILHOWEE	CHILHOWEE	0.07
CIN	CIN	0.84
COTTONWOOD	COTTONWOOD	0.5
G-007	G-007	0.09
HAMLET	HAMLET	1.38
IPL	IPL	0.56
LGEE	LGEE	0.26
MEC	MEC	0.89
MECS	MECS	1.35
O-066	O-066	0.55
RENSSELAER	RENSSELAER	0.01
SANTEETLA	SANTEETLA	0.07
TVA	TVA	0.35
UNIONPOWER	UNIONPOWER	0.35
WEC	WEC	0.2

17.6 Index 6

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
7107092	242555	05BLAINE	AEP	242773	05ROANO1	AEP	1	247499 05SMITHMTN2 - 242802 05SMITHMTN1 CKT Z1	single	223.0	113.01	115.0	DC	4.44

Bus #	Bus	MW Impact
246844	05SMG2	5.87
246845	05SMG3	3.44
246846	05SMG4	6.06
247723	05PHILPOTT	0.19
919841	AA2-070	1.11
926051	AC1-083 C 01	7.8
926461	AC1-117 C	0.62
933941	AD1-017 C	1.56
938741	AE1-100 C 01	2.96
938931	AE1-121 O1	34.19
938941	AE1-122 O1	34.19
940081	AE1-250 C	14.22
940601	AE2-047 C 01	2.92
941431	AE2-140 C 01	8.51
941671	AE2-166 C	4.44
942321	AE2-245	0.57
BLUEG	BLUEG	0.6
CANNELTON	CANNELTON	0.01
CARR	CARR	0.04
CBM-S1	CBM-S1	0.69
CBM-S2	CBM-S2	2.31
CBM-W2	CBM-W2	3.42
COFFEEN	COFFEEN	0.02
CPLE	CPLE	1.31
DUCKCREEK	DUCKCREEK	0.07
EDWARDS	EDWARDS	0.04
ELMERSMITH	ELMERSMITH	0.01
GIBSON	GIBSON	0.02
MEC	MEC	0.02
NEWTON	NEWTON	0.05
RENSSELAER	RENSSELAER	0.03
TATANKA	TATANKA	0.0
TILTON	TILTON	0.06
TRIMBLE	TRIMBLE	0.07

17.7 Index 7

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
2582429	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	402.0	110.12	116.94	DC	27.41

Bus #	Bus	MW Impact
242906	05CLAY-1	0.32
242907	05CLAY-2	0.32
247723	05PHILPOTT	0.53
926461	AC1-117 C	3.86
934751	AD1-102 C	1.32
938741	AE1-100 C O1	23.49
938931	AE1-121 O1	271.61
938941	AE1-122 O1	271.61
939441	AE1-176	0.15
940601	AE2-047 C O1	8.58
941431	AE2-140 C O1	70.37
941671	AE2-166 C	27.41
942321	AE2-245	3.51
942641	AE2-280 C O1	5.48
CALDERWOOD	CALDERWOOD	0.24
CARR	CARR	0.01
CATAWBA	CATAWBA	0.61
CBM-W1	CBM-W1	1.93
CBM-W2	CBM-W2	0.02
CHEOAH	CHEOAH	0.24
CHILHOWEE	CHILHOWEE	0.07
CIN	CIN	0.92
COTTONWOOD	COTTONWOOD	0.53
HAMLET	HAMLET	1.5
IPL	IPL	0.62
LGEE	LGEE	0.29
MEC	MEC	0.99
MECS	MECS	1.48
RENSSELAER	RENSSELAER	0.01
SANTEETLA	SANTEETLA	0.08
TVA	TVA	0.37
UNIONPOWER	UNIONPOWER	0.38
WEC	WEC	0.23

17.8 Index 8

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
1565827	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	AEP_P4_#2916_05J.FERR 765_A	breaker	296.0	125.01	133.86	DC	26.19

Bus #	Bus	MW Impact
244012	05PINNACLE	2.39
247723	05PHILPOTT	0.29
926461	AC1-117 C	2.21
926462	AC1-117 E	3.61
936161	AD2-022 C O1	12.52
936162	AD2-022 E O1	7.51
938741	AE1-100 C O1	13.58
938742	AE1-100 E O1	7.81
938931	AE1-121 O1	157.01
938941	AE1-122 O1	157.01
939943	AE1-230 E2	0.27
940083	AE1-250 EBAT	49.74
940601	AE2-047 C O1	4.83
940602	AE2-047 E O1	3.22
941431	AE2-140 C O1	40.8
941432	AE2-140 E O1	27.2
941671	AE2-166 C	15.71
941672	AE2-166 E	10.47
942321	AE2-245	2.01
CBM-N	CBM-N	0.01
CBM-S1	CBM-S1	0.55
CBM-S2	CBM-S2	0.34
CBM-W1	CBM-W1	0.81
CBM-W2	CBM-W2	3.82
CIN	CIN	0.36
CPLE	CPLE	0.05
G-007A	G-007A	0.02
IPL	IPL	0.23
LGEE	LGEE	0.11
MEC	MEC	0.7
MECS	MECS	0.44
NYISO	NYISO	0.06
VFT	VFT	0.05
WEC	WEC	0.1

17.9 Index 9

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC DC	MW IMPACT
1565686	242711	05MARTN1	AEP	242744	05PATCT R	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	202.0	140.33	153.58	DC	26.76

Bus #	Bus	MW Impact
926461	AC1-117 C	2.26
926462	AC1-117 E	3.69
938741	AE1-100 C O1	8.02
938742	AE1-100 E O1	4.61
938931	AE1-121 O1	92.69
938941	AE1-122 O1	92.69
941671	AE2-166 C	16.06
941672	AE2-166 E	10.71
942321	AE2-245	2.05
CARR	CARR	0.01
CBM-S1	CBM-S1	0.69
CBM-S2	CBM-S2	0.7
CBM-W1	CBM-W1	0.59
CBM-W2	CBM-W2	4.27
CIN	CIN	0.27
CPLE	CPLE	0.47
G-007	G-007	0.05
IPL	IPL	0.17
LGEE	LGEE	0.08
MEC	MEC	0.63
MECS	MECS	0.22
O-066	O-066	0.28
RENSSELAER	RENSSELAER	0.01
WEC	WEC	0.07

17.10 Index 10

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
1565652	941430	AE2-140 TAP	AEP	242620	05DANVL2	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	382.0	152.79	164.24	DC	43.74

Bus #	Bus	MW Impact
247723	05PHILPOTT	0.49
926461	AC1-117 C	3.69
926462	AC1-117 E	6.03
938741	AE1-100 C O1	22.65
938742	AE1-100 E O1	13.03
938931	AE1-121 O1	261.96
938941	AE1-122 O1	261.96
940083	AE1-250 EBAT	6.02
940601	AE2-047 C O1	3.77
940602	AE2-047 E O1	2.52
941431	AE2-140 C O1	69.89
941432	AE2-140 E O1	46.59
941671	AE2-166 C	26.25
941672	AE2-166 E	17.5
942321	AE2-245	3.36
CALDERWOOD	CALDERWOOD	0.22
CARR	CARR	0.01
CATAWBA	CATAWBA	0.56
CBM-W1	CBM-W1	1.75
CHEOAH	CHEOAH	0.23
CHILHOWEE	CHILHOWEE	0.07
CIN	CIN	0.84
COTTONWOOD	COTTONWOOD	0.5
G-007	G-007	0.09
HAMLET	HAMLET	1.38
IPL	IPL	0.56
LGEE	LGEE	0.26
MEC	MEC	0.89
MECS	MECS	1.35
O-066	O-066	0.55
RENSSELAER	RENSSELAER	0.01
SANTEETLA	SANTEETLA	0.07
TVA	TVA	0.35
UNIONPOWER	UNIONPOWER	0.35
WEC	WEC	0.2

Affected Systems

18 Affected Systems

18.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

18.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

18.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

18.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

18.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

19 Contingency Descriptions

Contingency Name	Contingency Definition
AEP_P4_#10171_05AXTON 138_G	CONTINGENCY 'AEP_P4_#10171_05AXTON 138_G' OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242509 TO BUS 242545 CKT 1 / 242509 05AXTON 765 242545 05AXTONX 138 1 OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT SR / 242544 05AXTON 138 242545 05AXTONX 138 SR OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT ZB / 242544 05AXTON 138 242545 05AXTONX 138 ZB OPEN BRANCH FROM BUS 242544 TO BUS 242619 CKT 2 / 242544 05AXTON 138 242619 05DANVL1 138 2 END
AEP_P1-2_#5459	CONTINGENCY 'AEP_P1-2_#5459' OPEN BRANCH FROM BUS 242544 TO BUS 242712 CKT 1 / 242544 05AXTON 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242638 CKT 1 / 242614 05COLLIN 138 242638 05FIELDAL1 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242712 CKT 1 / 242614 05COLLIN 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242712 TO BUS 243977 CKT 1 / 242712 05MARTN2 138 243977 05MART 115 34.5 1 OPEN BRANCH FROM BUS 243977 TO BUS 243979 CKT Z1 / 243977 05MART 115 34.5 243979 05MART2-30 34.5 Z1 OPEN BRANCH FROM BUS 243977 TO BUS 243980 CKT 1 / 243977 05MART 115 34.5 243980 05MORRIS-N 34.5 1 END
242509 05AXTON 765 242514 05J.FERR 765 1	CONTINGENCY '242509 05AXTON 765 242514 05J.FERR 765 1' / 8403 OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 END
AEP_P1-2_#1370	CONTINGENCY 'AEP_P1-2_#1370' OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242509 TO BUS 242545 CKT 1 / 242509 05AXTON 765 242545 05AXTONX 138 1 OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT SR / 242544 05AXTON 138 242545 05AXTONX 138 SR OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT ZB / 242544 05AXTON 138 242545 05AXTONX 138 ZB END

Contingency Name	Contingency Definition
AEP_P4_#2916_05J.FERR 765_A	CONTINGENCY 'AEP_P4_#2916_05J.FERR 765_A' OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242511 TO BUS 242514 CKT 1 / 242511 05BROADF 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242509 TO BUS 242545 CKT 1 / 242509 05AXTON 765 242545 05AXTONX 138 1 OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT SR / 242544 05AXTON 138 242545 05AXTONX 138 SR OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT ZB / 242544 05AXTON 138 242545 05AXTONX 138 ZB OPEN BRANCH FROM BUS 242566 TO BUS 242567 CKT ZB / 242566 05BROADF 138 242567 05BROADX 138 ZB END
Base Case	
AEP_P7-1_#10781-B	CONTINGENCY 'AEP_P7-1_#10781-B' OPEN BRANCH FROM BUS 936160 TO BUS 304024 CKT 1 / 936160 AD2-022 TAP 230 304024 6ROXSEP230 T 230 1 OPEN BRANCH FROM BUS 936170 TO BUS 304094 CKT 1 / 936170 AD2-023 TAP 230 304094 6YANCY TAP 230 1 OPEN BRANCH FROM BUS 304098 TO BUS 304094 CKT 1 / 304098 6CONCRD230TT 230 304094 6YANCY TAP 230 1 OPEN BRANCH FROM BUS 304094 TO BUS 304095 CKT 1 / 304094 6YANCY TAP 230 304095 6YANCYVILLE 230 1 END
AEP_P4_#10168_05AXTON 138_H	CONTINGENCY 'AEP_P4_#10168_05AXTON 138_H' OPEN BRANCH FROM BUS 242544 TO BUS 941430 CKT 1 / 242544 05AXTON 138 941430 AE2- 140 TAP 138 1 /* CONTINGENCY LINE ADDED FOR AE2 BUILD OPEN BRANCH FROM BUS 242544 TO BUS 242712 CKT 1 / 242544 05AXTON 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242638 CKT 1 / 242614 05COLLIN 138 242638 05FIELDAL1 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242712 CKT 1 / 242614 05COLLIN 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242712 TO BUS 243977 CKT 1 / 242712 05MARTN2 138 243977 05MART 115 34.5 1 OPEN BRANCH FROM BUS 243977 TO BUS 243979 CKT Z1 / 243977 05MART 115 34.5 243979 05MART2-30 34.5 Z1 OPEN BRANCH FROM BUS 243977 TO BUS 243980 CKT 1 / 243977 05MART 115 34.5 243980 05MORRIS-N 34.5 1 END
247499 05SMITHMTN2 - 242802 05SMITHMTN1 CKT Z1	CONTINGENCY '247499 05SMITHMTN2 - 242802 05SMITHMTN1 CKT Z1' /MISSING SINGLE DISCONNECT BRANCH FROM BUS 247499 TO BUS 242802 CKT Z1 END

Short Circuit

20 Short Circuit

The following Breakers are overduty

None

Secondary Point of Interconnection:

AE2-166 will interconnect with the AEP transmission system via a new station cut into Axton – Stockton 138 kV section of Axton – Martinsville 138kV Circuit.

To accommodate the interconnection at the Axton – Stockton 138 kV section of Axton – Martinsville 138kV Circuit, a new three (3) circuit breaker 138kV switching station physically configured in a breaker and half bus arrangement but operated as a ring-bus will be constructed (see Figure 3). Installation of associated protection and control equipment, 138 kV line risers, SCADA, and 138 kV revenue metering will also be required. AEP reserves the right to specify the final acceptable configuration considering design practices, future expansion, and compliance requirements.

Option -2 : Network Impacts

The Queue Project AE2-166 was evaluated as a 90 MW (Capacity 54 MW) injection via a switching station cut into Axton – Stockton 138kV section of Axton – Martinsville 138kV Circuit in the AEP area. Project AE2-166 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AE2-166 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

21 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
1566402	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	Base Case	single	202.0	96.38	102.27	DC	11.88

22 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
1566247	242614	05COLLIN	AEP	242638	05FIELDAL1	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	376.0	96.49	101.1	DC	17.32
1566243	242744	05PATCTR	AEP	243799	05FIELDAL2	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	296.0	90.76	99.45	DC	25.71
1566241	243799	05FIELDAL2	AEP	242736	05OAKLEV	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	223.0	94.09	100.08	DC	13.35
1567318	926050	AC1-083 TAP	AEP	242802	05SMITHMTN1	AEP	1	AEP_P7-1_#10781-B	tower	296.0	96.48	100.92	DC	13.15

23 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
11625127	242544	05AXTON	AEP	242620	05DANVL2	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	382.0	149.78	161.62	DC	45.22
1566517	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	AEP_P1-2_#1370	single	402.0	109.38	116.41	DC	28.27
2582429	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	402.0	109.38	116.41	DC	28.27
1565827	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	AEP_P4_#2916_05J.FERR 765_A	breaker	296.0	123.98	133.13	DC	27.08
1565685	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	202.0	140.87	153.59	DC	25.71
1565686	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	202.0	159.38	171.21	DC	23.9
1566479	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	AEP_P1-2_#5459	single	202.0	129.88	136.09	DC	12.55
1566481	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	AEP_P1-2_#1370	single	202.0	115.63	122.53	DC	13.93
2582391	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	202.0	115.63	122.53	DC	13.93
1566244	242744	05PATCTR	AEP	243799	05FIELDAL2	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	296.0	103.43	111.5	DC	23.9
1565620	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	202.0	160.34	174.42	DC	28.45
1565621	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	202.0	179.02	191.73	DC	25.67

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
1566394	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P1-2_#5459	single	202.0	147.34	154.02	DC	13.47
1566396	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P1-2_#1370	single	202.0	132.82	140.46	DC	15.44
2582307	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	202.0	132.82	140.46	DC	15.44
44626543	941670	AE2-166 TAP	AEP	242816	05STOCKT	AEP	1	AEP_P1-2_#5459	single	273.0	112.55	117.49	DC	13.47
44626544	941670	AE2-166 TAP	AEP	242816	05STOCKT	AEP	1	AEP_P1-2_#1370	single	273.0	101.71	107.36	DC	15.44
44626545	941670	AE2-166 TAP	AEP	242816	05STOCKT	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	273.0	101.71	107.36	DC	15.44
45308205	941670	AE2-166 TAP	AEP	242816	05STOCKT	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	273.0	134.44	143.85	DC	25.67
45308206	941670	AE2-166 TAP	AEP	242816	05STOCKT	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	273.0	120.31	130.73	DC	28.45

24 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
11969043	242544	05AXTON	AEP	242620	05DANVL2	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	operation	382.0	102.29	110.35	DC	30.79
11969044	242544	05AXTON	AEP	242620	05DANVL2	AEP	1	AEP_P1-2_#1370	operation	382.0	102.29	110.35	DC	30.79
1566515	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	AEP_P1-2_#1370	operation	402.0	129.03	140.75	DC	47.11
1566516	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	Base Case	operation	275.0	112.03	122.6	DC	29.05
2582426	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	operation	402.0	129.03	140.75	DC	47.11
1566568	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	AEP_P1-2_#1370	operation	296.0	123.9	133.06	DC	27.09
2582480	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	242509 05AXTON 765 242514 05J.FERR 765 1	operation	296.0	123.9	133.06	DC	27.09
44626742	242638	05FIELDALE1	AEP	247713	05FIELDALE_C	AEP	Z1	AEP_P1-2_#5458-A	operation	240.0	97.14	101.06	DC	9.41
1566476	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	AEP_P1-2_#5459	operation	202.0	139.85	150.21	DC	20.92

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
1566391	242816	05STOCT	AEP	242711	05MARTN1	AEP	1	AEP_P1-2_#5459	operation	202.0	158.03	169.15	DC	22.46
1566401	242816	05STOCT	AEP	242711	05MARTN1	AEP	1	Base Case	operation	202.0	103.53	113.34	DC	19.81
44626540	941670	AE2-166 TAP	AEP	242816	05STOCT	AEP	1	AEP_P1-2_#5459	operation	273.0	119.16	127.39	DC	22.46

25 Flow Gate Details

The following appendices contain additional information about each flowgate presented in the body of the report. For each appendix, a description of the flowgate and its contingency was included for convenience. However, the intent of the appendix section is to provide more information on which projects/generators have contributions to the flowgate in question. Although this information is not used "as is" for cost allocation purposes, it can be used to gage other generators impact. It should be noted the generator contributions presented in the appendices sections are full contributions, whereas in the body of the report, those contributions take into consideration the commercial probability of each project.

25.1 Index 1

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC DC	MW IMPACT
1565621	242816	05STOCKT	AEP	242711	05MARTN1	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	202.0	179.02	191.73	DC	25.67

Bus #	Bus	MW Impact
926461	AC1-117 C	2.43
926462	AC1-117 E	3.96
938741	AE1-100 C O1	8.61
938742	AE1-100 E O1	4.95
938931	AE1-121 O1	99.51
938941	AE1-122 O1	99.51
941431	AE2-140 C O2	24.78
941432	AE2-140 E O2	16.52
941671	AE2-166 C	15.4
941672	AE2-166 E	10.27
942321	AE2-245	2.21
CARR	CARR	0.01
CBM-S1	CBM-S1	0.72
CBM-S2	CBM-S2	0.73
CBM-W1	CBM-W1	0.63
CBM-W2	CBM-W2	4.48
CIN	CIN	0.29
CPLE	CPLE	0.49
G-007	G-007	0.05
IPL	IPL	0.18
LGEE	LGEE	0.08
MEC	MEC	0.67
MECS	MECS	0.23
O-066	O-066	0.3
RENSSELAER	RENSSELAER	0.01
WEC	WEC	0.08

25.2 Index 2

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC DC	MW IMPACT
1566247	242614	05COLLIN	AEP	242638	05FIELDAL1	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	376.0	96.49	101.1	DC	17.32

Bus #	Bus	MW Impact
244012	05PINNACLE	0.91
926461	AC1-117 C	1.27
926462	AC1-117 E	2.07
938741	AE1-100 C O1	10.57
938742	AE1-100 E O1	6.08
938931	AE1-121 O1	122.17
938941	AE1-122 O1	122.17
941431	AE2-140 C O2	30.42
941432	AE2-140 E O2	20.28
941671	AE2-166 C	10.39
941672	AE2-166 E	6.93
942321	AE2-245	1.15
BLUEG	BLUEG	1.07
CANNELTON	CANNELTON	0.05
CBM-N	CBM-N	0.01
CBM-S1	CBM-S1	0.15
CBM-S2	CBM-S2	1.81
CBM-W2	CBM-W2	0.09
COFFEEN	COFFEEN	0.07
CPL	CPL	1.24
DUCKCREEK	DUCKCREEK	0.18
EDWARDS	EDWARDS	0.09
ELMERSMITH	ELMERSMITH	0.07
FARMERCITY	FARMERCITY	0.03
G-007A	G-007A	0.11
GIBSON	GIBSON	0.04
NEWTON	NEWTON	0.2
NYISO	NYISO	0.05
PRAIRIE	PRAIRIE	0.19
SMITHLAND	SMITHLAND	0.0
TATANKA	TATANKA	0.07
TILTON	TILTON	0.12
TRIMBLE	TRIMBLE	0.12
VFT	VFT	0.28

25.3 Index 3

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC DC	MW IMPACT
1566244	242744	05PATCT R	AEP	243799	05FIELDAL E 2	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	296.0	103.43	111.5	DC	23.9

Bus #	Bus	MW Impact
926461	AC1-117 C	2.26
926462	AC1-117 E	3.69
938741	AE1-100 C O1	8.02
938742	AE1-100 E O1	4.61
938931	AE1-121 O1	92.69
938941	AE1-122 O1	92.69
941431	AE2-140 C O2	23.08
941432	AE2-140 E O2	15.39
941671	AE2-166 C	14.34
941672	AE2-166 E	9.56
942321	AE2-245	2.05
CARR	CARR	0.01
CBM-S1	CBM-S1	0.69
CBM-S2	CBM-S2	0.7
CBM-W1	CBM-W1	0.59
CBM-W2	CBM-W2	4.27
CIN	CIN	0.27
CPLE	CPLE	0.47
G-007	G-007	0.05
IPL	IPL	0.17
LGEE	LGEE	0.08
MEC	MEC	0.63
MECS	MECS	0.22
O-066	O-066	0.28
RENSSELAER	RENSSELAER	0.01
WEC	WEC	0.07

25.4 Index 4

ID	FROM BUS#	FROM BUS	FRO M BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Ratin g MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPAC T
156624 1	24379 9	05FIELDALE 2	AEP	24273 6	05OAKLE V	AEP	1	AEP_P4_#10171_05AXTO N 138_G	breake r	223.0	94.09	100.08	DC	13.35

Bus #	Bus	MW Impact
244012	05PINNACLE	0.63
247723	05PHILPOTT	0.32
926461	AC1-117 C	1.16
926462	AC1-117 E	1.89
938741	AE1-100 C O1	5.8
938742	AE1-100 E O1	3.33
938931	AE1-121 O1	67.04
938941	AE1-122 O1	67.04
940601	AE2-047 C O2	3.81
940602	AE2-047 E O2	2.54
941431	AE2-140 C O2	16.7
941432	AE2-140 E O2	11.13
941671	AE2-166 C	8.01
941672	AE2-166 E	5.34
942321	AE2-245	1.05
BLUEG	BLUEG	0.47
CANNELTON	CANNELTON	0.01
CARR	CARR	0.01
CBM-S1	CBM-S1	0.56
CBM-S2	CBM-S2	1.94
CBM-W2	CBM-W2	2.88
COFFEEN	COFFEEN	0.01
CPLE	CPLE	1.06
DUCKCREEK	DUCKCREEK	0.05
EDWARDS	EDWARDS	0.03
ELMERSMITH	ELMERSMITH	0.01
G-007	G-007	0.01
GIBSON	GIBSON	0.01
MEC	MEC	0.05
NEWTON	NEWTON	0.04
O-066	O-066	0.07
RENSSELAER	RENSSELAER	0.01
TILTON	TILTON	0.04
TRIMBLE	TRIMBLE	0.06

25.5 Index 5

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
1567318	926050	AC1-083 TAP	AEP	242802	05SMITHMTN1	AEP	1	AEP_P7-1_#10781-B	tower	296.0	96.48	100.92	DC	13.15

Bus #	Bus	MW Impact
244012	05PINNACLE	3.29
926051	AC1-083 C O1	25.0
926052	AC1-083 E O1	40.78
926461	AC1-117 C	1.07
926462	AC1-117 E	1.75
933941	AD1-017 C	5.0
933942	AD1-017 E	8.16
936161	AD2-022 C O1	18.75
936162	AD2-022 E O1	11.25
936171	AD2-023 C O1	10.95
936172	AD2-023 E O1	5.95
938741	AE1-100 C O1	6.6
938742	AE1-100 E O1	3.8
938931	AE1-121 O1	76.3
938941	AE1-122 O1	76.3
939943	AE1-230 E2	0.42
940081	AE1-250 C	48.34
940082	AE1-250 E	32.23
940601	AE2-047 C O2	5.43
940602	AE2-047 E O2	3.62
941431	AE2-140 C O2	19.0
941432	AE2-140 E O2	12.67
941671	AE2-166 C	7.89
941672	AE2-166 E	5.26
942321	AE2-245	0.98
CARR	CARR	0.0
CBM-S1	CBM-S1	1.19
CBM-S2	CBM-S2	0.35
CBM-W1	CBM-W1	1.89
CBM-W2	CBM-W2	8.3
CIN	CIN	0.86
G-007	G-007	0.04
IPL	IPL	0.55
LGEE	LGEE	0.26
MEC	MEC	1.59
MECS	MECS	1.03
O-066	O-066	0.25
RENSSELAER	RENSSELAER	0.0
WEC	WEC	0.22

25.6 Index 6

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC DC	MW IMPACT
11625127	242544	05AXTON	AEP	242620	05DANVL2	AEP	1	AEP_P4_#10171_05AXTON 138_G	breaker	382.0	149.78	161.62	DC	45.22

Bus #	Bus	MW Impact
247723	05PHILPOTT	0.49
926461	AC1-117 C	3.69
926462	AC1-117 E	6.03
938741	AE1-100 C O1	22.65
938742	AE1-100 E O1	13.03
938931	AE1-121 O1	261.96
938941	AE1-122 O1	261.96
940083	AE1-250 EBAT	6.02
940601	AE2-047 C O2	2.61
940602	AE2-047 E O2	1.74
941431	AE2-140 C O2	65.24
941432	AE2-140 E O2	43.49
941671	AE2-166 C	27.13
941672	AE2-166 E	18.09
942321	AE2-245	3.36
CALDERWOOD	CALDERWOOD	0.22
CARR	CARR	0.01
CATAWBA	CATAWBA	0.56
CBM-W1	CBM-W1	1.75
CHEOAH	CHEOAH	0.23
CHILHOWEE	CHILHOWEE	0.07
CIN	CIN	0.84
COTTONWOOD	COTTONWOOD	0.5
G-007	G-007	0.09
HAMLET	HAMLET	1.38
IPL	IPL	0.56
LGEE	LGEE	0.26
MEC	MEC	0.89
MECS	MECS	1.35
O-066	O-066	0.54
RENSSELAER	RENSSELAER	0.01
SANTEETLA	SANTEETLA	0.07
TVA	TVA	0.35
UNIONPOWER	UNIONPOWER	0.35
WEC	WEC	0.2

25.7 Index 8

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
2582429	242620	05DANVL2	AEP	242631	05EDAN 1	AEP	1	242509 05AXTON 765 242514 05J.FERR 765 1	single	402.0	109.38	116.41	DC	28.27

Bus #	Bus	MW Impact
242906	05CLAY-1	0.32
242907	05CLAY-2	0.32
247723	05PHILPOTT	0.53
926461	AC1-117 C	3.86
934751	AD1-102 C	1.32
938741	AE1-100 C O1	23.49
938931	AE1-121 O1	271.61
938941	AE1-122 O1	271.61
939441	AE1-176	0.15
940601	AE2-047 C O2	8.42
941431	AE2-140 C O2	67.64
941671	AE2-166 C	28.27
942321	AE2-245	3.51
942641	AE2-280 C O2	5.14
CALDERWOOD	CALDERWOOD	0.24
CARR	CARR	0.01
CATAWBA	CATAWBA	0.61
CBM-W1	CBM-W1	1.93
CBM-W2	CBM-W2	0.02
CHEOAH	CHEOAH	0.24
CHILHOWEE	CHILHOWEE	0.07
CIN	CIN	0.92
COTTONWOOD	COTTONWOOD	0.53
HAMLET	HAMLET	1.5
IPL	IPL	0.62
LGEE	LGEE	0.29
MEC	MEC	0.98
MECS	MECS	1.48
RENSSELAER	RENSSELAER	0.01
SANTEETLA	SANTEETLA	0.08
TVA	TVA	0.37
UNIONPOWER	UNIONPOWER	0.38
WEC	WEC	0.23

25.8 Index 9

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CKT ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC DC	MW IMPACT
1565827	242631	05EDAN 1	AEP	242632	05EDAN 2	AEP	Z1	AEP_P4_#2916_05J.FERR 765_A	breaker	296.0	123.98	133.13	DC	27.08

Bus #	Bus	MW Impact
244012	05PINNACLE	2.39
247723	05PHILPOTT	0.29
926461	AC1-117 C	2.21
926462	AC1-117 E	3.61
936161	AD2-022 C O1	12.52
936162	AD2-022 E O1	7.51
938741	AE1-100 C O1	13.58
938742	AE1-100 E O1	7.81
938931	AE1-121 O1	157.01
938941	AE1-122 O1	157.01
939943	AE1-230 E2	0.27
940083	AE1-250 EBAT	49.74
940601	AE2-047 C O2	4.77
940602	AE2-047 E O2	3.18
941431	AE2-140 C O2	39.1
941432	AE2-140 E O2	26.07
941671	AE2-166 C	16.25
941672	AE2-166 E	10.83
942321	AE2-245	2.01
CBM-N	CBM-N	0.01
CBM-S1	CBM-S1	0.55
CBM-S2	CBM-S2	0.34
CBM-W1	CBM-W1	0.81
CBM-W2	CBM-W2	3.82
CIN	CIN	0.36
CPLE	CPLE	0.05
G-007A	G-007A	0.02
IPL	IPL	0.23
LGEE	LGEE	0.11
MEC	MEC	0.7
MECS	MECS	0.44
NYISO	NYISO	0.06
VFT	VFT	0.05
WEC	WEC	0.1

25.9 Index 10

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC DC	MW IMPACT
1565686	242711	05MARTN1	AEP	242744	05PATCTR	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	202.0	159.38	171.21	DC	23.9

Bus #	Bus	MW Impact
926461	AC1-117 C	2.26
926462	AC1-117 E	3.69
938741	AE1-100 C O1	8.02
938742	AE1-100 E O1	4.61
938931	AE1-121 O1	92.69
938941	AE1-122 O1	92.69
941431	AE2-140 C O2	23.08
941432	AE2-140 E O2	15.39
941671	AE2-166 C	14.34
941672	AE2-166 E	9.56
942321	AE2-245	2.05
CARR	CARR	0.01
CBM-S1	CBM-S1	0.69
CBM-S2	CBM-S2	0.7
CBM-W1	CBM-W1	0.59
CBM-W2	CBM-W2	4.27
CIN	CIN	0.27
CPLE	CPLE	0.47
G-007	G-007	0.05
IPL	IPL	0.17
LGEE	LGEE	0.08
MEC	MEC	0.63
MECS	MECS	0.22
O-066	O-066	0.28
RENSSELAER	RENSSELAER	0.01
WEC	WEC	0.07

25.10 Index 11

ID	FROM BUS#	FROM BUS	FROM BUS AREA	TO BUS#	TO BUS	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADIN G %	POST PROJECT LOADIN G %	AC D C	MW IMPACT
45308205	941670	AE2-166 TAP	AEP	242816	05STOCK T	AEP	1	AEP_P4_#10168_05AXTON 138_H	breaker	273.0	134.44	143.85	DC	25.67

Bus #	Bus	MW Impact
938741	AE1-100 C O1	8.61
938742	AE1-100 E O1	4.95
938931	AE1-121 O1	99.51
938941	AE1-122 O1	99.51
941431	AE2-140 C O2	24.78
941432	AE2-140 E O2	16.52
941671	AE2-166 C	15.4
941672	AE2-166 E	10.27
CARR	CARR	0.01
CBM-S1	CBM-S1	0.72
CBM-S2	CBM-S2	0.73
CBM-W1	CBM-W1	0.63
CBM-W2	CBM-W2	4.48
CIN	CIN	0.29
CPLE	CPLE	0.49
G-007	G-007	0.05
IPL	IPL	0.18
LGEE	LGEE	0.08
MEC	MEC	0.67
MECS	MECS	0.23
O-066	O-066	0.3
RENSSELAER	RENSSELAER	0.01
WEC	WEC	0.08

Affected Systems

26 Affected Systems

26.1 LG&E

LG&E Impacts to be determined during later study phases (as applicable).

26.2 MISO

MISO Impacts to be determined during later study phases (as applicable).

26.3 TVA

TVA Impacts to be determined during later study phases (as applicable).

26.4 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

26.5 NYISO

NYISO Impacts to be determined during later study phases (as applicable).

27 Contingency Descriptions

Contingency Name	Contingency Definition
242509 05AXTON 765 242514 05J.FERR 765 1	CONTINGENCY '242509 05AXTON 765 242514 05J.FERR 765 1' / 8403 OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 END
AEP_P1-2_#5459	CONTINGENCY 'AEP_P1-2_#5459' OPEN BRANCH FROM BUS 242544 TO BUS 242712 CKT 1 / 242544 05AXTON 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242638 CKT 1 / 242614 05COLLIN 138 242638 05FIELDAL1 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242712 CKT 1 / 242614 05COLLIN 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242712 TO BUS 243977 CKT 1 / 242712 05MARTN2 138 243977 05MART 115 34.5 1 OPEN BRANCH FROM BUS 243977 TO BUS 243979 CKT Z1 / 243977 05MART 115 34.5 243979 05MART2-30 34.5 Z1 OPEN BRANCH FROM BUS 243977 TO BUS 243980 CKT 1 / 243977 05MART 115 34.5 243980 05MORRIS-N 34.5 1 END
AEP_P1-2_#1370	CONTINGENCY 'AEP_P1-2_#1370' OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242509 TO BUS 242545 CKT 1 / 242509 05AXTON 765 242545 05AXTONX 138 1 OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT SR / 242544 05AXTON 138 242545 05AXTONX 138 SR OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT ZB / 242544 05AXTON 138 242545 05AXTONX 138 ZB END
AEP_P4_#2916_05J.FERR 765_A	CONTINGENCY 'AEP_P4_#2916_05J.FERR 765_A' OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242511 TO BUS 242514 CKT 1 / 242511 05BROADF 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242509 TO BUS 242545 CKT 1 / 242509 05AXTON 765 242545 05AXTONX 138 1 OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT SR / 242544 05AXTON 138 242545 05AXTONX 138 SR OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT ZB / 242544 05AXTON 138 242545 05AXTONX 138 ZB OPEN BRANCH FROM BUS 242566 TO BUS 242567 CKT ZB / 242566 05BROADF 138 242567 05BROADX 138 ZB END

Contingency Name	Contingency Definition
AEP_P4_#10171_05AXTON 138_G	CONTINGENCY 'AEP_P4_#10171_05AXTON 138_G' OPEN BRANCH FROM BUS 242509 TO BUS 242514 CKT 1 / 242509 05AXTON 765 242514 05J.FERR 765 1 OPEN BRANCH FROM BUS 242509 TO BUS 242545 CKT 1 / 242509 05AXTON 765 242545 05AXTONX 138 1 OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT SR / 242544 05AXTON 138 242545 05AXTONX 138 SR OPEN BRANCH FROM BUS 242544 TO BUS 242545 CKT ZB / 242544 05AXTON 138 242545 05AXTONX 138 ZB OPEN BRANCH FROM BUS 242544 TO BUS 242619 CKT 2 / 242544 05AXTON 138 242619 05DANVL1 138 2 END
AEP_P1-2_#5458-A	CONTINGENCY 'AEP_P1-2_#5458-A' OPEN BRANCH FROM BUS 941670 TO BUS 242816 CKT 1 / 941670 AE2-166 TAP 138 242816 05STOCKT 138 1 OPEN BRANCH FROM BUS 242711 TO BUS 242816 CKT 1 / 242711 05MARTN1 138 242816 05STOCKT 138 1 END
Base Case	
AEP_P7-1_#10781-B	CONTINGENCY 'AEP_P7-1_#10781-B' OPEN BRANCH FROM BUS 936160 TO BUS 304024 CKT 1 / 936160 AD2-022 TAP 230 304024 6ROXSEP230 T 230 1 OPEN BRANCH FROM BUS 936170 TO BUS 304094 CKT 1 / 936170 AD2-023 TAP 230 304094 6YANCY TAP 230 1 OPEN BRANCH FROM BUS 304098 TO BUS 304094 CKT 1 / 304098 6CONCRD230TT 230 304094 6YANCY TAP 230 1 OPEN BRANCH FROM BUS 304094 TO BUS 304095 CKT 1 / 304094 6YANCY TAP 230 304095 6YANCYVILLE 230 1 END
AEP_P4_#10168_05AXTON 138_H	CONTINGENCY 'AEP_P4_#10168_05AXTON 138_H' OPEN BRANCH FROM BUS 242544 TO BUS 242620 CKT 1 / 242544 05AXTON 138 242620 05DANVL2 138 1 OPEN BRANCH FROM BUS 242544 TO BUS 242712 CKT 1 / 242544 05AXTON 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242638 CKT 1 / 242614 05COLLIN 138 242638 05FIELDAL1 138 1 OPEN BRANCH FROM BUS 242614 TO BUS 242712 CKT 1 / 242614 05COLLIN 138 242712 05MARTN2 138 1 OPEN BRANCH FROM BUS 242712 TO BUS 243977 CKT 1 / 242712 05MARTN2 138 243977 05MART 115 34.5 1 OPEN BRANCH FROM BUS 243977 TO BUS 243979 CKT Z1 / 243977 05MART 115 34.5 243979 05MART2-30 34.5 Z1 OPEN BRANCH FROM BUS 243977 TO BUS 243980 CKT 1 / 243977 05MART 115 34.5 243980 05MORRIS-N 34.5 1 END
247499 05SMITHMTN2 - 242802 05SMITHMTN1 CKT Z1	CONTINGENCY '247499 05SMITHMTN2 - 242802 05SMITHMTN1 CKT Z1' /MISSING SINGLE DISCONNECT BRANCH FROM BUS 247499 TO BUS 242802 CKT Z1 END

Short Circuit

28 Short Circuit

The following Breakers are overduty

None