



**Generation Interconnection
Feasibility Study Report
for
Queue Project AF1-042
GARNER DP-LANCASTER 115 KV
17.1 MW Capacity / 45 MW Energy**

January, 2020

Table of Contents

1	Introduction	4
2	Preface	4
3	General	5
3.1	Point of Interconnection	5
3.2	Cost Summary	6
4	Transmission Owner Scope of Work	6
5	Non-Direct Connection Cost Estimate	7
6	Schedule	7
7	Transmission Owner Analysis	8
7.1	Power Flow Analysis	8
7.2	Short Circuit Analysis	8
7.3	Stability Analysis	8
8	Interconnection Customer Requirements	8
8.1	System Protection	8
8.2	Compliance Issues and Interconnection Customer Requirements	8
8.3	Power Factor Requirements	9
9	Revenue Metering and SCADA Requirements	9
9.1	PJM Requirements	9
9.1.1	Meteorological Data Reporting Requirement	9
9.2	Dominion Requirements	9
10	Network Impacts	10
10.1	Generation Deliverability	12
10.2	Multiple Facility Contingency	12
10.3	Contribution to Previously Identified Overloads	12
10.4	Potential Congestion due to Local Energy Deliverability	12
10.5	System Reinforcements	13
10.6	Flow Gate Details	13
10.6.1	Contingency Descriptions	13

10.7	Short Circuit.....	15
11	Affected Systems	17
11.1	Duke Energy Progress.....	17
Attachment 1	18

1 Introduction

This Feasibility Study has been prepared in accordance with the PJM Open Access Transmission Tariff, 36.2, as well as the Feasibility Study Agreement between, the Interconnection Customer (IC), and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Virginia Electric and Power Company (VEPCO).

2 Preface

The intent of the feasibility study is to determine a plan, with ballpark cost and construction time estimates, to connect the subject generation to the PJM network at a location specified by the Interconnection Customer. The Interconnection Customer may request the interconnection of generation as a capacity resource or as an energy-only resource. As a requirement for interconnection, the Interconnection Customer may be responsible for the cost of constructing: (1) Direct Connections, which are new facilities and/or facilities upgrades needed to connect the generator to the PJM network, and (2) Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system.

In some instances, a generator interconnection may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection, may also contribute to the need for the same network reinforcement. Cost allocation rules for network upgrades can be found in PJM Manual 14A, Attachment B. The possibility of sharing the reinforcement costs with other projects may be identified in the feasibility study, but the actual allocation will be deferred until the impact study is performed.

The Interconnection Customer seeking to interconnect a wind or solar generation facility shall maintain meteorological data facilities as well as provide that meteorological data which is required per Schedule H to the Interconnection Service Agreement and Section 8 of Manual 14D.

An Interconnection Customer with a proposed new Customer Facility that has a Maximum Facility Output equal to or greater than 100 MW shall install and maintain, at its expense, phasor measurement units (PMUs). See Section 8.5.3 of Appendix 2 to the Interconnection Service Agreement as well as section 4.3 of PJM Manual 14D for additional information.

PJM utilizes manufacturer models to ensure the performance of turbines is properly captured during the simulations performed for stability verification and, where applicable, for compliance with low voltage ride through requirements. Turbine manufacturers provide such models to their customers. The list of manufacturer models PJM has already validated is contained in Attachment B of Manual 14G. Manufacturer models may be updated from time to time, for various reasons such as to reflect changes to the control systems or to more accurately represent the capabilities turbines and controls which are currently available in the field. Additionally, as new turbine models are developed, turbine manufacturers provide such new models which must be used in the conduct of these studies. PJM needs adequate time to evaluate the new models in

order to reduce delays to the System Impact Study process timeline for the Interconnection Customer as well as other Interconnection Customers in the study group. Therefore, PJM will require that any Interconnection Customer with a new manufacturer model must supply that model to PJM, along with a \$10,000 fully refundable deposit, no later than three (3) months prior to the starting date of the System Impact Study (See Section 4.3 for starting dates) for the Interconnection Request which shall specify the use of the new model. The Interconnection Customer will be required to submit a completed dynamic model study request form (Attachment B-1 of Manual 14G) in order to document the request for the study.

The Feasibility Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The project developer is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

3 General

The Interconnection Customer (IC), has proposed an uprate to a planned solar generating facility located in Lancaster County, Virginia. This projects requests an increase to the facility capability of 45 MW with 17.1 MW of this output being recognized by PJM as Capacity. The entire facilities will have a total capability of 131 MW with 49.78 MW of this output being recognized by PJM as Capacity. The proposed in-service date for this project is 11/30/2021. This study does not imply a TO commitment to this in-service date.

Note that this project is an increase to the Interconnection Customer's AD2-074 project, which will share the same property and connection point.

Queue Number	AF1-042
Project Name	GARNER DP-LANCASTER 115 KV
State	Virginia
County	Lancaster
Transmission Owner	Dominion
MFO	131
MWE	45
MWC	17.1
Fuel	Solar
Basecase Study Year	2023

3.1 Point of Interconnection

AF1-042 will interconnect with the Dominion transmission system. The POI will be a 115 kV substation tapping the Garner - Lancaster 115kV line. The POI will be 5.58 miles away from Dominion Garner substation and 8.40 miles away from Lancaster substation.

3.2 Cost Summary

The AF1-042 project will utilize the interconnection facilities being developed under the AD2-074 project.

In addition, the AF1-042 project may be responsible for a contribution to the following costs

Description	Total Cost
System Upgrades	\$ 0

Cost allocations for upgrades will be provided in the System Impact Study Report.

The Feasibility Study is used to make a preliminary determination of the type and scope of Attachment Facilities, Local Upgrades, and Network Upgrades that will be necessary to accommodate the Interconnection Request and to provide the Interconnection Customer a preliminary estimate of the time that will be required to construct any necessary facilities and upgrades and the Interconnection Customer's cost responsibility. The System Impact Study provides refined and comprehensive estimates of cost responsibility and construction lead times for new facilities and system upgrades. Facilities Studies will include, commensurate with the degree of engineering specificity as provided in the Facilities Study Agreement, good faith estimates of the cost, determined in accordance with Section 217 of the Tariff,

- (a) to be charged to each affected New Service Customer for the Facilities and System Upgrades that are necessary to accommodate this queue project;
- (b) the time required to complete detailed design and construction of the facilities and upgrades; and
- (c) a description of any site-specific environmental issues or requirements that could reasonably be anticipated to affect the cost or time required to complete construction of such facilities and upgrades.

4 Transmission Owner Scope of Work

Dominion assessed the impact of the proposed Queue Project AF1-042. The project was evaluated as a 17.1 MW Capacity (45.0 MW energy) injection at the existing AD2-074 substation in the Dominion Transmission System, for compliance with NERC Reliability Criteria on Dominion Transmission System. The system was assessed using the summer 2023 AF1 case provided to Dominion by PJM. When performing a generation analysis, Dominion's main analysis will be load flow study results under single contingency (both normal and stressed system conditions). Dominion Criteria considers a transmission facility overloaded if it exceeds 94% of its emergency rating under normal and stressed system conditions. A full listing of Dominion's Planning Criteria and interconnection requirements can be found in the Company's Facility Connection Requirements which are publicly available at: <http://www.dominionenergy.com>.

The results of these studies evaluate the system under a limited set of operating conditions and do not guarantee the full delivery of the capacity and associated energy of this proposed generation facility under all operating conditions. NERC Planning and Operating Reliability Criteria allow for the re-dispatch of generating units to resolve projected and actual deficiencies in real time and planning studies. Specifically, in Planning Studies, NERC Planning Event 3 and 6 Contingency Conditions (Loss of generator, transmission circuit, transformer, shunt device, or Single Pole of a DC line followed by the loss of a generator, transmission circuit, transformer, shunt device or single pole of a DC line) allow for re-dispatch of generating units to resolve potential reliability deficiencies. For Dominion Planning Criteria the re-dispatch of generating units for these contingency conditions is allowed as long as the projected loading does not exceed 100% of a facility Load Dump Rating.

The required Attachment Facilities, Direct Connection and Non-Direct Connection work for the interconnection of the AF1-042 generation project to the Dominion Transmission System is detailed in the following sections. The associated one-line with the generation project attachment facilities and primary direct and non-direct connection are shown in Attachment 1.

Note that the ITO findings were made from a conceptual review of this project. A more detailed review of the connection facilities and their cost will be identified in a future study phases. Further note that the cost estimate data contained in this document should be considered high level estimates since it was produced without a detailed engineering review. The applicant will be responsible for the actual cost of construction. ITO herein reserves the right to return to any issues in this document and, upon appropriate justification, request additional monies to complete any reinforcements to the transmission systems.

5 Non-Direct Connection Cost Estimate

Remote Terminal Work: During the Facilities Study, ITO's System Protection Engineering Department will review transmission line protection as well as anti-islanding required to accommodate the new generation and interconnection substation. System Protection Engineering will determine the minimal acceptable protection requirements to reliably interconnect the proposed generating facility with the transmission system. The review is based on maintaining system reliability by reviewing ITO's protection requirements with the known transmission system configuration which includes generating facilities in the area. This review may determine that transmission line protection and communication upgrades are required at remote substations.

6 Schedule

The schedule for the required Network Impact Reinforcements will be more clearly identified in future study phases. The estimate elapsed time to complete each of the required reinforcements is identified in the "System Reinforcements" section of the report.

7 Transmission Owner Analysis

7.1 Power Flow Analysis

PJM performed a power flow analysis of the transmission system using a 2023 summer peak load flow model and the results were verified by Dominion. Additionally, Dominion performed an analysis of its transmission system and no further deficiencies were identified.

7.2 Short Circuit Analysis

PJM performed a short circuit analysis and the results were verified by Dominion. The connection of AF1-042 project to the system does not result in any newly overdutied circuit breakers on the Dominion transmission system and does not have a significant fault current contribution to existing overdutied circuit breakers.

7.3 Stability Analysis

PJM will complete a dynamic stability analysis, if necessary, as part of the System Impact Study. The results of this analysis will be reviewed by Dominion. Should stability concerns be identified in PJM's study, Dominion will develop appropriate system reinforcement(s) and included the estimated cost of any reinforcement(s) in Dominion's System Impact Study report.

8 Interconnection Customer Requirements

8.1 System Protection

The IC must design its Customer Facilities in accordance with all applicable standards, including the standards in Dominion's "Dominion Energy Electric Transmission Generator Interconnection Requirements" documented in Dominion's Facility Interconnection Requirements "Exhibit C" located at:

<https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>. Preliminary

Protection requirements will be provided as part of the Facilities Study. Detailed Protection Requirements will be provided once the project enters the construction phase.

8.2 Compliance Issues and Interconnection Customer Requirements

The proposed Customer Facilities must be designed in accordance with Dominion's "Dominion's Facility Interconnection Requirements" document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>. In particular, the IC is responsible for the following:

1. The purchase and installation of a fully rated protection device (circuit breaker, circuit switcher, fuse) to protect the IC's GSU transformer(s).
2. The purchase and installation of the minimum required Dominion generation interconnection relaying and control facilities as described in the System Protection noted above. This includes over/under voltage protection, over/under frequency protection, and zero sequence voltage protection relays.
3. The purchase and installation of supervisory control and data acquisition ("SCADA") equipment to provide information in a compatible format to the Dominion Transmission System Control Center.

4. Compliance with the Dominion and PJM generator power factor and voltage control requirements.

The GSU(s) associated with the IC queue request shall meet the grounding requirements as noted in Dominion's "Dominion's Facility Interconnection Requirements" document located at:

<https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>.

The IC will also be required to meet all PJM, SERC, and NERC reliability criteria and operating procedures for standards compliance. For example, the IC will need to properly locate and report the over and under voltage and over and under frequency system protection elements for its units as well as the submission of the generator model and protection data required to satisfy the PJM and SERC audits. Failure to comply with these requirements may result in a disconnection of service if the violation is found to compromise the reliability of the Dominion system.

8.3 Power Factor Requirements

The IC shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading (absorbing VARs) to 0.95 lagging (supplying VARs) measured at the high-side of the facility substation transformer(s) connected to the Dominion transmission system.

9 Revenue Metering and SCADA Requirements

9.1 PJM Requirements

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Section 8 of Attachment O.

9.1.1 Meteorological Data Reporting Requirement

The solar generation facility shall provide the Transmission Provider with site-specific meteorological data including:

- Temperature (degrees Fahrenheit)
- Atmospheric pressure (hectopascals)
- Irradiance
- Forced outage data

9.2 Dominion Requirements

See Section 3.4.6 "Metering and telecommunications" of Dominion's "Dominion's Facility Interconnection Requirements" document located at: <https://www.dominionenergy.com/company/moving-energy/electric-transmission-access>.

10 Network Impacts

The Queue Project AF1-042 was evaluated as a 45.0 MW (Capacity 17.1 MW) injection as an uprate to AD2-074 that taps the Garner to Lancaster 115 kV line in the Dominion area. Project AF1-042 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AF1-042 was studied with a commercial probability of 53%. Potential network impacts were as follows:

Summer Peak Load Flow

10.1 Generation Deliverability

(Single or N-1 contingencies for the Capacity portion only of the interconnection)

None

10.2 Multiple Facility Contingency

(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output)

None

10.3 Contribution to Previously Identified Overloads

(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)

None

10.4 Potential Congestion due to Local Energy Deliverability

PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The developer can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.

Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this project by fixing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.

ID	FROM BUS#	FROM BUS	kV	FROM BUS AREA	TO BUS#	TO BUS	kV	TO BUS AREA	CK T ID	CONT NAME	Type	Rating MVA	PRE PROJECT LOADING %	POST PROJECT LOADING %	AC/DC	MW IMPACT
43014920	313886	3GREYST	115.0	DVP	314174	3HARMONY	115.0	DVP	1	DVP_P1-2: LN 2083	operation	138.18	84.89	101.16	DC	22.5
43014816	314173	3GARNER	115.0	DVP	314181	3NORNECK	115.0	DVP	1	DVP_P1-2: LN 65-B	operation	203.98	104.57	126.63	DC	45.0
45983808	314173	3GARNER	115.0	DVP	314181	3NORNECK	115.0	DVP	1	3141783LANCAST 115 936590 AD2-074 TAP 115 1	operation	203.98	104.57	126.63	DC	45.0
43014918	314191	3WHITSTONE	115.0	DVP	313870	3RAPPHNCK	115.0	DVP	1	DVP_P1-2: LN 2083	operation	138.18	84.96	101.23	DC	22.5

10.5 System Reinforcements

None

10.6 Flow Gate Details

The following indices contain additional information about each flowgate presented in the body of the report. For each index, a description of the flowgate and its contingency was included for convenience. However, the intent of the appendix section is to provide more information on which projects/generators have contributions to the flowgate in question. Although this information is not used "as is" for cost allocation purposes, it can be used to gage other generators impact. It should be noted the generator contributions presented in the appendices sections are full contributions, whereas in the body of the report, those contributions take into consideration the commercial probability of each project.

10.6.1 Contingency Descriptions

Contingency Name	Contingency Definition
DVP_P1-2: LN 2083	CONTINGENCY 'DVP_P1-2: LN 2083' OPEN BRANCH FROM BUS 314132 TO BUS 314163 CKT 1 /* 6BIRCHWD 230.00 - 6FINES 230.00 OPEN BRANCH FROM BUS 314137 TO BUS 314163 CKT 1 /* 6FREDBRG 230.00 - 6FINES 230.00 OPEN BUS 314163 /* ISLAND: 6FINES 230.00 END
DVP_P1-2: LN 65-B	CONTINGENCY 'DVP_P1-2: LN 65-B' OPEN BRANCH FROM BUS 313813 TO BUS 314178 CKT 1 /* 3OCRAN 115.00 - 3LANCAST 115.00 OPEN BRANCH FROM BUS 313813 TO BUS 314191 CKT 1 /* 3OCRAN 115.00 - 3WHIT STONE 115.00 OPEN BRANCH FROM BUS 313870 TO BUS 314191 CKT 1 /* 3RAPPAHNCK 115.00 - 3WHIT STONE 115.00 OPEN BRANCH FROM BUS 936590 TO BUS 314178 CKT 1 /* AD2-074 TAP 115.00 - 3LANCAST 115.00 OPEN BRANCH FROM BUS 314178 TO BUS 314400 CKT 1 /* 3LANCAST 115.00 - 3LANCA_1 115.00 OPEN BUS 313813 /* ISLAND: 3OCRAN 115.00 OPEN BUS 314178 /* ISLAND: 3LANCAST 115.00 OPEN BUS 314191 /* ISLAND: 3WHIT STONE 115.00 OPEN BUS 314400 /* ISLAND: 3LANCA_1 115.00 END
314178 3LANCAST 115 936590 AD2-074 TAP 115 1	CONTINGENCY '314178 3LANCAST 115 936590 AD2-074 TAP 115 1' OPEN BRANCH FROM BUS 314178 TO BUS 936590 CKT 1 END

Short Circuit

10.7 Short Circuit

The following Breakers are overdutied:

None

Affected Systems

11 Affected Systems

11.1 Duke Energy Progress

Duke Energy Progress Impacts to be determined during later study phases (as applicable).

Attachment 1

System Configuration