

***Generation Interconnection  
System Impact Study Report***

***For***

***PJM Generation Interconnection Request  
Queue Position AD1-041***

***Harmony Village – Shackleford 115kV  
30MW Capacity / 50 MW Energy***

**Revised July 2020**

**Revised May 2019**

**December 2018**

## Introduction

This System Impact Study (SIS) has been prepared in accordance with the PJM Open Access Transmission Tariff, Section 205, as well as the System Impact Study Agreement between Carvers Creek LLC, the Interconnection Customer (IC) and PJM Interconnection, LLC (PJM), Transmission Provider (TP). The Interconnected Transmission Owner (ITO) is Virginia Electric and Power Company (VEPCO).

## Preface

The intent of the System Impact Study is to determine a plan, with approximate cost and construction time estimates, to connect the subject generation interconnection project to the PJM network at a location specified by the IC. As a requirement for interconnection, the IC may be responsible for the cost of constructing Network Upgrades, which are facility additions, or upgrades to existing facilities, that are needed to maintain the reliability of the PJM system. All facilities required for interconnection of a generation interconnection project must be designed to meet the technical specifications (on PJM web site) for the appropriate transmission owner.

In some instances an IC may not be responsible for 100% of the identified network upgrade cost because other transmission network uses, e.g. another generation interconnection or merchant transmission upgrade, may also contribute to the need for the same network reinforcement. The possibility of sharing the reinforcement costs with other projects may be identified in the Feasibility Study, but the actual allocation will be deferred until the System Impact Study is performed.

The System Impact Study estimates do not include the feasibility, cost, or time required to obtain property rights and permits for construction of the required facilities. The IC is responsible for the right of way, real estate, and construction permit issues. For properties currently owned by Transmission Owners, the costs may be included in the study.

## General

The IC has proposed a solar generating facility located in Gloucester Courthouse, VA (Gloucester County). The installed facilities will have a total capability of 50 MW with 30 MW of this output being recognized by PJM as capacity. The proposed in-service date for this project is 12/23/2019. **This study does not imply an ITO commitment to this in-service date.**

## Point of Interconnection

AD1-041 will interconnect with the ITO transmission system via a new three breaker ring bus switching station that connects on the Harmony Village – Shackleford 115kV line #85.

## **Cost Summary**

The AD1-041 interconnection request will be responsible for the following costs:

<b>Description</b>	<b>Total Cost</b>
Attachment Facilities	\$1,550,000
Direct Connection Network Upgrades	\$5,500,000
Non Direct Connection Network Upgrades	\$800,000
Allocation for New System Upgrades	\$0
Contribution for Previously Identified Upgrades	\$0
<b>Total Costs</b>	<b>\$7,850,000</b>

## **Attachment Facilities**

Generation Substation: Install metering and associated protection equipment. Estimated Cost \$550,000.

Transmission: Construct approximately one span of 115 kV Attachment line between the generation substation and a new AD1-041 Switching Station. The estimated cost for this work is \$1,000,000.

The estimated total cost of the Attachment Facilities is \$1,550,000. It is estimated to take 18-24 months to complete this work. These preliminary cost estimates are based on typical engineering costs. A more detailed engineering cost estimates are normally done when the IC provides an exact site plan location for the generation substation during the Facility Study phase. These costs do not include CIAC Tax Gross-up. The single line is shown below in Attachment 1.

## **Direct Connection Cost Estimate**

Substation: Establish the new 115 kV AD1-041 Switching Substation (interconnection substation). The estimated cost to complete this work scope is \$5,500,000. It is estimated to take 24-36 months to complete this work.

## **Non-Direct Connection Cost Estimate**

Transmission: Install transmission structure in-line with transmission line to allow the proposed interconnection switching station to be interconnected with the transmission system. Estimated cost is \$800,000 and is estimated to take 24-30 months to complete.

Remote Terminal Work: During the Facilities Study, ITO's System Protection Engineering Department will review transmission line protection as well as anti-islanding required to accommodate the new generation and interconnection substation. System Protection Engineering will determine the minimal acceptable protection requirements to reliably interconnect the proposed generating facility with the transmission system. The review is based on maintaining system reliability by reviewing ITO's protection requirements with the known transmission system configuration which includes generating facilities in the area. This review may determine that transmission line protection and communication upgrades are required at remote substations.

## **System Reinforcements**

None

## **Interconnection Customer Requirements**

ITO's Facility Interconnection Requirements as posted on PJM's website

<http://www.pjm.com/~media/planning/plan-standards/private-dominion/facility-connection-requirements1.ashx>

**Voltage Ride Through Requirements** - The Customer Facility shall be designed to remain in service (not trip) for voltages and times as specified for the Eastern Interconnection in Attachment 1 of NERC Reliability Standard PRC-024-1, and successor Reliability Standards, for both high and low voltage conditions, irrespective of generator size, subject to the permissive trip exceptions established in PRC-024-1 (and successor Reliability Standards).

**Frequency Ride Through Requirements** - The Customer Facility shall be designed to remain in service (not trip) for frequencies and times as specified in Attachment 2 of NERC Reliability Standard PRC-024-1, and successor Reliability Standards, for both high and low frequency condition, irrespective of generator size, subject to the permissive trip exceptions established in PRC-024-1 (and successor Reliability Standards).

**Reactive Power** - The Generation Interconnection Customer shall design its non-synchronous Customer Facility with the ability to maintain a power factor of at least 0.95 leading to 0.95 lagging measured at the generator's terminals.

**Meteorological Data Reporting Requirement** - The solar generation facility shall, at a minimum, be required to provide the Transmission Provider with site-specific meteorological data including:

- Temperature (degrees Fahrenheit)
- Atmospheric pressure (hectopascals)
- Irradiance
- Forced outage data

## **Revenue Metering and SCADA Requirements**

### **PJM Requirements**

The Interconnection Customer will be required to install equipment necessary to provide Revenue Metering (KWH, KVARH) and real time data (KW, KVAR) for IC's generating Resource. See PJM Manuals M-01 and M-14D, and PJM Tariff Sections 24.1 and 24.2.

### **Interconnected Transmission Owner Requirements**

Metering and SCADA/Communication equipment must meet the requirements outlined in section 3.1.6 Metering and Telecommunications of ITO's Facility Connection Requirement NERC Standard FAC-001 which is publically available at [www.dom.com](http://www.dom.com).

## **Network Impacts**

The Queue Project AD1-041 was evaluated as a 50.0 MW (Capacity 30.0 MW) injection tapping into Harmony Village - Shackleford 115kV line in the ITO area. Project AD1-041 was evaluated for compliance with applicable reliability planning criteria (PJM, NERC, NERC Regional Reliability Councils, and Transmission Owners). Project AD1-041 was studied with a commercial probability of 100%. Potential network impacts were as follows:

## **Summer Peak Analysis – 2021**

### **Generator Deliverability**

*(Single or N-1 contingencies for the Capacity portion only of the interconnection)*

None

### **Multiple Facility Contingency**

*(Double Circuit Tower Line, Fault with a Stuck Breaker, and Bus Fault contingencies for the full energy output).*

None

### **Short Circuit**

*(Summary of impacted circuit breakers)*

New circuit breakers found to be over-duty:

None

Contributions to previously identified circuit breakers found to be over-duty:

None

### **Contribution to Previously Identified Overloads**

*(This project contributes to the following contingency overloads, i.e. "Network Impacts", identified for earlier generation or transmission interconnection projects in the PJM Queue)*

None

### **Steady-State Voltage Requirements**

*(Summary of the VAR requirements based upon the results of the steady-state voltage studies)*

None

## **Stability and Reactive Power Requirement for Low Voltage Ride Through**

*(Summary of the VAR requirements based upon the results of the dynamic studies)*

No mitigations were found to be required.

## **New System Reinforcements**

*(Upgrades required to mitigate reliability criteria violations, i.e. Network Impacts, initially caused by the addition of this interconnection request)*

None

## **Contribution to Previously Identified System Reinforcements**

*(Overloads initially caused by prior Queue positions with additional contribution to overloading by this project. This project may have a % allocation cost responsibility which is calculated and reported for in the Impact Study)*

None

## **Potential Congestion due to Local Energy Deliverability**

*PJM also studied the delivery of the energy portion of this interconnection request. Any problems identified below are likely to result in operational restrictions to the project under study. The IC can proceed with network upgrades to eliminate the operational restriction at their discretion by submitting a Merchant Transmission Interconnection request.*

*Note: Only the most severely overloaded conditions are listed below. There is no guarantee of full delivery of energy for this interconnection request by addressing only the conditions listed in this section. With a Transmission Interconnection Request, a subsequent analysis will be performed which shall study all overload conditions associated with the overloaded element(s) identified.*

None

## **Light Load Analysis in 2021**

Not required

## **Affected System Analysis & Mitigation**

### **Duke Energy:**



None

# Attachment 1.

## System Configuration

